



# Energy Market Information Exchange (EMIX) Version 1.0

## Committee Specification Draft 02

28 April 2011

### Specification URIs:

#### This version:

<http://docs.oasis-open.org/emix/emix/v1.0/csd02/emix-v1.0-csd02.doc> (Authoritative)  
<http://docs.oasis-open.org/emix/emix/v1.0/csd02/emix-v1.0-csd02.html>  
<http://docs.oasis-open.org/emix/emix/v1.0/csd02/emix-v1.0-csd02.pdf>

#### Previous version:

<http://docs.oasis-open.org/emix/emix/v1.0/csprd01/emix-v1.0-csprd01.doc> (Authoritative)  
<http://docs.oasis-open.org/emix/emix/v1.0/csprd01/emix-v1.0-csprd01.html>  
<http://docs.oasis-open.org/emix/emix/v1.0/csprd01/emix-v1.0-csprd01.pdf>

#### Latest version:

<http://docs.oasis-open.org/emix/emix/v1.0/emix-v1.0.doc> (Authoritative)  
<http://docs.oasis-open.org/emix/emix/v1.0/emix-v1.0.html>  
<http://docs.oasis-open.org/emix/emix/v1.0/emix-v1.0.pdf>

### Technical Committee:

OASIS Energy Market Information Exchange (EMIX) TC

### Chair(s):

William Cox, Individual  
Edward Cazalet, Individual

### Editor(s):

Toby Considine, University of North Carolina at Chapel Hill

### Related work:

This specification is related to:

- [OASIS Specification WS-Calendar V1.0](#), in process
- [OASIS Specification Energy Interoperation V1.0](#), in process
- XML schema(s): [emix/v1.0/csd02/xsd/](#)

### Declared XML namespace(s):

<http://docs.oasis-open.org/ns/emix>  
<http://docs.oasis-open.org/ns/emix/power>  
<http://docs.oasis-open.org/ns/emix/power/resource>

### Abstract:

The data models and XML vocabularies defined by this TC will address issues in energy markets and the Smart Grid, but are defined so as to support requirements for other markets. The TC will develop an information model and XML vocabulary to exchange prices and product definitions for transactive energy markets.

- Price information
- Bid information
- Time for use or availability
- Units and quantity to be traded
- Characteristics of what is traded

The definition of a price and of other market information exchanged depends on the market context in which it exists. It is not in scope for this TC to define specifications for markets, nor how prices are determined, nor the mechanisms for interoperation.

**Status:**

This document was last revised or approved by the OASIS Energy Market Information Exchange (EMIX) TC on the above date. The level of approval is also listed above. Check the “Latest Version” location noted above for possible later revisions of this document.

Technical Committee members should send comments on this specification to the Technical Committee’s email list. Others should send comments to the Technical Committee by using the “[Send A Comment](#)” button on the Technical Committee’s web page at <http://www.oasis-open.org/committees/emix/>.

For information on whether any patents have been disclosed that may be essential to implementing this specification, and any offers of patent licensing terms, please refer to the Intellectual Property Rights section of the Technical Committee web page (<http://www.oasis-open.org/committees/emix/ipr.php>).

**Citation format:**

When referencing this specification the following citation format should be used:

**[EMIX-v1.0]**

Energy Market Information Exchange (EMIX) Version 1.0. 28 April, 2011. OASIS Committee Specification Draft 02. <http://docs.oasis-open.org/emix/emix/v1.0/csd02/emix-v1.0-csd02.doc>

---

## Notices

Copyright © OASIS Open 2011. All Rights Reserved.

All capitalized terms in the following text have the meanings assigned to them in the OASIS Intellectual Property Rights Policy (the "OASIS IPR Policy"). The full [Policy](#) may be found at the OASIS website.

This document and translations of it may be copied and furnished to others, and derivative works that comment on or otherwise explain it or assist in its implementation may be prepared, copied, published, and distributed, in whole or in part, without restriction of any kind, provided that the above copyright notice and this section are included on all such copies and derivative works. However, this document itself may not be modified in any way, including by removing the copyright notice or references to OASIS, except as needed for the purpose of developing any document or deliverable produced by an OASIS Technical Committee (in which case the rules applicable to copyrights, as set forth in the OASIS IPR Policy, must be followed) or as required to translate it into languages other than English.

The limited permissions granted above are perpetual and will not be revoked by OASIS or its successors or assigns.

This document and the information contained herein is provided on an "AS IS" basis and OASIS DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY OWNERSHIP RIGHTS OR ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

OASIS requests that any OASIS Party or any other party that believes it has patent claims that would necessarily be infringed by implementations of this OASIS Committee Specification or OASIS Standard, to notify OASIS TC Administrator and provide an indication of its willingness to grant patent licenses to such patent claims in a manner consistent with the IPR Mode of the OASIS Technical Committee that produced this specification.

OASIS invites any party to contact the OASIS TC Administrator if it is aware of a claim of ownership of any patent claims that would necessarily be infringed by implementations of this specification by a patent holder that is not willing to provide a license to such patent claims in a manner consistent with the IPR Mode of the OASIS Technical Committee that produced this specification. OASIS may include such claims on its website, but disclaims any obligation to do so.

OASIS takes no position regarding the validity or scope of any intellectual property or other rights that might be claimed to pertain to the implementation or use of the technology described in this document or the extent to which any license under such rights might or might not be available; neither does it represent that it has made any effort to identify any such rights. Information on OASIS' procedures with respect to rights in any document or deliverable produced by an OASIS Technical Committee can be found on the OASIS website. Copies of claims of rights made available for publication and any assurances of licenses to be made available, or the result of an attempt made to obtain a general license or permission for the use of such proprietary rights by implementers or users of this OASIS Committee Specification or OASIS Standard, can be obtained from the OASIS TC Administrator. OASIS makes no representation that any information or list of intellectual property rights will at any time be complete, or that any claims in such list are, in fact, Essential Claims.

The names "OASIS" and "EMIX" are trademarks of [OASIS](#), the owner and developer of this specification, and should be used only to refer to the organization and its official outputs. OASIS welcomes reference to, and implementation and use of, specifications, while reserving the right to enforce its marks against misleading uses. Please see <http://www.oasis-open.org/who/trademark.php> for above guidance.

---

# Table of Contents

1	Introduction.....	9
1.1	Terminology.....	9
1.2	Process.....	9
1.3	Normative References.....	10
1.4	Non-Normative References.....	10
1.5	Namespace.....	11
1.6	Naming Conventions.....	11
1.7	Editing Conventions.....	11
1.8	Semantics from WS-Calendar.....	12
1.9	Market Semantics.....	12
1.10	Security Approaches.....	12
2	Overview.....	13
2.1	Introduction.....	13
2.2	Approach.....	13
2.3	Information Structure.....	14
2.4	EMIX Time and Schedules.....	15
2.5	Tenders and Transactions for Power Products and Resource Capabilities.....	15
2.6	Transport.....	15
2.7	Verification.....	16
3	Guide to the Schema Structures.....	17
3.1	Core Extension Elements.....	17
3.2	Extensibility.....	18
3.3	Power and Resource Schemas.....	18
4	Overview of the Information Elements.....	19
4.1	The Intrinsic Elements: EMIX Products.....	19
4.1.1	Intrinsic Elements of the EMIX Product Type.....	20
4.1.2	Intrinsic Elements of the EMIX Option.....	21
4.1.3	Intrinsic Elements of the TeMIX.....	23
4.1.4	Intrinsic Elements of Delivery.....	24
4.1.5	Other Envelopes and Information Elements.....	24
4.2	Transactive States.....	24
4.3	Inside the Envelope – the Extrinsic Items.....	25
4.4	Summary of the EMIX Base Derivations.....	26
5	Constraints and Market Requirements.....	27
5.1	EMIX Constraints.....	27
5.2	Market Requirements.....	28
6	Interfaces and Items – Components for Constructing Product Descriptions.....	29
6.1	EMIX Interfaces.....	29
6.2	Item Base.....	29
6.2.1	Example of use of Item Base.....	29
7	The Schedule in the EMIX Product: Gluons and Intervals.....	31
7.1	The EMIX Gluon.....	31

7.2	The EMIX Sequence and Intervals .....	32
7.3	EMIX Product Model .....	32
8	EMIX Power Product Descriptions .....	34
8.1	Power Product Descriptions .....	34
8.2	Resource Offer Descriptions.....	34
8.3	Transport Product Descriptions .....	34
9	Power Product Descriptions .....	35
9.1	Base Power Contract.....	36
9.2	Full Requirements Power .....	37
9.3	Block Power Full Requirements .....	37
9.4	TEMIX Power Product .....	39
9.5	Power Product Charges.....	40
9.6	Enumerated Power Product Types.....	40
10	Energy Resources .....	42
10.1	Resource Capabilities .....	42
10.2	Resource Description Semantics .....	44
10.3	Generic Power Resource.....	45
10.3.1	Offer Curves .....	46
10.4	Reactive Power Resources .....	46
10.5	Summary of Resource Types .....	47
11	Transactive Energy (TeMIX) Products .....	48
12	Ancillary Services .....	51
13	Power Quality .....	52
13.1	Electrical Power Quality.....	52
14	Power Transport Product Descriptions.....	53
15	EMIX Warrants .....	54
15.1	Warrant List Definition .....	54
16	Conformance and Rules for EMIX and Referencing Specifications.....	55
16.1	EMIX Conformance with WS-Calendar .....	55
16.1.1	Inheritance in EMIX Base.....	55
16.1.2	Specific Attribute Inheritance in EMIX.....	56
16.2	Miscellaneous Business Rules not yet dealt with.....	56
A.	Acknowledgements .....	57
B.	Extensibility and EMIX.....	58
B.1	Extensibility in Enumerated values .....	58
B.2	Extension of Structured Information Collective Items .....	59
C.	Semantics from WS-Calendar .....	61
D.	Electrical Power and Energy .....	64
E.	Mapping between NAESB PAP03 work and this specification .....	65
F.	Schemas (Non-Normative).....	66
F.1	EMIX Schemas.....	66
F.1.1	EMIX.XSD .....	66
F.1.2	EMIX-Requirements .....	73
F.1.3	EMIX Warrants.....	80

F.2 Power Schemas .....	82
F.2.1 Power.xsd.....	83
F.2.2 Power Quality .....	89
F.2.3 Power Products.xsd .....	93
F.3 Resource.xsd.....	98
G. An Example .....	106
H. Revision History.....	118

---

# Tables, Figures & Examples

## Index to Figures

Figure 4-1: EMIX Base Type.....	19
Figure 4-2: EMIX Product Type.....	20
Figure 4-3: EMIX Option Type .....	21
Figure 4-4: The TEMIX Product .....	23
Figure 4-5: Delivery.....	24
Figure 4-6: Envelope Contents .....	25
Figure 4-7: UML of EMIX Base and its Extensions.....	26
Figure 6-1: UML showing use of Item Base in Energy Types.....	30
Figure 7-1: EMIX Model .....	32
Figure 9-1: Base Power Product.....	36
Figure 9-2 Block Power Full Requirements .....	38
Figure 9-3: TeMIX Power .....	39
Figure 10-1: Attributes of a Generic Resource .....	42
Figure 10-2: Equivalence of Load Shed and Generation.....	43
Figure 10-3: Combining Response Capabilities .....	43
Figure 10-4: Ramp Rate Curve—CIM Style.....	44
Figure 10-5: Resource Description base .....	44
Figure 10-6: UML Summary of Resource Types .....	47

---

## Index to Tables

Table 3-1: EMIX Schemas .....	17
Table 4-1: Elements of the EMIX Product.....	20
Table 4-2: Option Elements – another "Face of the Envelope" .....	21
Table 4-3: Elements of the TeMIX .....	23
Table 4-4: Elements of the EMIX Delivery .....	24
Table 4-5: Transactive States Enumeration.....	24
Table 5-1: Constraints .....	27
Table 5-2: Market Requirements for EMIX Products .....	28
Table 7-1: EMIX Base Product – the Gluon.....	31
Table 7-2: EMIX Base Product - the Interval .....	32
Table 9-1: Semantic Elements common to Multiple Power Products .....	35
Table 9-2: Base Power Product Description .....	36
Table 9-3: Full Requirements Power Product Description.....	37
Table 9-4: Block Power Full Requirements.....	38
Table 9-5: TEMIX Power Product Description .....	39

Table 9-6: Elements of Power Demand Charges .....	40
Table 9-7: Requirements Power Products .....	40
Table 10-1: Resource Description Elements .....	45
Table 10-2: Constraints unique to Power Resources .....	45
Table 10-3: Generic Power Response Resource .....	45
Table 10-4: Power Ramp .....	46
Table 10-5: Resource Offer Segment .....	46
Table 10-6 Semantics for Voltage Regulation Services .....	46
Table 11-1: TeMIX Power Product Description.....	49
Table 11-2: TeMIX Power Option Product Description .....	49
Table 13-1: AC Power Quality.....	52
Table 14-1: Transport Description .....	53
Table 15-1: Warrant Types .....	54
Table C-16-1: WS-Calendar Foundational Semantics.....	61
Table C-16-2: WS-Calendar Semantics of Inheritance.....	61
Table 16-3: WS-Calendar Semantics of Information Processing .....	62

---

# 1 Introduction

This document defines an information model to exchange Price and Product information for power and energy markets. Product definition includes quantity and quality of supply as well as attributes of interest to consumers distinguishing between power and energy sources. Energy Market Information Exchange (EMIX) is not intended as a stand-alone signal; rather, it is anticipated to be used for information exchange in a variety of market-oriented interactions.

The EMIX Technical Committee (TC) is developing this specification in support of the US Department of Commerce National Institute of Standards and Technology (NIST) NIST Framework and Roadmap for Smart Grid Interoperability Standards [**NIST**] and in support of the US Department of Energy (DOE) as described in the Energy Independence and Security Act of 2007 (EISA 2007) [**EISA**].

This specification defines the following:

- The characteristics of power and energy that along with price define a product
- An [**XML Schema**] for Price and Product definition for products whose value varies with time of delivery.
- An [**XML Schema**] for Price and Product definition for Power-related products and services.
- An [**XML Schema**] describing the capabilities of resources that are being offered to the market.

Key to reading the document:

- **BOLD** terms are the names of referenced standards
- *Italic phrases* are quotes from external material.
- [**bracketed**] are references to the standards listed in listed in the normative or non-normative sections references sections.
- All examples and all Appendices are non-normative.

## 1.1 Terminology

The key words “MUST”, “MUST NOT”, “REQUIRED”, “SHALL”, “SHALL NOT”, “SHOULD”, “SHOULD NOT”, “RECOMMENDED”, “MAY”, and “OPTIONAL” in this document are to be interpreted as described in [**RFC2119**].

## 1.2 Process

This information exchange was developed primarily by integrating requirements and use cases for Price and Product definition developed by the North American Energy Standards Board (NAESB) as part of its response to NIST Priority Action Plan 03 (PAP03), “Develop Common Specification for Price and Product Definition” [**PAP03**], which was driven by NIST, Federal Energy Regulatory Commission (FERC), and DOE priority items.

Where appropriate, semantic elements from the International Electrotechnical Commission (IEC) Technical Committee (TC) 57 Power systems management and associated information exchange Common Information Model (CIM) are used [**IEC**]. Business and market information was borrowed from the financial instruments Common Information Models as described in International Standards Organization (ISO) [**ISO20022**] standard and in the financial trading protocol, [**FIX**] (Financial Information eXchange).

Both the supply and the use of energy products, and therefore the market value, are time dependent, so precise communication of time of delivery is a significant component of product definition. EMIX incorporates schedule and interval communication interfaces from Web Services Calendar ([**IWS-Calendar**]) to communicate schedule-related information.

43 Additional guidance was drawn from subject matter experts familiar with the design and implementation of  
44 enterprise and other systems that may interact with smart grids.

### 45 1.3 Normative References

- 46 **RFC2119** S. Bradner, *Key words for use in RFCs to Indicate Requirement Levels*,  
47 <http://www.ietf.org/rfc/rfc2119.txt>, IETF RFC 2119, March 1997.
- 48 **CEFACT** United Nations Centre for Trade Facilitation and Electronic Business, Currency  
49 codes, ISO 4217 3A - Code List Schema Module  
50 [http://www.unece.org/unecefact/codelist/standard/ISO\\_ISO3AlphaCurrencyCode\\_20100407.xsd](http://www.unece.org/unecefact/codelist/standard/ISO_ISO3AlphaCurrencyCode_20100407.xsd)
- 51 **GML** L van den Brink, C Portele, P. Vretanos *Geography Markup Language (GML)*  
52 *simple features profile*, OpenGIS® Implementation Standard, GML 3.2 Profile,  
53 Version 2.0, October 2010, <http://schemas.opengis.net/gml/3.2.1/gml.xsd>
- 54 **SOA-RM** M MacKenzie, K Laskey, F McCabe, P Brown, R Metz, *OASIS Reference Model*  
55 *for Service Oriented Architecture 1.0*, October 2006 [http://docs.oasis-](http://docs.oasis-open.org/soa-rm/v1.0/)  
56 [open.org/soa-rm/v1.0/](http://docs.oasis-open.org/soa-rm/v1.0/)
- 57 **UML** *Unified Modeling Language (UML), Version 2.2*, Object Management Group,  
58 February, 2009, <http://www.omg.org/spec/UML/2.2/>
- 59 **URI** T. Berners-Lee, R. Fielding, L. Masinter, *Uniform Resource Identifier (URI):*  
60 *Generic Syntax*, <http://www.ietf.org/rfc/rfc3986.txt>, January 2005
- 61 **WS-Calendar** T. Considine, M. Douglas, *OASIS WS-Calendar Public Review Draft 02*, April  
62 2011, specification in progress, [http://docs.oasis-open.org/ws-calendar/ws-](http://docs.oasis-open.org/ws-calendar/ws-calendar-spec/v1.0/csprd02/ws-calendar-spec-v1.0-csprd02.pdf)  
63 [calendar-spec/v1.0/csprd02/ws-calendar-spec-v1.0-csprd02.pdf](http://docs.oasis-open.org/ws-calendar/ws-calendar-spec/v1.0/csprd02/ws-calendar-spec-v1.0-csprd02.pdf)
- 64 **XML Schema** H. Thompson, D Beech, M Maloney, N Mendelsohn, *XML Schema Part 1:*  
65 *Structures Second Edition*, <http://www.w3.org/TR/xmlschema-1/> October 2004  
66 PV Biron, A Malhotra, *XML Schema Part 2: Datatypes Second Edition*,  
67 <http://www.w3.org/TR/xmlschema-2/> October 2004.  
68

### 69 1.4 Non-Normative References

- 70 **EISA** Energy Independence and Security Act (EISA 2007)  
71 <http://www.gpo.gov/fdsys/pkg/PLAW-110publ140/content-detail.html>
- 72 **FIX** Financial Information eXchange (FIX) Protocol,  
73 <http://www.fixprotocol.org/specifications/FIX.5.0SP2>
- 74 **IEC TC57** IEC TC 57 Power and Load Management, <http://tc57.iec.ch/index-tc57.html>
- 75 **NIEM** NIEM Technical Architecture Committee (NTAC), *National Information Exchange*  
76 *Model Naming and Design Rules v1.3*, October 2008,  
77 <http://www.niem.gov/pdf/NIEM-NDR-1-3.pdf>
- 78 **TeMIX** Transactional Energy Market Information Exchange [TeMIX] an approved White  
79 Paper of the EMIX TC. Ed Cazalet et al. [http://www.oasis-](http://www.oasis-open.org/committees/download.php/37954/TeMIX-20100523.pdf)  
80 [open.org/committees/download.php/37954/TeMIX-20100523.pdf](http://www.oasis-open.org/committees/download.php/37954/TeMIX-20100523.pdf)
- 81 **NAESB 03** *Requirements Specification for Common Electricity Product and Pricing*  
82 *Definition*, North American Energy Standards Board [NAESB], March, 2010  
83 (Public Review Draft).  
84 [http://naesb.org/pdf4/weq\\_2010\\_ap6a\\_retail\\_2010\\_ap9a\\_rec.doc](http://naesb.org/pdf4/weq_2010_ap6a_retail_2010_ap9a_rec.doc)
- 85 **NIST Roadmap** NIST Framework and Roadmap for Smart Grid Interoperability Standards,  
86 Release 1.0, online.  
87 [http://www.nist.gov/public\\_affairs/releases/upload/smartgrid\\_interoperability\\_final](http://www.nist.gov/public_affairs/releases/upload/smartgrid_interoperability_final.pdf)  
88 [.pdf](http://www.nist.gov/public_affairs/releases/upload/smartgrid_interoperability_final.pdf)
- 89 **PAP03** Details of PAP03 may be found at [http://collaborate.nist.gov/twiki-](http://collaborate.nist.gov/twiki-sggrid/bin/view/SmartGrid/PAP03PriceProduct)  
90 [sggrid/bin/view/SmartGrid/PAP03PriceProduct](http://collaborate.nist.gov/twiki-sggrid/bin/view/SmartGrid/PAP03PriceProduct) (link retrieved 06/23/2010)

91 **RFC5545** B. Desruisseaux *Internet Calendaring and Scheduling Core Object Specification*  
92 (*iCalendar*), <http://www.ietf.org/rfc/rfc5545.txt>, IETF RFC 5545, September 2009.  
93 **White Paper on WS-Calendar** [http://docs.oasis-open.org/ws-  
94 calendar/v1.0/CD01/WS-Calendar-Conceptual-Overview-CD01.pdf](http://docs.oasis-open.org/ws-calendar/ws-)

## 95 1.5 Namespace

96 XML namespaces and prefixes used in this standard:

Prefix	Namespace
<b>emix:</b>	<a href="http://docs.oasis-open.org/ns/emix">http://docs.oasis-open.org/ns/emix</a>
<b>power:</b>	<a href="http://docs.oasis-open.org/ns/emix/power">http://docs.oasis-open.org/ns/emix/power</a>
<b>resource:</b>	<a href="http://docs.oasis-open.org/ns/emix/power/resource">http://docs.oasis-open.org/ns/emix/power/resource</a>
<b>xs</b>	<a href="http://www.w3.org/2001/XMLSchema">http://www.w3.org/2001/XMLSchema</a>
<b>gml:</b>	<a href="http://www.opengis.net/gml/3.2">http://www.opengis.net/gml/3.2</a>
<b>xcal:</b>	urn:ietf:params:xml:ns:icalendar-2.0
<b>clm5ISO42173A:</b>	urn:un:unece:uncefact:codelist:standard:5:ISO42173A:2010-04-07

97 Namespace URIs resolve to a Resource Directory Description Language [RDDL 2.0] document  
98 describing the namespace.

## 99 1.6 Naming Conventions

100 This specification generally follows the follows the National Information Exchange Model [NIEM] naming  
101 and design rules for artifacts defining the specification, as follows:

102 For the names of elements and the names of attributes within XSD files, the names follow the lower  
103 camelCase convention, with all names starting with a lower case letter. For example,

```
104 <element name="componentService" type="emix:ComponentServiceType"/>
```

105 For the names of types within XSD files, the names follow the Upper CamelCase convention with all  
106 names starting with an upper case letter postfixed with "Type". For example,

```
107 <complexType name="ComponentServiceType">
```

## 108 1.7 Editing Conventions

109 For readability, element names in tables appear as separate words. The actual names are  
110 lowerCamelCase, as specified above, and as they appear in the XML schemas.

111 The cardinality of each element can vary by transactive state. For clarity, cardinality for each element is  
112 not indicated in the tables in the specification. Note: because of EMIX Inheritance (see section 16.1), a  
113 :”missing” required element may be supplied through inheritance.

114 Information in the “Specification” column of the tables is normative. Information appearing in the note  
115 column is explanatory and non-normative.

116 All sections explicitly noted as examples are informational and are not to be considered normative.

## 117 **1.8 Semantics from WS-Calendar**

118 Time semantics are critical to EMIX. An overview of EMIX semantics is in Appendix C for easy reference.  
119 Practitioners should read that specification or the [**White Paper on WS-Calendar**].

## 120 **1.9 Market Semantics**

121 Different energy markets have specific market terms and interaction patterns. This specification endorses  
122 none of them, but still needs to discuss the various stages of a market transaction. Without mandating the  
123 terminology used in any particular market, the EMIX specification uses the common market terms as  
124 defined in *Table 4-5: Transactive States Enumeration*.

125 You may want to turn ahead to have these definitions in mind as you read this document.

## 126 **1.10 Security Approaches**

127 EMIX is an information model, and thus security per se is out of scope for this specification. EMIX will  
128 normally be conveyed in messages as part of business processes. Each business process will have its  
129 own security needs, including different consequences for failure of security.

---

## 130 2 Overview

### 131 2.1 Introduction

132 Energy markets have been characterized by tariffs and embedded knowledge that make decision  
133 automation difficult. Different market segments use conflicting terms for similar attributes. Smart grids  
134 introduce rapidly changing products and product availability, with associated dynamic prices. A lack of a  
135 widely understood model conveying market information has been a barrier to development and  
136 deployment of technology to respond to changing market circumstances.

137 Price and product definition are *actionable information*. When presented with standard messages  
138 conveying price and product, automated systems can make decisions to optimize energy and economic  
139 results. In regulated electricity markets, price and products often are defined by complex tariffs, derived  
140 through not strictly economic processes. These tariffs convey the price and product information to make  
141 buying and selling decisions easier. The same information can be derived from market operations in non-  
142 tariffed markets. EMIX defines the information for use in messages that convey this actionable  
143 information.

144 An essential distinction between energy and other markets is that price is strongly influenced by time of  
145 delivery. Energy for sale at 2:00 AM, when energy use is low, is not the same product as energy for sale  
146 at the same location at 2:00 PM, during the working day. EMIX conveys time and interval by incorporating  
147 WS-Calendar into tenders, transactions, and performance calls.

148 Not all market information is available in real time. Present day markets, particularly wholesale markets,  
149 may have deferred charges (e.g. balancing charges) that cannot be determined at point of sale. Other  
150 markets may require additional purchases to allow the use of the energy purchased (e.g. same-time  
151 transmission rights or pipeline fees when accepting delivery on a forward contract). EMIX is useful for  
152 representing available price and product information.

### 153 2.2 Approach

154 The EMIX TC has prepared a white paper which provides a context for discussing the use of transactions  
155 in retail and wholesale energy markets. The Transactional Energy Market Information Exchange (**TeMIX**)  
156 white paper can be found in the non-normative references.

157 Transactive Energy Market Information Exchange (TeMIX) was developed as a specialization of work  
158 within the EMIX TC to address retail and wholesale transactions using approaches common in energy  
159 wholesale and financial transactions. The Energy Interoperation TC defines a TeMIX profile which is a  
160 subset of the EMIX information model and the Energy Interoperation TC services.

161 The TeMIX profile allows only specific tenders and transactions for block power on defined intervals of  
162 time. Tenders may be offered by any party to any other party, as market rules and regulations may allow.  
163 Any party can be a buyer, seller or both. Transactions may include call and put options. TeMIX Options  
164 perform a similar function to demand response contracts or ancillary service contracts where an operator  
165 has dispatch control over the exercise of the option. TeMIX products also include transmission and  
166 distribution (transport) products.

167 TeMIX tenders and transactions can support dynamic tariffs by retail providers to retail customers. TeMIX  
168 is designed for interval metering where delivery can be accurately measured. The simplified information  
169 model and services of the TeMIX profile also support increased automation of transactions using the  
170 computer and communications technology of the smart grid.

171 EMIX has adopted the much of the TeMIX terminology. EMIX supports current operating models of  
172 market operators, utilities, and demand response providers while at the same time supporting the TeMIX  
173 model and future transitions among the models.

174 Power is a commodity whose market value may be different based upon how it is produced or generated.  
175 After production, though, the commodity is commingled with production from other sources with which it is

176 fully fungible. Even so, some energy purchasers distinguish between sources of this product even as they  
177 consume the commingled commodity.

178 Throughout this work, we refer to the intrinsic and extrinsic properties of an energy product. An intrinsic  
179 property is one “*belonging to a thing by its very nature.*” An extrinsic property is one “*not forming an*  
180 *essential part of a thing or arising or originating from the outside.*” In EMIX, the term intrinsic properties  
181 refers to those that can be measured and / or verified at the point of delivery, i.e., electric power and  
182 price. The term extrinsic properties refers to those that can only be known with prior knowledge, such as  
183 the carbon cost, the energy source, or the sulfate load from generation.

184 EMIX artifacts communicate both intrinsic and extrinsic properties; extrinsic properties must be able to  
185 clear in the market just as do intrinsic properties.

186 EMIX is not concerned with the processes whereby an actor provides the products and resources it  
187 describes. EMIX is an information model that assumes conveyance within a service-based environment.  
188 As defined in the OASIS Reference Model for Service Oriented Architecture 1.0 [SOA-RM], service  
189 requests access the capability of a remote system.

190 *The purpose of using a capability is to realize one or more real world effects. At its core, an*  
191 *interaction is “an act” as opposed to “an object” and the result of an interaction is an effect (or a*  
192 *set/series of effects). This effect may be the return of information or the change in the state of*  
193 *entities (known or unknown) that are involved in the interaction.*

194 *We are careful to distinguish between public actions and private actions; private actions are*  
195 *inherently unknowable by other parties. On the other hand, public actions result in changes to the*  
196 *state that is shared between at least those involved in the current execution context and possibly*  
197 *shared by others. Real world effects are, then, couched in terms of changes to this shared state*

198 A request for the delivery of a product is a request for specific real world effects. For EMIX, these effects  
199 are expected to occur during a given period. Consider two sellers that offer the same product. One must  
200 start planning an hour or more in advance. The second may be able to deliver the product in five minutes.  
201 The service start time is the time when product delivery begins. Because this service start time and  
202 service period are all that matters, different providers using quite different technologies can provide  
203 equivalent product as specified in EMIX.

204 Time semantics are critical to EMIX. EMIX uses semantics from [WS-Calendar] to describe time,  
205 duration, and schedule. WS-Calendar also defines an information model wherein services or products  
206 that vary over time can be efficiently and unambiguously communicated using inheritance. Lastly, WS-  
207 Calendar describes an approach wherein an incompletely specified sequence of information can be  
208 completed using minimal re-definition and remote invocation. EMIX uses these semantic and  
209 conformance rules throughout this specification.

## 210 2.3 Information Structure

211 As a conceptual aid, we discuss the information structure using the metaphor of an *envelope containing*  
212 *warrants*. The intrinsic properties and the price are on the face of the envelope, easy to read by all. The  
213 contents of the envelope are the supporting information and various warrants about the extrinsic qualities.

214 On the face of the envelope, EMIX lists the intrinsic qualities of the energy product. In the simplest model,  
215 the intrinsic qualities are limited to the price and the information a meter can provide. In a market of  
216 homogenous energy sources and commodity energy, only the intrinsic qualities are actionable. In postal  
217 handling, information on the face is meant for high-speed automated processing. The simplest devices,  
218 including the proverbial smart toaster, may understand only the intrinsic qualities. The phrase “prices to  
219 devices” is used in energy policy discussions to describe a market model in which energy use decisions  
220 are distributed to each device that uses energy. Under this model, decisions about whether to use energy  
221 now or delay energy use until later are best made where the value is received for that energy use, the  
222 end device. The smart toaster is shorthand for the smallest, least capable device that can receive such a  
223 message. The Committee anticipates that the information on the face of the envelope will be sufficient for  
224 many if not most energy decisions.

225 The envelope contents are the supporting documents that explain and support the price for the intrinsic  
226 qualities on the face of the envelope. These extrinsic qualities are separable from the intrinsic transaction

227 and perhaps can be traded in secondary markets. The contents can include Warrants about the source  
228 and the environmental attributes which provide information about the energy, but they are not the energy.  
229 The extrinsic qualities enable traceability and auditing, increasing public trust in energy markets and on  
230 energy differentiation. The simplest gateways and devices may ignore the warrants, that is, they can  
231 forward or process messages without opening the envelope.

232 Extrinsic information conveyed within the envelope includes supporting information. For example, a  
233 purchaser may opt to buy energy from a particular supplier with advertised rates. Transport loss may  
234 reduce the quantity delivered. Markets may add congestion charges along the way. Such supporting  
235 information can explain why the delivered cost, on the face of the envelope, is different than the purchase  
236 cost.

## 237 **2.4 EMIX Time and Schedules**

238 Time is an important component of energy products. An energy product produced in one Interval of time  
239 may or may not be able to be stored for delivery at a later Interval of time. Thus the same product in  
240 different Intervals of time may have different prices. EMIX uses **[WS-Calendar]** to apply prices and  
241 products to time Intervals.

242 WS-Calendar defines a mechanism to apply a schedule to a Sequence of time Intervals. WS-Calendar  
243 further defines how to use a process analogous to inheritance to apply a single information artifact to  
244 each Interval in the Sequence, allowing elements of that artifact to be over-ridden within any given  
245 Interval. WS-Calendar also defines a schedule entry point, defining how specific performance can be  
246 contracted and scheduled.

247 This document assumes that the reader has a clear understanding of WS-Calendar and its interfaces.  
248 The non-normative white paper on the use of the WS-Calendar specification published by that committee  
249 is a good place to start.

## 250 **2.5 Tenders and Transactions for Power Products and Resource** 251 **Capabilities**

252 The focus of EMIX is on price and product communication in support of commercial transactions. The  
253 messaging and interaction patterns for commercial transactions are out of scope for EMIX but worth a  
254 brief discussion here to provide context.

255 EMIX is intended for commercial transactions in all types of markets including ISO/RTO markets,  
256 exchange markets, regulated markets, regulated retail tariffs, open markets, and wholesale and retail  
257 bilateral markets. The commercial practices that determine prices vary in these markets but all markets  
258 can benefit from interoperable communication of price and product.

259 Transactions in most markets begin with Tenders (offers to buy or sell) by a Party to another Party. Once  
260 an agreement among Parties is reached, the parties Agree to a Transaction (contract or award). The  
261 parties to the Transaction then must perform on the Transaction by arranging for supply, transport,  
262 consumption, settlement and payment. At every stage in this process, clear communication of the terms  
263 (price, quantity, delivery schedule and other attributes) of the tender or transaction is essential. Section 4,  
264 "*Overview of the Information Elements*" describes EMIX Base Type, the core of EMIX information models.

265 In many electricity markets Operators are offered electrical products based on specific resources, i.e.,  
266 generators, load curtailment, and other energy resources. EMIX uses EMIX Resource Descriptions to  
267 describe the responsiveness, capacity, and other aspects of these Resources. EMIX Resource Offers  
268 combine an EMIX Resource Description with a multi-part offer. A Party can use EMIX Resource Offers to  
269 tender to an Operator one or more EMIX Products. Similarly, an EMIX Load Curtailment Offer combines a  
270 Load Curtailment Resource Description with a multi-part offer.

## 271 **2.6 Transport**

272 Product transport costs vary over time. Delivery costs come in two general forms. Congestion charges  
273 apply to each unit of product that passes through a particular point in the distribution system. Congestion

274 charges increase the cost of the Product delivered in a particular Interval. Loss reduces the product  
275 delivered as it passes from the purchase point to the delivery point. Loss may reduce the amount of  
276 product received or a loss charge may be applied to purchase replacement energy for the energy loss.  
277 If the Product is priced for Delivery to the consumer, transport charges may not apply. Product  
278 descriptions for Transport charges are discussed in Section 14, *Power Transport Product Descriptions*.

## 279 **2.7 Verification**

280 Many products, particularly those transacted for Demand Response, are distinguished by particular  
281 Verification Methods. In a pure transactive energy market, the meter would be the only Verification  
282 mechanism. In today's markets, Verification can be more complex.

283 Verification is out of scope for this document. Verification is fully specified under NAESB Business  
284 Practices for Verification. This specification does not describe verification.

## 285 3 Guide to the Schema Structures

286 The EMIX information exchange model defines common structures that can be used to define products  
287 whose value varies with the time of delivery. Because the future of smart energy markets its not known,  
288 there is an emphasis on extensibility and composition to allow EMIX to be suitable for markets known and  
289 unknown, and for easy evolution.

290 The EMIX 1.0 Specification consists of three schemas.

- 291 • The EMIX schema defines the framework and extensibility as well as agreement types common  
292 to many markets.
- 293 • The Power schema defines the specific information exchanges, based on the EMIX framework,  
294 needed for markets in power and energy.
- 295 • The Resource schema defines how load and generation, specific capabilities of devices and  
296 systems to affect power and energy markets, can be described irrespective of the underlying  
297 technologies.

298 Other markets, particularly other products for energy markets, share the characteristic that value is  
299 closely linked to time of delivery. Power and Resource provide examples of extension and conformance  
300 with the EMIX model. Specifications that wish to claim conformance with EMIX use should follow the  
301 same approaches. Information exchanges based on specifications that conform to the EMIX specification,  
302 can be used within any business process or specification that uses or exchanges EMIX payloads.

303 *Table 3-1: EMIX Schemas*

Schema	Definition
<b>EMIX</b>	The EMIX schema has target namespace <a href="http://docs.oasis-open.org/ns/emix">http://docs.oasis-open.org/ns/emix</a> and consists of three files—emix.xsd, emix-requirements.xsd, and emix-warrants.xsd
<b>Power</b>	The Power schema as target namespace <a href="http://docs.oasis-open.org/ns/emix/power">http://docs.oasis-open.org/ns/emix/power</a> consists of three files—power.xsd, power-product.xsd, and power-quality.xsd.
<b>Resource</b>	The Resource schema has target namespace <a href="http://docs.oasis-open.org/ns/emix/power">http://docs.oasis-open.org/ns/emix/power</a> and consists of one file—resource.xsd

304

### 305 3.1 Core Extension Elements

306 The core extension elements are the Product Description Type and the EMIX Base Type. These types  
307 include the abstract types Item (Item Base), and the Interface (EMIX Interface). Almost all of EMIX using  
308 these four abstract types.

309 The abstract Product Description Type is the basis for all static descriptions of EMIX products. Product  
310 Descriptions are static in that they refer to a particular instance in time. Most of the elements in the Power  
311 and Resource schemas are creating Product Descriptions for Power Markets.

312 The abstract EMIX Base Type defines a Product Description Type to a Schedule. That Schedule may be  
313 as simple as a single 5 minute interval on a particular day, or as complex and repeating you can find in  
314 your own personal calendar. Any type derived from the EMIX Base Type can hold any Product  
315 Description. Information elements derived from the EMIX Base include Products, Options, TEMIX, and  
316 Delivery (Metered Information).

317 The Item Base is the basis for the lowest level description of each Product and its aspects. The term Item  
318 is in common business use for that thing on a line of a purchase order, or of a receipt, or on a bill of

319 lading. Item Base derived types have at least a name, a unit of measure, and a scale factor. The Power  
320 schema defines 3 power types and three energy types derived from the Item Base Type.  
321 All product descriptions include the EMIX Interface. The EMIX Interface is where something transfers  
322 ownership for the market. In Power, it can be a node or meter, and aggregation of nodes or meters, a pair  
323 of nodes, or a geographic area. Other specifications can derive from the base type to support their own  
324 needs. Any type derived from the Interface can be used in any of the EMIX Base derived types.

## 325 **3.2 Extensibility**

326 EMIX supports a modular model in which extensions to EMIX can easily be propagated into standards  
327 that communicate EMIX. There are multiple EMIX envelopes to participate in different roles; each  
328 includes a set of EMIX Base Types that describe what is tendered or transacted.

329 New efforts could specify novel Product Descriptions by extending the EMIX Product Description Type.  
330 These new Product Descriptions would define new conformant EMIX Products merely by application the  
331 EMIX Base Type. Such conforming Products could then be transported on any EMIX Envelope. Any  
332 Specification that communicates EMIX Products can exchange market information about these new  
333 Product Descriptions. A new committee can extend EMIX into new products without re-considering any  
334 aspects of the EMIX specification itself.

335 A similar logic applies to the warrants, which outside the scope of this specification. If the warrant  
336 information varies over time, the warrant information can be applied to a WS-Calendar Sequence just as  
337 if it were a Product Description.

338 Extensibility mechanisms supported in EMIX are discussed in Appendix B.

## 339 **3.3 Power and Resource Schemas**


340 The Power and Resource schemas are, in effect, the first extensions to the EMIX Schema. This  
341 specification includes two schemas that extend EMIX. The Power schema extends the EMIX schema to  
342 define products for Power markets. The Resource schema extends the EMIX schema to define the  
343 capabilities of systems in ways that allow market participants to make buying decisions.

344

## 4 Overview of the Information Elements

345 EMIX describes the market communications (EMIX Base type) of tenders and transactions for products  
346 whose market value varies with time of delivery. An energy product typically is delivered over time at a  
347 specific location. Five kW at 2:00 AM does not provide the same energy services as five kW at 2:00 PM.  
348 EMIX describes the terms of tenders and transactions for which time and location are essential  
349 characteristics. For example, the price and quantity (rate of delivery) of energy in each time Interval of a  
350 Sequence of Intervals may vary for energy transactions made in a Sequence of Intervals.

351 EMIX Base derived types are created by applying Product Descriptions to WS-Calendar Sequences. WS-  
352 Calendar Sequences embody the same calendaring standards used by most business and personal  
353 calendaring systems. This enables greater interoperability between grid systems and business and  
354 personal systems. An EMIX Product Description describes the elements of an energy product at a  
355 location for a one Interval or a Sequence of Intervals. An EMIX Product Description for a constant rate of  
356 delivery power product over a single Interval comprises a (1) start time, (2) duration, (3) rate of delivery,  
357 (4) price and (5) location. If the rate of delivery (kW) and price (\$/kWh) have been exchanged in advance,  
358 the information exchanged to deliver the product is simply “start (reference [URI] to product) at 3:00 AM  
359 for 0.75 hours.”



360

361 *Figure 4-1: EMIX Base Type*

362 A Product Description included in each Interval in a Sequence could describe the same elements again  
363 and again. Only a few elements, perhaps only price, or quantity, may change per Interval. EMIX uses the  
364 WS-Calendar Sequence to specify product elements once, and then specifies which elements may vary  
365 by the time Intervals of a Sequence.

366 For example, a resource representing a responsive load may state that 15 minutes lead time is required  
367 between notification and load reduction. This characteristic may hold true whether the response  
368 requested is for a run-time of 10 minutes or for one of 10 hours. EMIX specifies invariant characteristics  
369 as part of a product description or resource, while offering the variable run-time to the market.

370 EMIX Base types using EMIX Product Descriptions applied to WS-Calendar Sequence provide a flexible  
371 information model for describing any energy tender or transaction. New or specialized energy products  
372 can be offered and transacted without changing the EMIX standard.


373 EMIX Base types minimize the size of information exchanged by efficiently describing how information  
374 elements of a tender or a transaction may or may not vary over time. This reduces communication  
375 overhead.

### 376 4.1 The Intrinsic Elements: EMIX Products

377 The following table Table 4-1: Elements of the EMIX Product specifies the Intrinsic Elements in the EMIX  
378 information model. Intrinsic elements make up the face of the envelope. EMIX-based transactions are  
379 based on the exchange of these envelopes. There are four types of envelopes defined in EMIX. These  
380 are Product, Option, TeMIX, and Delivery, each envelope with its own requirements.

381 Central to each is the Base Product Description Type. The Base Product Description Type is the abstract  
 382 class from which all Product Descriptions are derived. A Product is a description of the product or service  
 383 applied to a delivery schedule. Product Descriptions as concrete classes, make up most of the sections  
 384 after this one. However, as no envelope is complete without a Product Description, we define them here.

385 **4.1.1 Intrinsic Elements of the EMIX Product Type**



386  
 387 *Figure 4-2: EMIX Product Type*

388 The EMIX Product is the commonest of the envelopes. It is used for simple tenders, and agreements. It  
 389 describes specific product delivery.


390 *Table 4-1: Elements of the EMIX Product*

Product Element	Definition
<b>UID</b>	Identifier of this artifact. In many (if not most) markets the UID is required to be globally unique.
<b>Transactive State</b>	Used to aid parsing and conformance, e.g., to distinguish between different purposes for EMIX communications See <i>Table 4-5: Transactive States Enumeration</i>
<b>EMIX Product</b>	EMIX Products are created by applying a Product Description to a Schedule using the Base Product abstract class.
<b>Market Context</b>	An identification of the market in which the Product is offered. This may include standard financial and energy exchanges, markets managed by system operators, markets managed by or for aggregators and distributors, or an identification of the microgrid in which the Product is priced
<b>Party Type</b>	Identifies whether information originator is Buyer or Seller
<b>Currency</b>	A code that indicates the currency used, as specified in <b>[CEFACT]</b>

Product Element	Definition
<b>Constraints</b>	A collection of business and performance rules that constrain the option agreement. See Constraints at Section 16
<b>Envelope Contents</b>	As defined in section 4.3 <i>Inside the Envelope – the Extrinsic Items</i>

### 391 4.1.2 Intrinsic Elements of the EMIX Option

392 The EMIX Option is an elaboration of the EMIX Product described above. An option is a financial  
 393 instrument that gives the buyer the right, but not the obligation, to buy or sell a product at a set price  
 394 during given time windows. Many typical energy agreements, including demand response and reserves,  
 395 include elements that would give them the name Option in any other market.



396  
 397 *Figure 4-3: EMIX Option Type*


398 The EMIX option also specifies specific availability and performance. The “face of the envelope” displays  
 399 additional information to support these requirements.

400 *Table 4-2: Option Elements – another “Face of the Envelope”*

Option Element	Specification
----------------	---------------

Option Element	Specification
<b>UID</b>	Identifier of this artifact. In many (if not most) markets the UID is required to be globally unique.
<b>Transactive State</b>	Used to aid parsing and conformance, e.g., to distinguish between different purposes for EMIX communications
<b>EMIX Product</b>	EMIX Products are created by applying a Product Description to a Schedule using the Base Product abstract class.
<b>Market Context</b>	An identification of the market in which the Product is offered. This may include standard financial and energy exchanges, markets managed by system operators, markets managed by or for aggregators and distributors, or an identification of the microgrid in which the Product is priced
<b>Currency</b>	A code that indicates the currency used, as specified in <b>[CEFACT]</b>
<b>Envelope Contents</b>	As defined in section 4.3 <i>Inside the Envelope – the Extrinsic Items</i>
<b>Option Exercise Schedule</b>	Uses the Availability Schedule Constraint to specify the period or periods in which the option is available for exercise. For example, a reserve power option could specify a schedule of afternoons in July excluding the 4 <sup>th</sup>
<b>Option Holder Side</b>	The side which enjoys the benefit of choosing whether or not to exercise the terms specified in the option. Sometimes referred to as the Promisee
<b>Option Premium</b>	The price paid to the Promisor for the rights involved
<b>Option Strike Price</b>	The price at which an option holder (Promisee) has the right to require the option writer (Promisor) to deliver
<b>Exercise Lead Time</b>	The minimum notification time required by the Promisor to be able to perform. Uses the Minimum Notification Duration Constraint. The Promisor is not responsible for performance in less than the Exercise Lead Time.
<b>Strike Price</b>	The price the Promisee will pay the Promisor delivery of Product under the option. May be fixed or relative to a specified market.
<b>Side</b>	Identifies whether information originator is on the Buy or Sell side
<b>Option Type</b>	An enumerated list of Option types
<b>Constraints</b>	A collection of business and performance rules that constrain the option agreement. See Constraints at Section 16

401 **4.1.3 Intrinsic Elements of the TeMIX**



402  
403 *Figure 4-4: The TEMIX Product*


404 The TEMIX (Transactional Energy Market Information Exchange) is a model for balancing energy markets  
405 with pure economic trading. As such, it is the simplest of the EMIX Envelopes.

406 *Table 4-3: Elements of the TeMIX*

TEMIX Element	Specification
<b>UID</b>	Identifier of this artifact. In many (if not most) markets the UID is required to be globally unique.
<b>Transactive State</b>	Used to aid parsing and conformance, e.g., to distinguish between different purposes for EMIX communications See <i>Table 4-5: Transactive States Enumeration</i>
<b>EMIX Product</b>	EMIX Products are created by applying a Product Description to a Schedule using the Base Product abstract class.
<b>Currency</b>	A code that indicates the currency used, as specified in <b>[CEFACT]</b>
<b>Constraints</b>	A collection of business and performance rules that constrain the option transaction. See Constraints at Section 16. The permitted list of constraints for TeMIX is constrained to those discussed in section 11.
<b>Expiration Date</b>	For Tenders only, the date and time when this Tender expires.
<b>Envelope Contents</b>	As defined in section 4.3 <i>Inside the Envelope – the Extrinsic Items</i>

407 See Section 11 for a discussion putting TeMIX products in context.

408 **4.1.4 Intrinsic Elements of Delivery**



409  
 410 *Figure 4-5: Delivery*

411 In any market, order must be matched to delivery. EMIX Delivery reports the historical delivery of product  
 412 over time.

413 *Table 4-4: Elements of the EMIX Delivery*

Delivery Element	Specification
<b>UID</b>	Identifier of this artifact. In many (if not most) markets the UID is required to be globally unique.
<b>EMIX Product</b>	EMIX Products are created by applying a Product Description to a Schedule using the Base Product abstract class.
<b>Injection</b>	True means positive Delivery is injection into the grid. False means positive Delivery is extraction from Grid
<b>Envelope Contents</b>	As defined in section 4.3 <i>Inside the Envelope – the Extrinsic Items</i>

414 **4.1.5 Other Envelopes and Information Elements**

415 EMIX anticipates that further elements will be defined, and an EMIX envelope containing elements not  
 416 defined herein is fully compliant.

417 **4.2 Transactive States**

418 As parties use EMIX to come to an agreement and transact energy, the information required changes. An  
 419 initial offer may not have a price. An agreement may not yet have a performance date. It is necessary for  
 420 both parties in any communication to understand the Transactive State, i.e. what level of agreement  
 421 defines the current communication.


422 *Table 4-5: Transactive States Enumeration*

Transactive State	Description
<b>Indication of Interest</b>	Indication of Interest is a non-binding offer or request for offer for a transaction that may or may not indicate price and quantity and other terms.
<b>Tender</b>	A Tender is a binding offer or bid for a Transaction by a party that when accepted by a counter party will result in a binding Transaction. ISOs use the term Bids to describe offers and bids into their markets.

Transactive State	Description
<b>Transaction</b>	A Transaction between two parties is a binding agreement
<b>Exercise</b>	Exercise applies to two-part Transactions such as Ancillary Services Dispatch by ISOs, Call and Put Options and DR event dispatch that have an initial agreement that includes a second step to that results in another Transaction.
<b>Transport Commitment</b>	Transport Commitment is what the ISOs call "Transmission Scheduling" which is a Transport product and not an energy product transaction. Since the distribution grid may require such transactions or schedules in the future we use the term "Transport"
<b>Delivery</b>	Delivery, which includes both Production and Usage, is the act of actually generating and consuming power that is measured by meters and reported for settlement to the parties. Delivery also names the enumeration of the Delivery.
<b>Publication</b>	Publication is the act of general announcement or posting of appropriate prices and other information concerning products. Publications are not Tenders or Indications of Interest.

423 **4.3 Inside the Envelope – the Extrinsic Items**


424 While energy markets deliver a blended commodity, the customer may value the product differently based  
 425 upon indistinguishable characteristics of the commodity. Often this distinction is based upon the origin of  
 426 the product. The product may come with attached credits that may have re-sale value. The buyer may  
 427 contract for, and the supplier may need to report specific quality of product delivery. In other  
 428 circumstances, it may be necessary to deliver supporting detail to explain the prices delivered.



429  
 430 *Figure 4-6: Envelope Contents*

431 The definition of a warrant is “a written assurance that some product or service will be provided or will  
 432 meet certain specifications”. Sellers use EMIX Warrants to provide information about the source of the  
 433 energy or about its environmental characteristics. Buyers can use warrants to indicate what they wish to  
 434 purchase. It seems a fundamental market rule that a middleman cannot sell more wind power than he has  
 435 bought. Such rules are beyond the scope of EMIX, but EMIX-based information exchanges support such  
 436 market rules.  
 437 EMIX Warrants are assertions about the EMIX Product.

438 **4.4 Summary of the EMIX Base Derivations**



439  
 440 *Figure 4-7: UML of EMIX Base and its Extensions*

441

## 5 Constraints and Market Requirements

442 As noted on each of the elements above, EMIX Products can be subject to a number of Constraints and  
443 Market Requirements. These Constraints and Requirements can apply at each transactive state. Both  
444 Constraints and Requirements are extensible, so additional schemas, specifications, and standards can  
445 extend the lists while remaining in conformance.

446 Neither the EMIX Constraints nor Requirements are tied to any particular kind of Product or Resource  
447 (See section 10 for a discussion of Resources).

### 5.1 EMIX Constraints

449 Constraints are extrinsic to the product delivery but affect how a partner may request performance of a  
450 service. Performance constraints may originate in the basic mechanical needs of the Resource or to the  
451 business needs of the source. These constraints can affect the market value of the resource or the  
452 repeated invocation of a resource. It is possible for a given underlying resource to be offered to the  
453 market with different constraints and therefor different values.

454 *Table 5-1: Constraints*

Constraint	Definition
<b>Minimum Response Duration</b>	The shortest Duration for which the resource will accept a request to maintain a response before returning to pre-request levels.
<b>Maximum Response Duration</b>	The longest Duration for which the resource will accept a request.
<b>Minimum Recovery Duration</b>	The minimum Duration that the Resource requires after the end of a response the resource has is ready to respond to a new request.
<b>Minimum Duration Between Invocations</b>	The minimum Duration that the Resource requires after receiving a request before the resource has is ready to respond to a new request.
<b>Minimum Notification Duration</b>	The minimum Duration that the Resource requires for Notification before initiating a response to a request.
<b>Maximum Notification Duration</b>	The maximum Duration in advance of a response that the Resource will accept a Notification.
<b>Response Time</b>	Duration required from receipt of a request to supplying the requested level of response by the resource
<b>Maximum Invocations Per Duration</b>	Maximum number of invocations of service during a given duration
<b>Maximum Consecutive Durations</b>	Maximum consecutive durations in which service can be invoked, e.g., it will not accept requests on more than 3 consecutive days.
<b>Minimum Starts Per Duration</b>	The fewest Requests that the resource will accept during any duration. This constraint is typically used in market rather than in resource descriptions
<b>Maximum Run Duration</b>	The Maximum duration for which a resource will accept a request
<b>Minimum Run Duration</b>	The Minimum duration for which a resource will accept a request

Constraint	Definition
<b>Availability Schedule</b>	A schedule of time for which a resource will accept requests. The schedule may include multiple availability windows, i.e., an availability in May, can include weekday mornings and Thursday afternoons. The scheduled duration must be entirely within a single instance of an availability window.
<b>Notification Schedule</b>	A schedule of time during which a resource will accept requests. The schedule may include multiple availability windows which may be tied to business process, i.e., must receive notifications between 8:00 and 9:30 on business days. The notification must be received within a notification window.
<b>Unavailability Schedule</b>	A schedule of time during which a resource will accept requests. The schedule may include multiple availability windows, i.e., an availability in May, can include weekday mornings and Thursday afternoons. The scheduled duration must be entirely within a single instance of an availability window.

455 **5.2 Market Requirements**

456 Market Requirements are the market portion of Constraints, i.e., they are used to state the offeror's  
 457 expectations about a tender. It is possible for a given underlying resource to be offered to the market with  
 458 different Requirements and therefore different values.

459 *Table 5-2: Market Requirements for EMIX Products*

Market Requirement	Definition
<b>Minimum Economic Requirement</b>	Minimum net remuneration this resource requires from a total response
<b>Required Startup Cost</b>	Minimum remuneration required from start-up of this service.
<b>Minimum Resource Cost</b>	Resource requires this amount per period, i.e., a minimum requirement for \$100 / hour at whatever rate

460 There is a wide variety of warrant types, issuing authorities, and characteristics described by warrants.  
 461 For bilateral agreements, there may be self-issued warrants. In larger markets, there may be a  
 462 requirement that Warrants be traceable through multiple levels of transactions.  
 463 Warrants are discussed in Section 15.

---

## 464 **6 Interfaces and Items – Components for** 465 **Constructing Product Descriptions**

466 EMIX Product Descriptions applied to business schedules define EMIX Products. The EMIX Products  
467 were defined in section 4.1, including Products, Options, TEMIX, and Delivery. All product descriptions  
468 include an EMIX Interface and one or more elements derived from the EMIX Item Base.

### 469 **6.1 EMIX Interfaces**

470 Every market transaction occurs at an interface, where beneficial rights to or use of a product are  
471 transferred between buyer and seller. This is often the point at which the flow of product is measured  
472 although it may not be.

473 In power Markets, described in the sections below, it can be a node or meter, and aggregation of nodes  
474 or meters, a pair of nodes, or a geographic area. Only the geographic area is defined within the EMIX  
475 schema.

476 Other specifications can derive from the base type to support their own needs. Any type derived from the  
477 Interface can be used in any of the EMIX Base derived Product Descriptions.

### 478 **6.2 Item Base**

479 In common business usage, the item is that thing on each line of the Purchase Order, n each line of the  
480 Invoice, and on each line of the Shipping Document. Common aspects of the item is the name and the  
481 unit of measure. For general use, EMIX also defines the


482 EMIX references the International System of Units (SI) to specify a set of unit prefixes known as SI  
483 prefixes or metric prefixes. An SI prefix is a name that precedes a basic unit of measure to indicate a  
484 decadic multiple or fraction of the unit. The SI prefixes are standardized by the International Bureau of  
485 Weights and Measures (IBWM) in resolutions dating from 1960 to 1991. EMIX enumerates the Si prefixes  
486 in the SiScale enumeration. EMIX requires that conforming specifications use the SiScale to indicate the  
487 size of the unit of measure.

488 The Item Base is used not only to quantify the Item, but potential attributes of the Item as well.

489 Items do not include quantity or precise. The same Item definition may be used in every transactive state,  
490 and prices and quantities are not known for all.

#### 491 **6.2.1 Example of use of Item Base**

492 The Item Base is used in many derived types. This illustration shows the POWER Energy Item Type, from  
493 which Real, Apparent, and Reactive Energy are derived.



494  
495 Figure 6-1: UML showing use of Item Base in Energy Types

496 **7 The Schedule in the EMIX Product: Gluons and**  
 497 **Intervals.**

498 The EMIX Base Product is an abstract class that defines how all Product Descriptions are assembled with  
 499 a schedule to be brought to market. The Base Product also defines an inheritance model whereby a fixed  
 500 description of a product is refined with additional information as it becomes actionable.

501 While a product can be fully defined within an Interval, energy markets often consist of many consecutive  
 502 intervals throughout the day. The intervals can be as short as minutes, or even seconds. A day's worth of  
 503 intervals, each described separately, would consist of much duplicate information. For this reason, it is  
 504 desirable to define product information in the Gluon, and place only those bits of information that change  
 505 over time in each interval. Sometimes, the information in a particular interval takes precedence over the  
 506 inherited information. The rules of inheritance are discussed below in EMIX Conformance with WS-  
 507 Calendar,

508 **7.1 The EMIX Gluon**

509 The Base Product incorporates structures and inheritance patterns from **[WS-Calendar]** that are applied  
 510 to and through the schedule. Table 7-1 and Table 4-1 describe the key elements of the semantics of the  
 511 Base Product. **[WS-Calendar]** defines the Gluon as a way to convey information relating to an entire  
 512 Schedule. Those unfamiliar with WS-Calendar may wish to refer to Appendix C for an overview,

513 *Table 7-1: EMIX Base Product – the Gluon*

Gluon Element	Definition
<b>Product Description</b>	An EMIX ProductDescription describes the energy or services, the location and the price and quantity variables that can be set as a default in the Gluon and inherited by the Intervals in the Sequence. With the possibility of lineage of multiple gluons, product description in the interval, this is not required.
<b>Gluon Duration</b>	A Duration set in a Gluon can be inherited by a Sequence of Intervals, subject to the inheritance rules. Not present in all Gluons.
<b>Gluon Quantity</b>	A Quantity set in a Gluon can be inherited by a Sequence of Intervals, subject to the inheritance rules. Not present in all Gluons.
<b>Gluon Unit Price</b>	A Price set in a Gluon can be inherited by a Sequence of Intervals, subject to the inheritance rules. Not present in all Gluons.
<b>Sequence</b>	A sequence is a set of intervals and the Gluons associated with them. A Gluon influences a Sequence through Inheritance.
<b>Starting Date-Time</b>	A Price set in a Gluon can be inherited by the Designated Interval in the Sequence to define the schedule for all Intervals in the Sequence. Not present in all Gluons
<b>Designated Interval</b>	The Interval in a sequence which has a direct relation with a Gluon (or chain of Gluons).
<b>Availability</b>	When present in a tender, defines when the product is available for delivery.

514 **7.2 The EMIX Sequence and Intervals**


515 **[WS-Calendar]** defines a Sequence is a temporally related set of Intervals. An interval is a period when  
 516 something is done or delivered. Because of the temporal relation, Scheduling one Interval in the  
 517 Sequence schedules them all. For this reason, EMIX Intervals are normally brought to market through  
 518 one or more Gluons, each able to schedule its Sequence.

519 *Table 7-2: EMIX Base Product - the Interval*

Interval Element	Definition
<b>Product</b>	Elements of the Product Description that can be inherited without change from the Gluon need not be expressed in the Interval.
<b>Duration</b>	Can be inherited from the Gluon Lineage. Local expression supersedes inheritance.
<b>Quantity</b>	Can be inherited from the Gluon Lineage. Local expression supersedes inheritance.
<b>Unit Price</b>	Can be inherited from the Gluon Lineage. Local expression supersedes inheritance.
<b>Starting Date-Time</b>	Within a Sequence, is computed from the Starting Date Time of a single member of the Sequence. The Designated Interval can inherit this from the Gluon Lineage. Local expression supersedes inheritance.
<b>Relation</b>	Link from one Interval to other that specifies the relationship in time between Intervals in a Sequence.

520 **7.3 EMIX Product Model**

521 The illustration below provides a model demonstrating a sequence of three intervals, and the successive  
 522 application of Gluons to bring them to market.



523 *Figure 7-1: EMIX Model*

- 525 1. *Power source defines product to market (Sequence and Gluon 1).*
- 526 2. *Product is offered to market on a particular day ([1] and Gluon 2) (Date but not time, required*
- 527 *price specified)*
- 528 3. *Transaction specifies start time (9:00) and duration (6:30) (Gluon 3), inherited by Sequence*
- 529 *through Gluons 2 and 1. Interval B (linked to Gluon 1) is the Interval that starts at 9:00.*

---

## 530 8 EMIX Power Product Descriptions

531 Electrical Energy and must be described precisely as it comes to market. Different products can provide  
532 total power, real power, or reactive power. Products delivering the same Power at a different voltage, or in  
533 DC rather than AC, may be valued differently. For the convenience of the readers, terms associated with  
534 electrical power and energy, and the relationships between them, are reviewed in Appendix E.

535 EMIX Provides a general model for exchanging product and market information about products whose  
536 value is tied closely to the time of delivery. EMIX Power defines specific EMIX Products for Power  
537 delivery. EMIX Resources define capabilities that could be brought market and the performance  
538 characteristics those resources will have, and thus enable a buyer to determine which resources to seek  
539 agreements with.

540 EMIX Products consist of Product Descriptions applied to the EMIX Base Product. The sections ahead  
541 discuss three classes of Product Description:

- 542 1) Power Product Descriptions
- 543 2) Resource Offer Descriptions
- 544 3) Transport Product Descriptions

545 EMIX Electrical Power Products are defined using standard attribute definitions from the Power and Load  
546 Management Common Information Model (CIM). The canonical definitions are in the IEC TC57 CIM.

### 547 8.1 Power Product Descriptions

548 Power can be bought under terms that

- 549 a) Specify the rate of delivery over a duration of an interval. Duration times power = energy
- 550 b) Specify the amount of energy over an interval with no restrictions on the rate of delivery at any  
551 instant within the interval.
- 552 c) Made available as Full Requirements Power (the same as b) except that the amount of energy  
553 transacted is measured after delivery.

554 Power Products are the subject of tenders and transactions, i.e., they are what is actually bought and  
555 sold. Depending upon the market, Power can be bought under terms that specify the energy and its rate  
556 of delivery (power), or made available for use up to the maximum amount deliverable by the in-place  
557 infrastructure (also known as "Full-requirements Power") Power Products in Section 9, *Power Product*  
558 *Descriptions*.

### 559 8.2 Resource Offer Descriptions

560 Resources include generators that can produce power and other services, storage devices that can  
561 consume, store and then produce power, and load that produce a power through load curtailment.

562 A Resource Offer describes both the characteristics of the resource and the prices and quantities of  
563 products and services offered as described in Section 10, *Energy Resources*

### 564 8.3 Transport Product Descriptions

565 Product transport incurs specific costs that vary over time. Transport costs include congestion charges  
566 that apply to each unit of Product that passes through a particular point in the distribution system, and  
567 loss, which reduces the Product delivered. If the Product is priced for Delivery to the consumer, transport  
568 charges may not apply. Product descriptions for Transport charges are discussed in Section 14, *Power*  
569 *Transport Product Descriptions* *Descriptions*.

570

## 9 Power Product Descriptions

571 The information model in this section is described in POWER-PRODUCTS.XSD


572 All Power Products are based on core abstract class, the Power Product Description. The Power  
 573 Products also share core semantic elements, used throughout the Descriptions and their associated  
 574 charges. Not all elements are in all classes; these are the recurring elements.

575 *Table 9-1: Semantic Elements common to Multiple Power Products*

Name	Definition
<b>EMIX Interface</b>	An EMIX Interface is any of a number of metering points (as defined below), an aggregate point, or a geographic area at which a product exchanges ownership
<b>Attributes</b>	Essential characteristics (Voltage, Hz, AC or DC) of delivered electricity.
<b>Voltage</b>	One of three elements hereafter referred to as the Power Attributes.
<b>Hertz</b>	One of three elements hereafter referred to as the Power Attributes. Always 0 for DC
<b>AC</b>	One of three elements hereafter referred to as the Power Attributes.
<b>Power Units</b>	Enumeration of Power Units, e.g., total power (VA), real power (W), and reactive power (VAR)
<b>Energy Units</b>	Enumeration of Energy Units, e.g., including real energy (Wh), reactive energy, (VARh), and apparent energy (VAh)
<b>Voltage Units</b>	Enumeration of Voltage Units, e.g., MV
<b>VAR Units</b>	Enumeration of volt amperes reactive (var) units, e.g., Kvar
<b>Meter Asset</b>	Identifier for an actual or virtual meter
<b>Node</b>	Grid Location identifier
<b>Price</b>	A fixed price.
<b>Price Multiplier</b>	A multiplier relative to a market. It consists of a multiplier, which could be more or less than 1.0 and of a reference to a market context. PriceMultiplier can also be used to set a price now to match market at a forward period in time
<b>Price Relative</b>	A price to add or subtract from the pre-existing market price. It consists of a price, which could be positive or negative, and of a reference to a market context.

576

577 **9.1 Base Power Contract**



578  
579 *Figure 9-1: Base Power Product*

580 The Base Power Contract is the foundation for all the other Power Contracts. Each of them has the  
581 characteristics of the Base Power Contract plus their own additional elements:

582 *Table 9-2: Base Power Product Description*

Name	Definition
<b>Power Product Type</b>	Enumerated type of Power Product. Used to determine conformance requirements.

Name	Definition
<b>EMIX Interface</b>	An EMIX Interface is any of a number of market exchange points including a point, an aggregate point, or a geographic area at which a product exchanges ownership
<b>Unit Energy Price</b>	Price per Unit of Energy
<b>Power Item</b>	Can indicate Real, Apparent, or Reactive Power
<b>Charges</b>	Charges affect the power product in addition to the cost of the product delivered. Charges are defined below.

583 Each Power Product is applied to the EMIX Base Product before it is fully described. Because each  
584 element can be set for the while Sequence, or applied to individual intervals, each can vary over time.

## 585 9.2 Full Requirements Power

586 Full Requirements Power products are the traditional “all-you-can-eat” electrical contract. Maximum  
587 delivery is limited by the physical infrastructure. Demand Charges may apply. This type of product often  
588 appears in Residential markets.


589 As well as the attributes in the base Power Contract, the Full Requirements Product has:

590 *Table 9-3: Full Requirements Power Product Description*

Name	Definition
<b>Price</b>	EMIX Price is a choice one of a Price, a Price Multiplier, or a Price Relative.
<b>Energy Units</b>	Denominates the units that the Price applies to.
<b>Attributes</b>	Essential characteristics (Voltage, Hz, AC or DC) of delivered electricity.
<b>Maximum Power</b>	Denominates the most power available for transacting during the period.
<b>Minimum Power</b>	Denominates the least power that must be transacted during the Interval. Buyer is responsible for making up the difference if the stated value is not reached.

## 591 9.3 Block Power Full Requirements

592 Block Power Full Requirements products provide for full buyer requirement, but prices the power in  
593 “blocks”. Price is constant within a block, but changes as each block is used during a period. Demand  
594 Charges MAY be included. Often used in retail residential rates.




595  
596 *Figure 9-2 Block Power Full Requirements*

597 As well as the attributes in the base Power Contract, the Block Power Full Requirements Product has  
598 these additional elements:

599 *Table 9-4: Block Power Full Requirements*

Block Power Element	Definition
<b>Block Energy Price</b>	Blocks are sorted in order of Maximum Energy Quantity and price for next block starts when last block is used. Blocks can be confined within an interval to create different tiers at different times of day.
<b>Energy Units</b>	Denominates the units that the Price applies to.
<b>Attributes</b>	For residential, usually 60 Hz, 220V AC
<b>Maximum Power</b>	Denominates the most power available for transacting during the period.
<b>Minimum Power</b>	Denominates the least power that must be transacted during the Interval. Buyer is responsible for making up the difference if the stated value is not reached.

600 **9.4 TEMIX Power Product**



601  
602 *Figure 9-3: TeMIX Power*

603 TEMIX Products are specified by the power (rate of delivery of energy) over an interval. . TEMIX Products  
 604 are obligations in that a TeMIX Product is a commitment by the seller to deliver and the buyer to take the  
 605 power (energy) over the interval., When the interval includes more than one measurement or metering  
 606 interval, the TeMIX product is defined as a constant rate over those metering intervals. An example is the  
 607 sale of 1 MW tomorrow between 3 and 5 PM that may be measured every 15 minutes ( The energy is 1  
 608 MWh ). The power in each 15 minute intervals is 1 MW and the energy in each 15 minute interval is 0.25  
 609 MWh. A position in a TEMIX product may be resold or added to. Depending on local market rules  
 610 differences between the power purchased and the actual delivery may be delivered from or to spot  
 611 markets at spot market prices

612 *Table 9-5: TEMIX Power Product Description*

TEMIX Element	Definition
<b>Power Product Type</b>	Enumerated type of Power Product. Used to determine conformance requirements.
<b>EMIX Interface</b>	An EMIX Interface is any of a number of market exchange points including a point, an aggregate point, or a geographic area at which a product exchanges ownership

TEMIX Element	Definition
<b>Price</b>	Price per Unit of Energy. For TeMIX, this is always the actual price and not an offset.
<b>Energy Item</b>	Total Energy (Power * Time), Real, Apparent, or Reactive, in the block purchase
<b>Power Item</b>	Rate of Delivery of Energy. Can be Real, Apparent, or Reactive Power, and must match type of Energy Item.

613 TeMIX Product-based information exchanges are a little different than those for other products; they are  
614 discussed by themselves in Section 11.

## 615 9.5 Power Product Charges

616 Each of the products above, with the exception of TEMIX, can be subject to one or more Power Market  
617 Charges. All charges are based on the BasePowerCharge abstract interface, meaning markets the define  
618 new charges have the means to define new compliant charges. See the Appendices for a discussion of  
619 extensibility in EMIX.

620 Many of the charges defined are specific to Transport Products, although they can be applied to each of  
621 the Product herein. See Section 14, *Power Transport Product* Descriptions, for a discussion of those  
622 charges.

623 One charge can be applied to each of the Products as above, so is defined here. That charge is the  
624 Demand Charge.

625 *Table 9-6: Elements of Power Demand Charges*

Demand Charge Element	Definition
<b>Demand Charge Units</b>	Units upon which Demand Charges will be computed
<b>Demand Charge Floor</b>	Below this floor, demand charges are not applied
<b>Demand Charge Rate</b>	Incremental charge applied if floor is exceeded.
<b>Measurement Interval</b>	Granularity or Power Use readings. For example the demand charge may be incurred if the Power is above the floor for 5 minutes.
<b>Collection Interval</b>	Period during which power usage is summed for comparison to Demand Floor.
<b>Collection Period</b>	Period during which the Demand Charge applies
<b>Charge Duration</b>	Period during which Demand Charges will be applied after incurred.

## 626 9.6 Enumerated Power Product Types

627 Because different Power Product Descriptions use the same informational elements, and because  
628 different transaction states may not require all elements be present in every exchange, each Power  
629 Product Description includes a Power Contract Type. Different Power Contract Types MAY have different  
630 conformance requirements in different market contexts. The Power Contract Type MAY be extended per  
631 the extensibility rules.

632 The following Power Product Types are enumerated:

633 *Table 9-7: Requirements Power Products*

Power Contract Type	Note
---------------------	------

<b>Power Contract Type</b>	<b>Note</b>
<b>Energy</b>	Used in TeMIX for simple block of Energy agreement
<b>Transport</b>	Used in TeMIX for simple transport agreement
<b>Energy Option</b>	Used in TeMIX for Option to transact simple block of Energy
<b>Transport Option</b>	Used in TeMIX for Option to acquire rights to Transport
<b>Full Requirements Power</b>	Traditional power Product to provide all power used. Often used in retail residential rates. Demand Charges
<b>Full Requirements Power with Demand Charge</b>	Similar to Full Requirements except specific and perhaps recurring charges are incurred for exceeding set limit(s)
<b>Full Requirements Power with Maximum and Minimum</b>	Customer must draw energy at least the minimum rate (power) and no more than the maximum rate during any measurement Interval.
<b>Hourly Day Ahead Pricing</b>	Same Full requirements power but prices potentially change each day.
<b>Ex-Ante Real Time Price</b>	Used to report prices after the fact.
<b>Time of Use Pricing</b>	Similar to Hourly day-ahead pricing but prices may change seasonally and not be at hourly Intervals
<b>Transport Service</b>	Product to acquire Transport including factors for congestion, loss, charges, fees, etc.
<b>Congestion Revenue Rights</b>	Hedge product against future Transport / Congestion costs

634 Power products such as these can be described using the Power Product Descriptions

## 635 10 Energy Resources

636 The information model in this section is described in RESOURCE.XSD

637 Resources describe potential services to offer to others in a smart grid. Resource tenders are either  
638 requesting services or offering services. In a pure transactive market, these tenders might be identical to  
639 the services provided, i.e., they could be fully described using the same language used to transact  
640 execution and performance.


641 Resources often enter or are called to enter the market to meet specific needs. These needs can include  
642 a range of performance requirements; Resources might be able to perform a range of capabilities. These  
643 performance capabilities are described using the information in Resource Offers. Resource Offers are  
644 less specific than a single transactive request, and may thereby present the Resource to more than a  
645 single market.

646 When making a tender for products and services, it is useful to describe the capabilities of a resource, so  
647 the counter party can determine if a resource can meet the requirements. A notice of interest MAY specify  
648 performance expectations. A Resource MAY compare its own capabilities to those requirements before  
649 submitting a bid.

650 Resource Capabilities may describe a ramp rate, or maximum run time, or any number of elements useful  
651 to energy schedulers. A Resource Offer associates offers for power produces with a Resource Capability.

### 652 10.1 Resource Capabilities

653 Resources have capabilities rather than schedules. Resource descriptions describe what could be done,  
654 as distinguished from a transaction in which specific performance is requested or agreed to.




655

656 *Figure 10-1: Attributes of a Generic Resource*

657 In the Resource illustration above, there is some base level of energy, a *status quo ante*. When invoked,  
658 the resource takes some period of time to change to a different level. If the response is binary, then it can  
659 only go up to the maximum response, and that ramp rate takes a fixed time. If a resource is able to  
660 provide several layers of response, then the ramp time also varies. The ramp time can be computed from  
661 the ramp rate and the difference between the base power and the maximum response.

662 As electricity is fungible, a critical key element of power resources is that generation, that is the  
663 production of power, and load shedding, the reduction of power use are similar products with similar  
664 value.

## Equivalence of Load & Generation




665

666 *Figure 10-2: Equivalence of Load Shed and Generation*

667 As shown above, generation and load response are similar and can be described using the same  
 668 language.

669 Many Resources have capabilities that change over the range of response. A generator may have one  
 670 ramp speed until it gets up to half speed, and then another as it goes to full. Load response can have  
 671 similar characteristics. Such resources can be described by combining simple response characteristics.

## Generic 2-Level Resource




672

673 *Figure 10-3: Combining Response Capabilities*

674 Resources as in Figure 10-3 can be communicated as an array of ramp up rates, a maximum power  
 675 offered, and an array of ramp down rates. Between the Base 1 and Maximum 1, expressed in MW, the  
 676 resource can ramp up at Ramp 1 expressed in MW/min. Between the Base 2 and Maximum 2, expressed  
 677 in MW, the resource can ramp up at Ramp 1 expressed in MW/min.

678 With capabilities expressed as above, to capabilities of a Resource can be found by the time indicated  
 679 (moving along the X axis) between Base 1 and wherever the ramp up line passes through desired output  
 680 level.

681 Users of the IEC TC57 CIM express this with a Ramp Rate Curve. Figure 10-4 expresses similar  
 682 information as does Figure 10-3, showing Base1 at 50 MW of power and Maximum 1 at 100 MW with a  
 683 ramp rate of 10 MW/minute. Ramp 2, at 15 MW/minute goes from 100MW to 180 MW.




684  
 685 *Figure 10-4: Ramp Rate Curve—CIM Style*

686 By expressing Resources in terms of capabilities and ramp rates, a potential purchaser can determine if a  
 687 Resource meets his or her needs, tendering a single resource to a variety of purchase scenarios.

688 Picture several Resources each able to generate 10 MW of additional power. One can increase power at  
 689 1 MW/minute, one at 2 MW/minute, one at 5 MW/minute. The latter two each can enter into an  
 690 Agreement to supply 10 MW in 5 minutes. Only the last can Agree to supply an increase of 10 MW within  
 691 2 minutes. All three can Agree to supply an increase of 10 MW within 15 minutes.

692 **10.2 Resource Description Semantics**

693 EMIX Resource Descriptions are an extension of the EMIX Product Description. As an extension of the  
 694 Product Description, resources can be applied inside any EMIX schedule.



695  
 696 *Figure 10-5: Resource Description base*

697 The only aspects of a Resource that matters to the energy market are the effects it can provide, the  
 698 likelihood it will be able adequately to provide what it promises, and the financial incentives required to

699 acquire them. The technology and process control details are many, and new ones may be required for  
 700 each new power technology. Unless the market for the Resource requires direct control, such details are  
 701 irrelevant. The limited semantic set herein is sufficient to describe the capabilities of a Resource.

702 The EMIX Resource Description base consists of:

703 *Table 10-1: Resource Description Elements*

Resource Description Element	Note
<b>MRID</b>	The Multi-part resource id as defined in the [IEC TC57] CIM uniquely identifies each resource.
<b>EMIX Interface</b>	The Interface is where the Resource injects or extracts power. Note: for many transactions, reduced extraction is equivalent to injection.
<b>Constraints</b>	As well as all of the constraints listed for Product performance, Resources have additional constraints, listed below.

704 Power Resources descriptions can use any of the constraints or requirements defined in EMIX. Power  
 705 Resource descriptions can also use additional constraints that are specific to Power:

706 *Table 10-2: Constraints unique to Power Resources*

Power Constraint	Note
<b>Minimum Load</b>	Constraint on Minimum Load that a Resource can maintain
<b>Maximum Power</b>	Constraint on Maximum Power available from a resource
<b>Maximum Energy</b>	Constraint on Maximum Energy available from a resource
<b>Minimum Load Reduction</b>	Constraint on Minimum Load Reduction resource can make

### 707 **10.3 Generic Power Resource**

708 The Generic Power Resource description is used both for generation and for load Resources. The  
 709 common Resource model is as follows:

710 *Table 10-3: Generic Power Response Resource*

Generic Resource Element	Note
<b>Staging Ramp</b>	An array Power Ramp Segments describing a Resource's ability to change level at the initiation of a Response
<b>Minimum Response</b>	The least Response for which this resource will accept a request.
<b>Maximum Response</b>	The greatest Response for which this resource will accept a request
<b>Recovery Ramp</b>	An array Power Ramp Segments describing how a Resource's returns to its original state following a response.

711 A Power Response Description MAY be accompanied by an Offer Curve (*described in section 10.3.1*).

712 Each Ramp consists of zero to many Power Ramp Segments (see figure Figure 10-3: Combining  
 713 Response Capabilities). Each Power Ramp Segment Rate describes a change up or down in  
 714 units/duration, from the Power Quantity of the Begin Ramp to the Power Quantity of the End Ramp. The  
 715 rate of change is assumed to be constant between the Begin Ramp and the End Ramp.

716 Power Ramp Segments consist of the following elements:

Power Ramp Element	Note
<b>Rate</b>	Power Units for the Ramp
<b>Begin Ramp</b>	Power Quantity at the beginning of the Segment
<b>End Ramp</b>	Power Quantity at the end of the Segment
<b>Duration</b>	The time to get between the begin ramp and the end ramp.
<b>Integral Only</b>	If true, one can't stop between the begin and end rates.

718 While Power Ramps are generic, specific instances within derived Resource Descriptions are subject to  
719 different conformance rules.

720 For a Generation Resource, Staging Ramps are processed in order of increasing End Power. The  
721 quantity of End Power MUST be greater than the quantity of the Begin Power for each Ramp in the  
722 Staging Ramp. Recovery Ramps are processed in order of decreasing End Power. The quantity of End  
723 Power MUST be less than the quantity of Begin Power for each Ramp in the Recovery Ramp.

724 For a Load Resource, Staging Ramps are processed in order of decreasing End Power. The quantity of  
725 End Power MUST be less than the quantity of Begin Power for each Ramp in the Staging Ramp.  
726 Recovery Ramps are processed in order of increasing End Power. The quantity of End Power MUST be  
727 greater than the quantity of the Begin Power for each Ramp in the Recovery Ramp.

728 Load Resources and Power Resources are conformed instances of the Generic Power Resource.

### 729 10.3.1 Offer Curves

730 When a Power Resource is offered to the market, it may be accompanied by an Offer Curve. An Offer  
731 Curve is comprised of a number of Offer Segments. An Offer Segment defines the minimum requirements  
732 (as expressed in EMIX Requirements) of the Offeror for each block of response without which the Offeror  
733 will withdraw the Resource from the market.

734 Table 10-5: Resource Offer Segment

Resource Offer Element	Note
<b>Price</b>	Price required for this Segment
<b>Maximum Response</b>	Enumerator for the Power rate at the beginning of this Ramp maximum Power change in this segment
<b>Units</b>	Power Quantity at which the Ramp Ends

735 Because an Offer Curve is always figured in terms of the block size of the response, it is always sorted in  
736 order of increasing response. In many markets, they Offer Curves are then processed as a series of bids.

### 737 10.4 Reactive Power Resources


738 In addition, voltage regulation services have their own semantics.

739 Table 10-6 Semantics for Voltage Regulation Services

Voltage Regulation Element	Note
<b>VMin</b>	VMin is the IEEE 1547 minimum voltage level of 88% of nominal voltage where the PV inverter must disconnect. Also defined as the minimum Reactive Power of the Resource.

Voltage Regulation Element	Note
<b>VMax</b>	VMax is the IEEE 1547 maximum voltage level of 110% of nominal voltage where the PV inverter must disconnect. Also defined as the Maximum reactive power of the Resource
<b>QMax</b>	Qmax is the inverter's current var capability and may be positive (capacitive) or negative (inductive). It is the VA capability left after supporting the W demand.
<b>voltVar</b>	Reactive Power

740 **10.5 Summary of Resource Types**



741  
742 *Figure 10-6: UML Summary of Resource Types*

743

## 11 Transactive Energy (TeMIX) Products

744 TeMIX products use transactive interactions to acquire blocks of power. It emphasizes simple interactions  
745 and requires minimal knowledge of one's trading partner. All TeMIX Products are subscriptions for power  
746 over a single Delivery Interval. Subscriptions impose an obligation on the buyer to purchase and the seller  
747 to deliver a TeMIX Power Product. This simplicity reduces the number of products and interactions.

748 There are only four types of TeMIX Products:

- 749 1. TeMIX Power Product
- 750 2. TeMIX Transport Product
- 751 3. TeMIX Option Power Product
- 752 4. TeMIX Option Transport Product

753 The Transactive States for a TeMIX Product are:

- 754 • Indication of Interest
- 755 • Tender
- 756 • Transaction
- 757 • Delivery
- 758 • Price Publishing

759 A TeMIX Delivery Interval is specified by a Duration and Start Time. When TeMIX Product is specified for  
760 a set of Delivery Intervals, then elements that do not vary by Delivery Interval may be specified in a  
761 Gluon. However each TeMIX Delivery Interval is transacted independently of the others in the set.

762 A TeMIX Power Product defines a subscription for Power (energy = power \* duration) over a Delivery  
763 Interval. The subscribed power of TeMIX Power Product is constant over all measured (metered) intervals  
764 within a TeMIX Delivery Interval.

765 For example, 1 MW of power subscribed for delivery tomorrow for 2-hours between 3 and 5 PM provides  
766 1 MWh of energy over each hour and 2-MWh over the two hours. If delivery is measured every 15-  
767 minutes, then the power subscribed in each 15 minute interval is 1 MW. The energy subscribed in each  
768 15-minute interval is 0.25 MWh. If the energy delivered in each 15-minute interval is greater or less than  
769 0.25 MWh then the balance (positive or negative) will typically be sold or purchased in a subsequent  
770 balancing transaction.

771 The Price of a TeMIX Product is expressed in energy units. For the example above, when the price is \$80  
772 per MWh of energy, the extended price (cost) of 1 MW of Power for 2- hours between 3 and 5 PM is \$160  
773 and the extended price for 1 MW of Power in each 15-minute interval of the 2-hours is \$20.

774 A TeMIX Transport Product is a subscription for Transport (transmission or distribution) to transport a  
775 TeMIX Power Product from one EMIX Interface to another. A TeMIX Transport Product is a subscription  
776 for power transport at a constant rate over the delivery interval.

777 A TeMIX Option Product is a subscription for optionality applied to a TeMIX Power or Transport Product.  
778 A TeMIX Option Product is a subscription that provides the Option Holder a right to instruct the Option  
779 Writer to deliver (call) or take (put) a TeMIX Power or Transport Product up to the subscribed quantity  
780 (rate of delivery) of the Option at a Strike Price.

781 TeMIX Options are either Call or Put Options on TeMIX Power and Transport Products. A TeMIX Option  
782 can be exercised during the Delivery Interval of the Option for any subinterval not smaller than the Option  
783 Interval Granularity.

784 For example a TeMIX Option for 10 MW for a Day and an Option Interval Granularity of 1-hour and an  
785 Option Lead Time of 30 minutes would allow the Holder to exercise the option for any or all hours of the  
786 Day at the Strike Price by giving notice 30 minutes before each hour.

787 The elements of a TeMIX Power and Transport Product are shown in **Error! Reference source not**  
 788 **found..** When the Product Description (from section 9) is applied to the EMIX Base types, the TeMIX  
 789 elements are:

790 *Table 11-1: TeMIX Power Product Description*

TeMIX Element	Definition
<b>Power Product Type</b>	Enumerated type of Power Product. Used to determine conformance requirements.
<b>EMIX Interface</b>	The TeMIX Interface where the transaction occurs. Generally the Interface for a Power Product has one node and the Interface for a Transport Product has two nodes.
<b>Price</b>	Price per Unit of Energy. For TeMIX, this is always the actual price and not an offset.
<b>Start Date and Time</b>	When the Interval begins
<b>Duration</b>	The length of time of the Interval
<b>Price</b>	The Unit Energy Price for the interval. TeMIX does not allow Relative Prices or Price Multipliers.
<b>Energy Item</b>	Total Energy (Power * Time), Real, Apparent, or Reactive, in the block purchase
<b>Power Item</b>	Units for the Rate of Delivery of Energy for the Delivery Interval. Includes Power Attributes.
<b>Power Quantity</b>	Rate of Delivery of Energy for the Delivery Interval.
<b>Transactive State</b>	TeMIX Transactive state is conformed to Indication of Interest, Tender, Transaction, Delivery or Publish.
<b>Currency</b>	Currency for the exchange
<b>Side</b>	Indicates which side of the agreement the information originator is on. Buy or Sell
<b>Expires Date</b>	Date and Time Tender expires. Not present if the Transactive State is anything other than Tender.
<b>Envelope</b>	As defined in Section 4.1.5

791 The TeMIX Option extends the TeMIX Product by adding these additional elements:

792 *Table 11-2: TeMIX Power Option Product Description*

TeMIX Element	Definition
<b>Option Holder</b>	The side (buy or sell side of the option) which enjoys the benefit of choosing whether or not to exercise the option. The other side is the Option Writer
<b>Strike Price</b>	The price at which the Option Holder can require Option Writer to deliver.
<b>Option Lead Time</b>	The Minimum Notification Duration constraint
<b>Option Schedule</b>	The Availability Schedule constraint

TeMIX Element	Definition
<b>Minimum Option Call</b>	The shortest duration for which the Option can be called. Uses the Minimum Run Duration constraint
<b>Granularity</b>	If present, expresses the temporal granularity of requests as a duration. For example, if the Duration is 15 Minutes, the option can be called at 10:00, 10:15, 10:30, or 10:45.

793

---

## 12 Ancillary Services

794 Ancillary Services are typically products provided by a Resource Capability and historically were  
795 contracted to stand by for a request to deliver changes in power to balance the grid on very short notice.  
796 Ancillary services include Regulation Up, Regulation Down, Spinning Reserve, and Non-Spinning  
797 Reserve. These Ancillary services are different from other power products in that they are paid for  
798 availability, whether or not they perform. Of course, they must also perform when called.

799 In general, Ancillary services are a promise to perform, usually within tight constraints, i.e., within five  
800 minutes of notification in one market, or within one minute of notification for another. The promisee pays  
801 for this offer to perform, whether or not the promise is called. When the performance call comes, the  
802 promisor is then paid again, often at a premium over the market rate at the time of the performance call.

803 In EMIX, Reserves are modeled as simple Options using the EMIX Option type, which is one of the EMIX  
804 Base-derived types. Performance expectations are expressed using constraints, which can appear on  
805 either side of a Tender. Strike prices and the penalty for non-performance are part of the option  
806 agreement.

807 Because it is useful to have a short-hand to refer to these services, they are enumerated in the Power  
808 Option Type enumeration which is incorporated into the Power Product Types.

809 The enumerated Power Option Types are: Spinning Reserve, Non Spinning Reserve, Operating Reserve,  
810 and Demand Response. Because the exact definitions vary from market to market, and will continue to  
811 vary over time, EMIX does not define these terms. All definitions and performance requirements SHALL  
812 be expressed through the constraints.

## 813 13 Power Quality

814 The information model in this section is described in POWER-QUALITY.XSD

815 Higher quality power can obtain a market premium. A buyer willing to accept lower quality power may be  
816 able to obtain inexpensive power. Power Qualities must be measurable, discrete, and on a spectrum  
817 allowing the buyers to make choices. They must also be verifiable, measurable by defined protocols, so  
818 performance can be compared to promise.

### 819 13.1 Electrical Power Quality

820 *Table 13-1: AC Power Quality*

Name	Specification
<b>Measurement Protocol</b>	A string containing an identification of the standard or other protocol used to measure power quality
<b>Power Frequency</b>	A floating point number describing the measured Power frequency. Users who wish to describe how the frequency varies over time will need to derive their own measure from the base Powr Quality type.
<b>Supply Voltage Variations</b>	An unsigned integer count of Supply Voltage Variations during the period
<b>Rapid Voltage Changes</b>	An unsigned integer count of Rapid Voltage Change events during the period
<b>Flicker</b>	An unsigned integer count of Flicker events during the period
<b>Supply Voltage Dips</b>	An unsigned integer count of Supply Voltage Dip events during the period
<b>Short Interruptions</b>	An unsigned integer count of Short Interruption events during the period
<b>Long Interruptions</b>	An unsigned integer count of Long Interruption events during the period
<b>Temp Overvoltage</b>	An unsigned integer count of Temporary Overvoltage events during the period
<b>Supply Voltage Imbalance</b>	An unsigned integer count of Supply Voltage Imbalance events during the period. Not meaningful for DC.
<b>Harmonic Voltage</b>	A floating point number for the Harmonic Voltage during the period. For DC, distortion is with respect to a signal of 0 Hz
<b>Mains Voltage</b>	A floating point number Mains [Signaling] Voltage

821

## 822 14 Power Transport Product Descriptions

823 The information model in this section is described in POWER-PRODUCTS.XSD

824 Transport costs affect the delivery of energy in all markets. Today's electrical power markets use different  
825 terms in transmission and delivery, but the underlying elements are the same. Future markets, including  
826 those for microgrids and virtual service providers, may not make the same distinctions between  
827 transmission and distribution as have been made in the past. Distributed Energy Resources (DER) may  
828 create new business models for use of the existing distribution networks.

829 The information model below merges the charges and approaches used in the respective transmission  
830 and distribution networks today. It anticipates that potential source selection markets may result in  
831 passage through multiple networks. The resulting EMIX Base can support either stand-alone transport  
832 products, or price support information conveyed within the Envelope, in support of Locational Marginal  
833 Pricing (LMP).

834 *Table 14-1: Transport Description*

Transport Product Element	Definition
<b>Point of Receipt</b>	Where power enters a network or changes ownership
<b>Point of Delivery</b>	Where power exits a network or changes ownership
<b>Transport Access Fee</b>	Fixed Charge (not dependent on congestion) to access transport system
<b>Transport Congestion Fee</b>	Congestion fee per unit of energy for energy flowing from receipt to delivery point. Can be a positive or negative price.
<b>Marginal Loss Fee</b>	Marginal Loss Fee
<b>Transport Loss Factor</b>	Reduction in amount delivered due to loss during transport. (Loss Factor * purchase amount) = delivered amount
<b>Conversion Loss Factor</b>	Reduction in amount delivered as product voltage is changed or as converted from AC to DC or DC to AC. (Loss Factor * purchase amount = delivered amount)

835 There MAY be multiple instances of the above Artifacts in a single Price instance. For example, in a given  
836 transaction, power may pass through multiple distribution nodes and congestion points.

837 The items listed in the table above are each derived from the base charge type. All other charges,  
838 previously described, are available for inclusion within a Transport Product.

## 839 15 EMIX Warrants

840 The information model in this section is described in EMIX-WARRANTS.XSD

841 Warrants are specific assertions about the extrinsic characteristics of EMIX Products that may affect  
842 market pricing. Warrants are in effect Product artifacts as defined in EMIX. Warrants are extensions of the  
843 Product Descriptions type that are applied the Intervals in a Schedule. There may be zero Intervals in a  
844 Product if the unchanged product description applies to all.

845 The Intervals in a warrant may differ from those of the Product on the outside of the envelope.

846 Some warrants may be applicable only in certain jurisdictions. For example, in today's energy markets  
847 (2011) energy warranted as renewable in the Pacific Northwest can include hydropower. Energy markets  
848 in California exclude hydropower from their definition of renewable power. Credits or mandates for  
849 renewable energy in California are not met by Products warranted as renewable in the Northwest.

850 Some warrants may be separable from the underlying energy. For example, a warrant that energy is  
851 generated by a source that is certified as "green" by an authority, may be issued a "green certificate". In  
852 some markets, such a certificate can be traded separately. The detailed specification of warrants is not  
853 part of version 1.0 of this specification.

### 854 15.1 Warrant List Definition

855 Warrant Types are abstract types defined in this specification for extension and definition elsewhere.  
856 Conforming information exchanges can include schema types derived from these types.

857 *Table 15-1: Warrant Types*

Warrant Type	Note
<b>Product Quality</b>	If during an offer, can be a promise of quality. If during verification, and be actual measurements. If during an indication of interest, might be a minimum standard.
<b>Environmental Warrant</b>	Quantifies the environmental burden created during the generation of the electric power.
<b>Content Warrant</b>	The proportion of the product defined that is from non-fossil fuel sources, including but not limited to "hydroelectric", "nuclear", "solar", and "wind".
<b>Source Warrant</b>	In aggregate may be the same as a Warrant Content
<b>Controllability Warrant</b>	Assertion that a Resource referenced on the face of the envelope can be controlled and/or operated by or to some standard.

858

---

## 859 16 Conformance and Rules for EMIX and Referencing 860 Specifications

861 This section specifies conformance related to the semantic model of EMIX. EMIX is heavily dependent  
862 upon WS-Calendar, and repeatedly incorporates WS-Calendar-based information models.

863 EMIX artifacts can be exchanged at any of several stages of a transaction. Necessarily, a tender must be  
864 able to accept an incomplete information model while a call for execution must fully define the  
865 performance expected. Specifications referencing EMIX SHALL define conformance rules by transaction  
866 type and market context.

867 EMIX Conformance necessarily occurs in two stages. EMIX uses WS-Calendar to communicate similar  
868 intervals that occur over time, each containing an EMIX artifact. Portions of that artifact may be expressed  
869 within the Lineage of the sequence. Applications MUST apply WS-Calendar Inheritance and then EMIX  
870 Inheritance to Compose the information exchange for each interval. Only after Composition, can the  
871 EMIX artifact within each Interval of the Sequence be evaluated for conformance and completeness.

### 872 16.1 EMIX Conformance with WS-Calendar

873 EMIX Base are EMIX Products and Resources instantiated through the schedule model of WS-Calendar.  
874 As such, EMIX Base SHALL follow WS-Calendar Conformance rules. These rules include the following  
875 conformance types

- 876 • Conformance to the **inheritance rules** in WS-Calendar, including the direction of inheritance
- 877 • **Specific attributes** for each type that MUST or MUST NOT be inherited.
- 878 • **Conformance rules** that Referencing Specifications MUST follow
- 879 • Description of **Covarying attributes** with respect to the Reference Specification
- 880 • **Semantic Conformance** for the information within the artifacts exchanged.

881 EMIX Products and Resources also extend the Inheritance patterns of WS-Calendar to include the EMIX  
882 information model. We address each of these in the following sections.

#### 883 16.1.1 Inheritance in EMIX Base

884 In this section we recapitulate the rules that define inheritance including direction in WS-Calendar.

885 **I1: Proximity Rule** Within a given lineage, inheritance is evaluated though each Parent to the Child  
886 before what the Child bequeaths is evaluated.

887 **I2: Direction Rule** Intervals MAY inherit attributes from the nearest gluon subject to the Proximity Rule  
888 and Override Rule, provided those attributes are defined as Inheritable.

889 **I3: Override Rule** If and only if there is no value for a given attribute of a Gluon or Interval, that Gluon or  
890 Interval SHALL inherit the value for that attribute from its nearest Ancestor in conformance to the  
891 Proximity Rule

892 **I4: Comparison Rule** Two Sequences are equivalent if a comparison of the respective Intervals  
893 succeeds as if each Sequence were fully Bound and redundant Gluons are removed.

894 **I5: Designated Interval Inheritance** [To facilitate composition of Sequences] the Designated Interval in  
895 the ultimate Ancestor of a Gluon is the Designated Interval of the composed Sequence. Special  
896 conformance rules for Designated Intervals apply only to the Interval linked from the Designator Gluon.

897 **I6: Start Time Inheritance** When a start time is specified through inheritance, that start time is inherited  
898 only by the Designated Interval; the start time of all other Intervals are computed through the durations

899 and temporal; relationships within the Sequence. The designated Interval is the Interval whose parent is  
900 at the end of the lineage.

## 901 **16.1.2 Specific Attribute Inheritance in EMIX**

902 This section refers to EMIX Products, agreements, and Resources as Artifacts. In general, if an artifact of  
903 a particular type blocks inheritance of a complete artifact of that type down the lineage.

904 If an Artifacts of the same type exist in both the parent and in the child, the prototypical argument can be  
905 discussed two-dimensional tree with branches. Blended inheritance consists of deciding when to graft a  
906 branch onto the root.

907 The root node of parent and the child must match for blended inheritance to occur, that is, the roots must  
908 be of the same type. The exception is if there are no roots the child's Artifact, then the root and all its  
909 branches are inherited by the child.

910 If matching roots are found in both the parent and in the child, then each tree should be navigated to  
911 determine blended inheritance. The child's artifact may be mostly unpopulated. Within any branch in the  
912 child, the first node that is populated blocks all further inheritance on that branch. All nodes deeper in the  
913 Artifact than that populated node, are determined by the child. When a branch is inherited from the child,  
914 it blocks the inheritance of any deeper nodes within that branch.

915 Specific artifacts may declare rules that break this inheritance pattern. As of now, the exceptions are:

916 - There are no exceptions.

917 Inheritance creates a virtual artifact at each level of processing. That virtual artifact is the basis for  
918 inheritance for any child artifact.

919 In EMIX the following attributes **MUST NOT** be inherited

- 920 • UID (Gluons and Intervals)
- 921 • Temporal Relationships

922 Some elements of EMIX are may be **covarying**, meaning that they change together. Such elements are  
923 treated as a single element for inheritance, they are either inherited together or the child keeps its current  
924 values intact. This becomes important if one or more of a covarying set have default values. In that case,  
925 if any are present, then inheritance should deem they are all present, albeit some perhaps in their default  
926 values.

## 927 **16.2 Miscellaneous Business Rules not yet dealt with.**

928 If the first Interval in a series has a price only, all Intervals in the Sequence have a price only and there is  
929 no price in the Product

930 If the first Interval in a series has a quantity only, all Intervals in the Sequence have a quantity only and  
931 there is no quantity in the Product

932 If the first Interval in a series has a price & quantity, all Intervals in the Sequence **MUST** have a Price and  
933 Quantity and there is neither Price not Quantity in the Product

934 All Intervals in a Sequence may be restricted to single service location. What are the rules?

935

936

---

## A. Acknowledgements

937 The following individuals have participated in the creation of this specification and are gratefully  
938 acknowledged:

939 **Participants:**

940 Bruce Bartell, Southern California Edison  
941 Timothy Bennett, Drummond Group Inc.  
942 Edward Cazalet, Individual  
943 Toby Considine, University of North Carolina at Chapel Hill\*  
944 William Cox, Individual  
945 Sean Crimmins, California Independent System Operator  
946 Phil Davis, Schneider Electric  
947 Sharon Dinges, Trane  
948 Pim van der Eijk, Sonnenglanz Consulting  
949 Girish Ghatikar, Lawrence Berkeley National Laboratory  
950 Todd Graves, Microsoft Corporation  
951 Anne Hendry, Individual  
952 David Holmberg, NIST\*  
953 Gale Horst, Electric Power Research Institute (EPRI)  
954 Ali Ipakchi, Open Access Technology International Inc. (OATi)  
955 Perry Krol, TIBCO Software Inc.  
956 Derek Lasalle, JPMorganChase  
957 Jeremy Laundergren, Southern California Edison  
958 Alex Levinson, Lockheed Martin\*  
959 Dirk Mahling, CPower  
960 Scott Neumann, Utility Integration Solutions Inc.  
961 Robert Old, Siemens AG  
962 John Petze, Individual  
963 Donna Pratt, ISO/RTO Council  
964 Ruchi Rajasekhar, Midwest Independent Transmission System Operator, Inc.  
965 Carl Reed, Open Geospatial Consortium, Inc. (OGC)\*  
966 Jeremy Roberts, LonMark International\*  
967 Anno Scholten, Individual  
968 Aaron F. Snyder, EnerNex  
969 Pornsak Songkakul, Siemens AG  
970 Bill Stocker, ISI/RTO Council (IRC)  
971 David Sun, Alstom Power Inc.  
972 Jake Thompson, EnerNOC  
973 Matt Wakefield, Electric Power Research Institute (EPRI)  
974 David Webber, Individual  
975 Leighton Wolffe, Individual  
976 Brian Zink, New York Independent System Operator (NYISO)

---

## 977 B. Extensibility and EMIX

978 Extensibility was a critical design constraint for EMIX. Extensibility allows the EMIX specification to be  
979 used in markets and in interactions that were not represented on the Technical Committee. Formal  
980 extensibility rules also create a set of complaint extensions for incorporation into later versions that are  
981 already compliant.

### 982 B.1 Extensibility in Enumerated values

983 EMIX defines a number of enumerations. Some of these, such as measurements of power, are  
984 predictably stable. Others, such as market contracts or energy sources, may well have new elements  
985 added. In general, these accept any string beginning with "x-" as a legal extension. In particular, these  
986 are defined using the following mechanism in the formal schemas (XSD's).

987 In emix.xsd, the extensibility pattern is defined. This pattern looks like:

```
988 <xs:simpleType name="EMIXExtensionType">  
989   <xs:annotation>  
990     <xs:documentation>Pattern used for extending string enumeration,  
991     where allowed</xs:documentation>  
992   </xs:annotation>  
993   <xs:restriction base="xs:string">  
994     <xs:pattern value="x-\.S.*"/>  
995   </xs:restriction>  
996 </xs:simpleType>
```

997 Non-extensible enumerated types look like this:

```
998 <xs:simpleType name="PowerOptionTypeEnumeratedType">  
999   <xs:annotation>  
1000     <xs:documentation>Power Reserve Options</xs:documentation>  
1001   </xs:annotation>  
1002   <xs:restriction base="xs:string">  
1003     <xs:enumeration value="SpinningReserve"/>  
1004     <xs:enumeration value="NonSpinningReserve"/>  
1005     <xs:enumeration value="OperatingReserve"/>  
1006     <xs:enumeration value="DemandResponse"/>  
1007   </xs:restriction>  
1008 </xs:simpleType>
```

1009 The enumerations used in the specifications look like this.

```
1010 <xs:element name="powerOptionType" type="power:PowerOptionTypeType"/>  
1011 <xs:simpleType name="PowerOptionTypeType">  
1012   <xs:union memberTypes="power:PowerOptionTypeEnumeratedType  
1013   emix:EmixExtensionType"/>  
1014 </xs:simpleType>
```

1015 This pattern has been followed throughout EMIX, allowing any string beginning "X-" to be a legal  
1016 extension numeration for EMIX enumerated strings.

1017 Some extensible enumerated types are planned for extension. For example, the means of measurement  
1018 for power quality are defined specific testing protocols. As of this writing, there are only two testing  
1019 protocols in the specification.

```
1020 <xs:simpleType name="MeasurementProtocolEnumeratedType">  
1021   <xs:restriction base="xs:string">  
1022     <xs:enumeration value="EN 50160"/>  
1023     <xs:enumeration value="IEEE 1549-2009"/>  
1024   </xs:restriction>
```

1025 `</xs:simpleType>`

1026 We anticipate that other protocols will be used. In this case, we use the suffix “EnumeratedType” to allow  
1027 for the possibility of other Measurement Protocols that are not enumerated. Actual compliance, though, is  
1028 based upon the type:

```
1029     <xs:simpleType name="MeasurementProtocolType">  
1030         <xs:union memberTypes="power:MeasurementProtocolEnumeratedType  
1031 emix:EMIXExtensionType"/>  
1032     </xs:simpleType>
```

1033 That is, valid values for the measurement protocol are the enumerated values, and any that match the  
1034 extension pattern “x-”

1035 EMIX defines extensibility for the following values:

- 1036 • [Quality] Measurement Protocol
- 1037 • Contract Type
- 1038 • Option Type
- 1039 • Power Option Type
- 1040 • Resource Type

## 1041 **B.2 Extension of Structured Information Collective Items**

1042 EMIX anticipates adding some information structures that are more complex than simple strings can be  
1043 extended as well. A challenge for these items is that they are more complicated and so require formal  
1044 definition. Formal definitions, expressed as additions to schema, could require changes to the  
1045 specification. Without formal definition, it is difficult for trading partners to agree on valid information  
1046 exchanges.

1047 EMIX uses abstract classes for many information exchanges. For example, trading partners could agree  
1048 on the exchange of larger or smaller lists of quality measures. Many measures of power quality are  
1049 defined in power-quality.xsd. Quality consists of an array of elements that are derived from the abstract  
1050 base quality element.

```
1051 <xs:complexType name="PowerQualityType">  
1052     <xs:annotation>  
1053         <xs:documentation>Power Quality consists of a number of measures,  
1054 based on contract, negotiation, and local regulation. Extend Power Quality to  
1055 incorporate new elements by creating additional elements based on  
1056 PowerQualityBaseType</xs:documentation>  
1057     </xs:annotation>  
1058     <xs:sequence>  
1059         <xs:element name="measurementProtocol"  
1060 type="power:MeasurementProtocolType"/>  
1061         <xs:element name="constraints" type="power:ArrayOfPowerQualities"/>  
1062     </xs:sequence>  
1063 </xs:complexType>
```

1064 A practitioner who wanted to add an additional quality type would need to develop a description and  
1065 instantiation of that type based on the abstract base, similar to that used below. The implementation  
1066 refers to the substitution group:

```
1067 <xs:element name="supplyVoltageVariations"  
1068 type="power:SupplyVoltageVariationsType"  
1069 substitutionGroup="power:basePowerQualityMeasurement"/>
```

1070 and the type extends the abstract base class BasePowerQualityMeasurementType:

```
1071 <xs:complexType name="SupplyVoltageVariationsType" mixed="false">  
1072     <xs:complexContent mixed="false">
```

1073  
1074  
1075  
1076  
1077  
1078  
1079

```
<xs:extension base="power:BasePowerQualityMeasurementType">
  <xs:sequence>
    <xs:element name="count" type="xs:int"/>
  </xs:sequence>
</xs:extension>
</xs:complexContent>
</xs:complexType>
```

1080 The resulting schema, which references the approved EMIX schemas, but does not change them, can  
1081 then be distributed to business partners to validate the resulting information exchanges. The core EMIX  
1082 types, which are used throughout the specifications herein, can be extended this way, including:

- 1083 - **EMIX Base Type:** iCalendar-derived object to host EMIX Product Descriptions
- 1084 - **Product Description Type:** In EMIX, the Product Description is the basis for all Resources and  
1085 Product Descriptions.
- 1086 - **Item Base:** Abstract base class for units for EMIX Product delivery, measurement, and warrants.  
1087 Item does not include Quantity or Price, because a single product description or transaction may  
1088 have multiple quantities or prices associated with a single item.
- 1089 - **EMIX Interface:** Abstract base class for the interfaces for EMIX Product delivery, measurement,  
1090 and/or pricing.

1091 The following additional abstract types are among those designed with extension by practitioners in mind:

- 1092 - **BasePowerQualityMeasurementType:** the basis for exchanging measurements of power quality
- 1093 - **BaseConstraintType:** used to express constraints on the performance of equipment exposed to  
1094 the market as Resources
- 1095 - **BaseRequirementType:** used to express the market or business requirements of a trading  
1096 partner.
- 1097 - **BaseWarrantType:** the root for all warrants delivered with the energy product.

1098

## C. Semantics from WS-Calendar

1099 Certain terms appear throughout this document that are defined in **[WS-Calendar]**. This section provides  
 1100 summary definitions for the convenience of the reader and reviewer. Nothing in this table replaces or  
 1101 over-rides the normative definitions in that specification.

1102 *Table C-16-1: WS-Calendar Foundational Semantics*

Time Segment	Definition
<b>Duration</b>	Duration is the length of an event scheduled using iCalendar or any of its derivatives.
<b>Interval</b>	The Interval is the core component of duration and sequence. Parties make Agreements for delivery of EMIX-described products during an Interval.
<b>Sequence</b>	A Sequence is a set of Intervals with defined temporal relationships. Sequences may have gaps between Intervals, or even simultaneous activities. A Sequence may be re-locatable, i.e., it does not require a specific date and time. A Sequence may consist of a single Interval. A Sequence MAY include a Lineage.
<b>Partition</b>	A Partition is a set of consecutive Intervals. The Partition includes the trivial case of a single Interval. Many energy negotiations apply an EMIX product to a partition, e.g., consecutive fifteen minute Intervals.
<b>Gluon</b>	A Gluon influences the serialization of Intervals in a Sequence, though inheritance and through schedule setting. The Gluon is similar to the Interval, but has no service or schedule effects until applied to an Interval or Sequence. A Gluon also defines a handle for invoking a sequence within a service.
<b>Artifact</b>	An Artifact is the thing that occurs during an Interval. The contents of the Artifact are not specified in WS-Calendar, rather the Artifact provides an extension base for the use of WS-Calendar in other specifications. EMIX product and performance Artifacts may inherit elements as do Intervals within a Sequence.

1103 Much of EMIX defines the payloads that are delivered in the artifact. WS-Calendar defines how schedule-  
 1104 related information, although incomplete in an Interval and Sequence can be modified and completed.  
 1105 WS-Calendar calls this process Inheritance and specifies a number of rules that govern Inheritance.  
 1106 EMIX artifacts define Inheritance in manner compliant with WS-Calendar. Table C-16-2 defines the terms  
 1107 used to describe inheritance.

1108 *Table C-16-2: WS-Calendar Semantics of Inheritance*

Term	Definition
<b>Parent</b>	A Gluon that points to a sequence is known as the sequence's Parent. A Gluon may alternately reference another Gluon, i.e., it is that other Gluon's Parent.
<b>Lineage</b>	Lineage refers to the full ordered set of Parents of a Sequence

Term	Definition
<b>Inheritance</b>	Parents bequeath information to Children that inherit them. If a child does not already possess that information, then it accepts the inheritance. Information specified in one informational object is considered present in another that is itself lacking expression of that information. This information is termed the Inheritance of that object.
<b>Bequeath</b>	A Parent Bequeaths attributes (Inheritance) to its Children
<b>Inherit</b>	A Child Inherits attributes (Inheritance) from its Parent
<b>Availability</b>	Availability expresses the range of times in which an Interval or Sequence can be Scheduled. Availability can overlay or be overlaid by Busy. Availability can be Inherited
<b>Busy</b>	Busy expresses the range of times in which an Interval or Sequence cannot be Scheduled. Busy can overlay or be overlaid by Availability. Busy can be Inherited

1109 As Intervals are processed, as Intervals are assembled, and as inheritance is processed, the information  
1110 conveyed about each element changes. EMIX artifacts may pass through several stages in which the  
1111 information is not yet complete or actionable, but is still a conforming expression of time and Sequence.  
1112 Table 16-3 defines the terms used when discussing the processing or processability of Intervals and  
1113 Sequences.

1114 *Table 16-3: WS-Calendar Semantics of Information Processing*

Term	Definition
<b>Bound</b>	As in mathematical logic where a metasyntactic variable is called "bound", an Interval, Sequence, or Partition is said to be Bound when the values necessary to execute it (as a service) are completely filled in.
<b>Partially Bound</b>	A Partially Bound Interval is one that is still not Bound after receiving its Inheritance. A Sequences or Partitions is Partially Bound if it contains at least one Interval that is Partially Bound.
<b>Unbound</b>	An Unbound Interval or Sequence is not itself complete, but must still receive inheritance to be fully specified. A Sequences or Partitions is Unbound if it contains at least one Interval that is Unbound.
<b>Fully Bound</b>	A synonym for Bound
<b>Scheduled</b>	A Sequence or Partition is said to be Scheduled when it is Anchored, Fully Bound, and service performance has been requested.
<b>Unscheduled</b>	An Interval is Unscheduled if its neither its begin date and time nor its end date and time have been set. A Sequence or Partition is Unscheduled if none of its Intervals, after when Fully Bound, is Scheduled.
<b>Designated Interval</b>	In a Sequence the Designated Interval is either (a) (if there are no Gluons related to the Sequence) one of the Earliest Interval(s), or (b) (if there is at least one Gluon related to the Sequence) the single Interval referenced by a Gluon as Parent.
<b>Composed Interval</b>	A Composed Interval is the virtual Interval specified by applying inheritance through the entire lineage and into the Sequence in accord with the inheritance rules. A Composed Interval may be Bound or Unbound.

Term	Definition
<b>Composed Sequence</b>	A Composed Sequence is the virtual Sequence specified by applying inheritance through the entire lineage and into the Sequence in accord with the inheritance rules. A Composed Sequence may be Bound or Unbound.

1115 The WS-Calendar defines more terms, and in greater detail, but the tables above are sufficient to be able  
1116 to discuss schedule, sequence, and inheritance in EMIX.  
1117

1118

## D. Electrical Power and Energy

1119 Each type of Electrical Power and Energy Product has its own definitions and its own descriptive  
1120 parameters. These artifacts are the specific descriptions relevant to defining the potential utility of the  
1121 power and energy Product. The Power and Energy Artifacts describe the intrinsic information. There may  
1122 be cases when an Artifact is held in the envelope contents, perhaps as informational support for the  
1123 intrinsic prices.

1124 To put the terms "Power" and "Energy" into the proper context for this specification, the following  
1125 definitions will be used:

- 1126 • Apparent Energy: the production or consumption of Apparent Power over time; unit: volt-ampere  
1127 hours, VAh
- 1128 • Apparent Power (S): mathematical product of root-mean-square voltage and root-mean-square  
1129 current, vector sum of Real Power and Reactive Power, square root of sum of squares of Real  
1130 Power and Reactive Power; unit: volt-ampere, VA
- 1131 • Current: flow of electric charge, or rate of flow of electric charge; unit: ampere, A
- 1132 • Energy: the production or consumption of Power over time.
- 1133 • Power Factor (p.f.): ratio of Real Power to Complex Power, cosine of the phase angle between  
1134 Current and Voltage, expressed as a number between 0 and 1, expressed as a percentage (i.e.,  
1135 50% = 0.5); unit: dimensionless
- 1136 • Reactive Energy: the production or consumption of Reactive Power over time; unit: volt-ampere-  
1137 reactive hours, VARh, VA-rh, varh
- 1138 • Reactive Power (Q): mathematical product of the root-mean-square voltage and root-mean-  
1139 square current multiplied by the sine of the angle between the voltage and current; unit: volt-  
1140 amperes reactive, VAR, VA-r, var
- 1141 • Real Energy: the production or consumption of Real Power over time; unit: Watt-hour, Wh
- 1142 • Real Power (P): rate at which electricity is produced or consumed, mathematical product of  
1143 Voltage and Current; unit: Watt, W
- 1144 • Voltage: difference in electric potential between two points; unit: volt, V
- 1145 • Generically, the use of the term "Power" refers to "Real Power" and is expressed in Watts.  
1146 Otherwise, one talks of Apparent Power in VA, or Reactive Power in VARs. Generically, the use  
1147 of the term "Energy" refers to "Real Energy" and is expressed in Watt-hours. Otherwise, one talks  
1148 of Apparent Energy in VAh, or Reactive Energy in VARh.

1149 Generically, the use of the term "Power" refers to "Real Power" and is expressed in Watts. Otherwise, one  
1150 talks of Apparent Power or Complex Power in VA, or Reactive Power in VARs.

1151  
1152

## E. Mapping between NAESB PAP03 work and this specification

1153 Under the [NIST]-led smart grid interoperability process, the North American Energy Standards Board  
1154 (NAESB) provided a minimal scope and requirements for this specification, specifically in its work to  
1155 address the Priority Action Plan 03 (PA03), Price and Product definition. This section maps the specific  
1156 requirements from NAESB to the work in this specification.  
1157

Tariff Rate Type	Description
<b>block rate</b>	In Power-Contracts.xsd, addressed by the Block Power Full Requirements Contract.
<b>critical peak price</b>	Addressed by both Price Relative and Price Multiplier when applies to a business schedule.
<b>demand rate</b>	Demand charges can be applied to all Product types in EMIX.
<b>day ahead market rate</b>	Either TEMIX or a Block Power agreement applied to a day-ahead schedule addresses this need.
<b>market clearing price for energy</b>	TEMIX addresses this use case directly.
<b>peak time rebate</b>	
<b>real time price rate</b>	Either TEMIX or a Block Power agreement applied to a day-ahead schedule addresses this need.
<b>time of use rate</b>	Either TEMIX or a Block Power agreement applied to a day-ahead schedule addresses this need. EMIX applied alongside any of the standard agreements can support variable peak pricing.
<b>variable peak pricing</b>	TEMIX applied alongside any of the standard products can support variable peak pricing.

1158  
1159

1160

## F. Schemas (Non-Normative)

1161 In OASIS, when there are external, machine-readable artifacts, they are always normative. These are  
1162 placed here as a convenience to the reviewer.

1163 If you are tracing inheritance, and the construction of EMIX information through the schemas, recall that  
1164 every EMIX Product is derived from EMIX Base which is a Business Schedule applied to a Product  
1165 Description. All transactions occur at the EMIX Interface. Products are described and enumerated using  
1166 extensions of the Item Base.

### 1167 F.1 EMIX Schemas

1168 The EMIX Schema is in three parts

#### 1169 F.1.1 EMIX.XSD

```
1170 <?xml version="1.0" encoding="UTF-8"?>
1171 <!-- emix.xsd
1172 Schema Set for OASIS EMIX 1.0 WD23 (20110411)
1173 Set includes:
1174     EMIX, EMIX-Requirements, EMIX-Warrants (emix)
1175     Power, Power-Contracts, Power-Quality (power)
1176     Resource (resource)
1177
1178 This set built on the WS-Calendar v1.0 PRD02 Schemas.
1179 -->
1180 <!-- 1.0 EMIX: Energy Market Information Exchange-->
1181 <xs:schema xmlns:emix="http://docs.oasis-open.org/ns/emix"
1182 xmlns:xcal="urn:ietf:params:xml:ns:icalendar-2.0"
1183 xmlns:clm5ISO42173A="urn:un:unece:uncefact:codelist:standard:5:ISO42173A:2010-04-07"
1184 xmlns:gml="http://www.opengis.net/gml/3.2"
1185 xmlns:gmlsf="http://www.opengis.net/gmlsf/2.0"
1186 xmlns:xs="http://www.w3.org/2001/XMLSchema" targetNamespace="http://docs.oasis-
1187 open.org/ns/emix" elementFormDefault="qualified" attributeFormDefault="unqualified">
1188     <xs:include schemaLocation="emix-requirements.xsd"/>
1189     <xs:include schemaLocation="emix-warrants.xsd"/>
1190     <xs:import namespace="urn:ietf:params:xml:ns:icalendar-2.0"
1191 schemaLocation="http://docs.oasis-open.org/ws-calendar/ws-calendar-
1192 spec/v1.0/csprd02/xsd/iCalendar.xsd"/>
1193     <xs:import namespace="urn:ietf:params:xml:ns:icalendar-2.0"
1194 schemaLocation="http://docs.oasis-open.org/ws-calendar/ws-calendar-
1195 spec/v1.0/csprd02/xsd/iCalendar-wscal-extensions.xsd"/>
1196     <xs:import namespace="urn:ietf:params:xml:ns:icalendar-2.0"
1197 schemaLocation="http://docs.oasis-open.org/ws-calendar/ws-calendar-
1198 spec/v1.0/csprd02/xsd/iCalendar-availability-extension.xsd"/>
1199     <xs:import namespace="urn:un:unece:uncefact:codelist:standard:5:ISO42173A:2010-04-07"
1200 schemaLocation="http://www.unece.org/uncefact/codelist/standard/ISO_ISO3AlphaCurrencyCod
1201 e_20100407.xsd"/>
1202     <xs:import namespace="http://www.opengis.net/gml/3.2"
1203 schemaLocation="http://schemas.opengis.net/gml/3.2.1/gml.xsd"/>
1204     <!-- 1.0 Core EMIX objects-->
1205     <xs:annotation>
1206         <xs:appinfo
1207 source="http://schemas.opengis.net/gml/3.2.1/profiles/gmlsfProfile/2.0/gmlsfLevels.xsd">
1208             <gmlsf:ComplianceLevel>0</gmlsf:ComplianceLevel>
1209
1210             <gmlsf:GMLProfileSchema>http://schemas.opengis.net/gml/3.2.1/profiles/gmlsfProfile/2.
1211 0/gmlsf.xsd</gmlsf:GMLProfileSchema>
1212         </xs:appinfo>
1213     </xs:annotation>
1214     <!-- 1.1 EMIX Product -->
1215     <xs:element name="product" type="emix:ProductType">
1216         <xs:annotation>
1217             <xs:documentation>Emix Product, .i.e., a Product Description applied
1218 to a schedule.</xs:documentation>
```

```

1219         </xs:annotation>
1220     </xs:element>
1221     <xs:complexType name="ProductType" mixed="false">
1222         <xs:annotation>
1223             <xs:documentation>EMIX Product Type, i.e. a Product Description
1224 applied to a Schedule</xs:documentation>
1225         </xs:annotation>
1226         <xs:complexContent mixed="false">
1227             <xs:extension base="emix:EmixBaseType">
1228                 <xs:sequence>
1229                     <xs:element ref="emix:currency"/>
1230                     <xs:element ref="emix:marketContext"/>
1231                     <xs:element ref="emix:transactiveState"/>
1232                     <xs:element ref="emix:side"/>
1233                     <xs:element ref="emix:constraints"/>
1234                 </xs:sequence>
1235             </xs:extension>
1236         </xs:complexContent>
1237     </xs:complexType>
1238     <!-- 1.2 EMIX Option -->
1239     <xs:element name="emixOption" type="emix:EmixOptionType">
1240         <xs:annotation>
1241             <xs:documentation>Option to buy an Emix Product</xs:documentation>
1242         </xs:annotation>
1243     </xs:element>
1244     <xs:complexType name="EmixOptionType" mixed="false">
1245         <xs:complexContent mixed="false">
1246             <xs:extension base="emix:EmixBaseType">
1247                 <xs:sequence>
1248                     <xs:element ref="emix:transactiveState"/>
1249                     <xs:element name="optionExerciseSchedule"
1250 type="emix:BusinessScheduleType"/>
1251                     <xs:element name="optionHolderSide"
1252 type="emix:SideType"/>
1253                     <xs:element name="optionPremium"
1254 type="emix:PriceType"/>
1255                     <xs:element name="optionExerciseLeadTime"
1256 type="xcal:DurationPropType"/>
1257                     <xs:element name="optionStrikePrice"
1258 type="emix:PriceType"/>
1259                     <xs:element ref="emix:optionType"/>
1260                     <xs:element ref="emix:side"/>
1261                     <xs:element ref="emix:marketContext"/>
1262                     <xs:element ref="emix:currency"/>
1263                     <xs:element ref="emix:constraints"/>
1264                 </xs:sequence>
1265             </xs:extension>
1266         </xs:complexContent>
1267     </xs:complexType>
1268     <!-- 1.3 EMIX TEMIX -->
1269     <xs:element name="temix" type="emix:TemixType">
1270         <xs:annotation>
1271             <xs:documentation>minimalist Energy Market Information Exchange (EMIX)
1272 Type</xs:documentation>
1273         </xs:annotation>
1274     </xs:element>
1275     <xs:complexType name="TemixType" mixed="false">
1276         <xs:complexContent mixed="false">
1277             <xs:extension base="emix:EmixBaseType">
1278                 <xs:sequence>
1279                     <xs:element ref="emix:currency"/>
1280                     <xs:element ref="emix:transactiveState"/>
1281                     <xs:element ref="emix:constraints"/>
1282                     <xs:element ref="emix:side"/>
1283                     <xs:element name="expires" type="xs:dateTime"
1284 minOccurs="0" maxOccurs="1"/>
1285                 </xs:sequence>
1286             </xs:extension>
1287         </xs:complexContent>
1288     </xs:complexType>
1289     <!-- 1.4 Delivery -->

```

```

1290     <xs:element name="delivery" type="emix:DeliveryType"/>
1291     <xs:complexType name="DeliveryType" mixed="false">
1292         <xs:annotation>
1293             <xs:documentation>Receipt / Report of Product Delivery. Injection flag
1294 is true for adding product to market supply, false for taking from
1295 market.</xs:documentation>
1296         </xs:annotation>
1297         <xs:complexContent mixed="false">
1298             <xs:extension base="emix:EmixBaseType">
1299                 <xs:sequence>
1300                     <xs:element name="injection" type="xs:boolean"/>
1301                 </xs:sequence>
1302             </xs:extension>
1303         </xs:complexContent>
1304     </xs:complexType>
1305     <!-- 2.0 EMIX Components-->
1306     <!-- 2.1 Envelope -->
1307     <xs:element name="envelopeContents" type="emix:EnvelopeContentsType"/>
1308     <xs:complexType name="EnvelopeContentsType">
1309         <xs:sequence>
1310             <xs:element ref="emix:warrants" minOccurs="0" maxOccurs="1"/>
1311         </xs:sequence>
1312     </xs:complexType>
1313     <!-- 8.0 Supporting Information Structures-->
1314     <!-- 8.2 Market definitions -->
1315     <!-- 8.2.1 Market Context -->
1316     <xs:element name="marketContext" type="emix:MarketContextType"/>
1317     <xs:simpleType name="MarketContextType">
1318         <xs:restriction base="xs:anyURI"/>
1319     </xs:simpleType>
1320     <!-- 8.2.2 Transactive State -->
1321     <xs:element name="transactiveState" type="emix:TransactiveStateType"/>
1322     <xs:simpleType name="TransactiveStateType">
1323         <xs:restriction base="xs:string">
1324             <xs:enumeration value="IndicationOfInterest"/>
1325             <xs:enumeration value="Tender"/>
1326             <xs:enumeration value="Transaction"/>
1327             <xs:enumeration value="Exercise"/>
1328             <xs:enumeration value="Delivery"/>
1329             <xs:enumeration value="TransportCommitment"/>
1330             <xs:enumeration value="Publication"/>
1331         </xs:restriction>
1332     </xs:simpleType>
1333     <!-- 8.2.3 Currency -->
1334     <xs:element name="currency" type="clm5ISO42173A:ISO3AlphaCurrencyCodeContentType">
1335         <xs:annotation>
1336             <xs:documentation>Currency codes coming from UN CEFACT
1337 schemas</xs:documentation>
1338         </xs:annotation>
1339     </xs:element>
1340     <!-- 8.2.4 Enumeration for Side -->
1341     <xs:element name="side" type="emix:SideType"/>
1342     <xs:simpleType name="SideType">
1343         <xs:restriction base="xs:string">
1344             <xs:enumeration value="Buy"/>
1345             <xs:enumeration value="Sell"/>
1346         </xs:restriction>
1347     </xs:simpleType>
1348     <!-- 8.3 Price -->
1349     <xs:element name="priceBase" type="emix:PriceBaseType" abstract="true">
1350         <xs:annotation>
1351             <xs:documentation>Abstract base for EMIX Prices</xs:documentation>
1352         </xs:annotation>
1353     </xs:element>
1354     <xs:complexType name="PriceBaseType" abstract="true">
1355         <xs:annotation>
1356             <xs:documentation>Type of Abstract base for EMIX
1357 Prices</xs:documentation>
1358         </xs:annotation>
1359     </xs:complexType>
1360     <!-- 8.3.1 Absolute Price -->

```

```

1361 <xs:element name="price" type="emix:PriceType" substitutionGroup="emix:priceBase"/>
1362 <xs:complexType name="PriceType" mixed="false">
1363 <xs:annotation>
1364 <xs:documentation>Simple Price</xs:documentation>
1365 </xs:annotation>
1366 <xs:complexContent mixed="false">
1367 <xs:extension base="emix:PriceBaseType">
1368 <xs:sequence>
1369 <xs:element ref="emix:value" minOccurs="1"
1370 maxOccurs="1"/>
1371 </xs:sequence>
1372 </xs:extension>
1373 </xs:complexContent>
1374 </xs:complexType>
1375 <!-- 8.3.2 Multiplier Price - multiplier on base amount -->
1376 <xs:element name="priceMultiplier" type="emix:PriceMultiplierType"
1377 substitutionGroup="emix:priceBase"/>
1378 <xs:complexType name="PriceMultiplierType" mixed="false">
1379 <xs:annotation>
1380 <xs:documentation>Multiplier times market price, 1 for same as
1381 market</xs:documentation>
1382 </xs:annotation>
1383 <xs:complexContent mixed="false">
1384 <xs:extension base="emix:PriceBaseType">
1385 <xs:sequence>
1386 <xs:element name="multiplier" type="xs:float"
1387 minOccurs="1" maxOccurs="1"/>
1388 <xs:element ref="emix:marketContext" minOccurs="0"
1389 maxOccurs="1">
1390 <xs:annotation>
1391 <xs:documentation>Market Context for
1392 base price. If blank, Market Context from hosting artifact.</xs:documentation>
1393 </xs:annotation>
1394 </xs:element>
1395 </xs:sequence>
1396 </xs:extension>
1397 </xs:complexContent>
1398 </xs:complexType>
1399 <!-- 8.3.4 Price Offset (additive or subtractive) over base amount -->
1400 <xs:element name="priceRelative" type="emix:PriceRelativeType"
1401 substitutionGroup="emix:priceBase"/>
1402 <xs:complexType name="PriceRelativeType" mixed="false">
1403 <xs:annotation>
1404 <xs:documentation>Price Relative is a fixed charge (positive or
1405 negative) applied to base price</xs:documentation>
1406 </xs:annotation>
1407 <xs:complexContent mixed="false">
1408 <xs:extension base="emix:PriceBaseType">
1409 <xs:sequence>
1410 <xs:element ref="emix:value" minOccurs="1"
1411 maxOccurs="1"/>
1412 <xs:element ref="emix:marketContext" minOccurs="0"
1413 maxOccurs="1">
1414 <xs:annotation>
1415 <xs:documentation>Market Context for
1416 base price. If blank, Market Context from hosting artifact.</xs:documentation>
1417 </xs:annotation>
1418 </xs:element>
1419 </xs:sequence>
1420 </xs:extension>
1421 </xs:complexContent>
1422 </xs:complexType>
1423 <!-- 8.3.6 Simple Price -->
1424 <xs:element name="value" type="emix:valueType"/>
1425 <xs:simpleType name="valueType">
1426 <xs:restriction base="xs:decimal"/>
1427 </xs:simpleType>
1428 <!-- 8.5 Quantity -->
1429 <xs:element name="integralOnly" type="emix:IntegralOnlyType"/>
1430 <xs:simpleType name="IntegralOnlyType">
1431 <xs:annotation>

```

```

1432         <xs:documentation>integralOnly is an element used in many EMIX objects
1433 distinguishing between an (amount, response, ramp) that is all (true) or nothing
1434 (false)</xs:documentation>
1435     </xs:annotation>
1436     <xs:restriction base="xs:boolean"/>
1437 </xs:simpleType>
1438 <xs:element name="autonomous" type="emix:AutonomousType"/>
1439 <xs:simpleType name="AutonomousType">
1440     <xs:annotation>
1441         <xs:documentation>An autonomous resource or service (true) is able to
1442 respond or maintain service independently. A non autonomous service (false) must await
1443 dispatch.</xs:documentation>
1444     </xs:annotation>
1445     <xs:restriction base="xs:boolean"/>
1446 </xs:simpleType>
1447 <!-- 8.7 Enumeration for Option Types -->
1448 <xs:element name="optionType" type="emix:OptionTypeType"/>
1449 <xs:simpleType name="OptionTypeType">
1450     <xs:union memberTypes="emix:OptionTypeEnumeratedType
1451 emix:EmixExtensionType"/>
1452 </xs:simpleType>
1453 <xs:simpleType name="OptionTypeEnumeratedType">
1454     <xs:annotation>
1455         <xs:documentation>Enumerated Option Types</xs:documentation>
1456     </xs:annotation>
1457     <xs:restriction base="xs:string"/>
1458 </xs:simpleType>
1459 <!-- 8.8 Performance Constraints -->
1460 <!-- 9.2 Abstract EMIX Base(product applied to a schedule) -->
1461 <xs:element name="emixBase" type="emix:EmixBaseType"/>
1462 <xs:complexType name="EmixBaseType" abstract="true">
1463     <xs:annotation>
1464         <xs:documentation>iCalendar-derived object to host EMIX
1465 elements</xs:documentation>
1466     </xs:annotation>
1467     <xs:complexContent>
1468         <xs:extension base="xcal:VcalendarType">
1469             <xs:sequence>
1470                 <xs:element ref="emix:envelopeContents" minOccurs="0"
1471 maxOccurs="1"/>
1472             </xs:sequence>
1473         </xs:extension>
1474     </xs:complexContent>
1475 </xs:complexType>
1476 <!-- 9.3 Abstract Product Description -->
1477 <xs:element name="productDescription" type="emix:ProductDescriptionType"
1478 substitutionGroup="xcal:artifactBase"/>
1479 <xs:complexType name="ProductDescriptionType" abstract="true">
1480     <xs:annotation>
1481         <xs:documentation>In EMIX, the Product Description is placed in the
1482 Interval or Gluon attachment. The respective product schemas extend this abstract
1483 class.</xs:documentation>
1484     </xs:annotation>
1485     <xs:complexContent>
1486         <xs:extension base="xcal:ArtifactBaseType"/>
1487     </xs:complexContent>
1488 </xs:complexType>
1489 <!-- 9.4 Interfaces -->
1490 <xs:element name="serviceArea" type="emix:ServiceAreaType"
1491 substitutionGroup="emix:emixInterface"/>
1492 <xs:complexType name="ServiceAreaType">
1493     <xs:annotation>
1494         <xs:documentation>The Service Area is the geographic region that is
1495 affected by the EMIX market condition</xs:documentation>
1496     </xs:annotation>
1497     <xs:complexContent>
1498         <xs:extension base="emix:EmixInterfaceType">
1499             <xs:sequence>
1500                 <xs:element ref="emix:geographicArea"/>
1501             </xs:sequence>
1502         </xs:extension>

```

```

1503         </xs:complexContent>
1504     </xs:complexType>
1505     <xs:element name="emixInterface" type="emix:EmixInterfaceType"/>
1506     <xs:complexType name="EmixInterfaceType" abstract="true" mixed="false">
1507         <xs:annotation>
1508             <xs:documentation>Abstract base class for the interfaces for EMIX
1509 Product delivery, measurement, and/or pricing</xs:documentation>
1510         </xs:annotation>
1511     </xs:complexType>
1512     <!-- 9.5 Geographic Area -->
1513     <xs:element name="geographicArea" type="emix:GeographicAreaType"
1514 substitutionGroup="gml:AbstractFeature"/>
1515     <xs:complexType name="GeographicAreaType" mixed="false">
1516         <xs:annotation>
1517             <xs:documentation>A service area is a geographic region that may be
1518 affected by the same EMIX market condition.</xs:documentation>
1519         </xs:annotation>
1520         <xs:complexContent mixed="false">
1521             <xs:extension base="gml:AbstractFeatureType">
1522                 <xs:sequence>
1523                     <xs:element name="foo"
1524 type="gml:GeometryPropertyType"/>
1525                 </xs:sequence>
1526             </xs:extension>
1527         </xs:complexContent>
1528     </xs:complexType>
1529     <!-- 9.6 Business Schedule -->
1530     <xs:element name="businessSchedule" type="emix:BusinessScheduleType"/>
1531     <xs:complexType name="BusinessScheduleType" mixed="false">
1532         <xs:annotation>
1533             <xs:documentation>iCalendar-derived business schedule, more variant
1534 than allowed in sequences</xs:documentation>
1535         </xs:annotation>
1536         <xs:complexContent mixed="false">
1537             <xs:extension base="xcal:VavailabilityType"/>
1538         </xs:complexContent>
1539     </xs:complexType>
1540     <xs:element name="duration" type="emix:DurationType"/>
1541     <xs:complexType name="DurationType" mixed="false">
1542         <xs:annotation>
1543             <xs:documentation>iCalendar-derived duration. This brings in
1544 xcal:duration and xcal:parameters. </xs:documentation>
1545         </xs:annotation>
1546         <xs:complexContent mixed="false">
1547             <xs:extension base="xcal:DurationPropType"/>
1548         </xs:complexContent>
1549     </xs:complexType>
1550     <!-- 9.7 emix Items -->
1551     <xs:element name="measurement" type="emix:MeasurementType"
1552 substitutionGroup="emix:productDescription"/>
1553     <xs:complexType name="MeasurementType">
1554         <xs:annotation>
1555             <xs:documentation>Type of Measurement</xs:documentation>
1556         </xs:annotation>
1557         <xs:complexContent>
1558             <xs:extension base="emix:ProductDescriptionType">
1559                 <xs:sequence>
1560                     <xs:element ref="emix:quantity"/>
1561                     <xs:element ref="emix:itemBase"/>
1562                 </xs:sequence>
1563             </xs:extension>
1564         </xs:complexContent>
1565     </xs:complexType>
1566     <xs:element name="emixGranularity" type="emix:EmixGranularityType"/>
1567     <xs:complexType name="EmixGranularityType" mixed="false">
1568         <xs:annotation>
1569             <xs:documentation>Abstract base class used for graularity of market
1570 indications of interest and tenders</xs:documentation>
1571         </xs:annotation>
1572         <xs:sequence>
1573             <xs:element ref="emix:quantity"/>

```

```

1574         <xs:element ref="emix:itemBase"/>
1575     </xs:sequence>
1576 </xs:complexType>
1577 <xs:element name="itemBase" type="emix:ItemBaseType" abstract="true"/>
1578 <xs:complexType name="ItemBaseType" abstract="true" mixed="false">
1579     <xs:annotation>
1580         <xs:documentation>Abstract base class for units for EMIX Product
1581 delivery, measurement, and warrants. Item as in PO Item, Requisition Item, Invoice Item,
1582 Lading Item. Item does not include Quantity or Price, because a single product
1583 description or transaction may have multiple quantities or prices associated with a
1584 single item.</xs:documentation>
1585     </xs:annotation>
1586 </xs:complexType>
1587 <!-- 9.8 Units and Measurement Abstractions -->
1588 <xs:element name="quantity" type="emix:QuantityType"/>
1589 <xs:simpleType name="QuantityType">
1590     <xs:annotation>
1591         <xs:documentation>Base type for all quantities in
1592 EMIX.</xs:documentation>
1593     </xs:annotation>
1594     <xs:restriction base="xs:float"/>
1595 </xs:simpleType>
1596 <xs:element name="scale" type="emix:SiScaleType"/>
1597 <xs:simpleType name="SiScaleType">
1598     <xs:annotation>
1599         <xs:documentation>Scale based on representations of SI scale as
1600 expressed in the unit multipliers defined for the CIM</xs:documentation>
1601         <xs:documentation xml:lang="en">enumeration</xs:documentation>
1602     </xs:annotation>
1603     <xs:restriction base="xs:string">
1604         <xs:enumeration value="n">
1605             <xs:annotation>
1606                 <xs:documentation>Nano 10**-9</xs:documentation>
1607                 <xs:documentation xml:lang="en">enum</xs:documentation>
1608             </xs:annotation>
1609         </xs:enumeration>
1610         <xs:enumeration value="micro">
1611             <xs:annotation>
1612                 <xs:documentation>Micro 10**-6</xs:documentation>
1613                 <xs:documentation xml:lang="en">enum</xs:documentation>
1614             </xs:annotation>
1615         </xs:enumeration>
1616         <xs:enumeration value="m">
1617             <xs:annotation>
1618                 <xs:documentation>Milli 10**-3</xs:documentation>
1619                 <xs:documentation xml:lang="en">enum</xs:documentation>
1620             </xs:annotation>
1621         </xs:enumeration>
1622         <xs:enumeration value="c">
1623             <xs:annotation>
1624                 <xs:documentation>Centi 10**-2</xs:documentation>
1625                 <xs:documentation xml:lang="en">enum</xs:documentation>
1626             </xs:annotation>
1627         </xs:enumeration>
1628         <xs:enumeration value="d">
1629             <xs:annotation>
1630                 <xs:documentation>Deci 10**-1</xs:documentation>
1631                 <xs:documentation xml:lang="en">enum</xs:documentation>
1632             </xs:annotation>
1633         </xs:enumeration>
1634         <xs:enumeration value="k">
1635             <xs:annotation>
1636                 <xs:documentation>Kilo 10**3</xs:documentation>
1637                 <xs:documentation xml:lang="en">enum</xs:documentation>
1638             </xs:annotation>
1639         </xs:enumeration>
1640         <xs:enumeration value="M">
1641             <xs:annotation>
1642                 <xs:documentation>Mega 10**6</xs:documentation>
1643                 <xs:documentation xml:lang="en">enum</xs:documentation>
1644             </xs:annotation>

```

```

1645     </xs:enumeration>
1646     <xs:enumeration value="G">
1647         <xs:annotation>
1648             <xs:documentation>Giga 10**9</xs:documentation>
1649             <xs:documentation xml:lang="en">enum</xs:documentation>
1650         </xs:annotation>
1651     </xs:enumeration>
1652     <xs:enumeration value="T">
1653         <xs:annotation>
1654             <xs:documentation>Tera 10**12</xs:documentation>
1655             <xs:documentation xml:lang="en">enum</xs:documentation>
1656         </xs:annotation>
1657     </xs:enumeration>
1658     <xs:enumeration value="none">
1659         <xs:annotation>
1660             <xs:documentation xml:lang="en">enum</xs:documentation>
1661         </xs:annotation>
1662     </xs:enumeration>
1663     <xs:enumeration value="p">
1664         <xs:annotation>
1665             <xs:documentation>Pico 10**-12</xs:documentation>
1666             <xs:documentation xml:lang="en">enum</xs:documentation>
1667         </xs:annotation>
1668     </xs:enumeration>
1669 </xs:restriction>
1670 </xs:simpleType>
1671 <!-- 9.9 Extension Type -->
1672 <xs:simpleType name="EmixExtensionType">
1673     <xs:annotation>
1674         <xs:documentation>Pattern used for extending string enumeration, where
1675 allowed</xs:documentation>
1676     </xs:annotation>
1677     <xs:restriction base="xs:string">
1678         <xs:pattern value="x-\S.*"/>
1679     </xs:restriction>
1680 </xs:simpleType>
1681 </xs:schema>

```

## 1682 F.1.2 EMIX-Requirements

```

1683 <?xml version="1.0" encoding="UTF-8"?>
1684 <!-- emix.xsd
1685 Schema Set for OASIS EMIX 1.0 WD23 (20110411)
1686 Set includes:
1687     EMIX, EMIX-Requirements, EMIX-Warrants (emix)
1688     Power, Power-Contracts, Power-Quality (power)
1689     Resource (resource)
1690
1691 This set built on the WS-Calendar v1.0 PRD02 Schemas.
1692 -->
1693 <!-- 8.9 Constraints & Requirements -->
1694 <xs:schema xmlns:emix="http://docs.oasis-open.org/ns/emix"
1695     xmlns:xs="http://www.w3.org/2001/XMLSchema"
1696     xmlns:xcal="urn:ietf:params:xml:ns:icalendar-2.0"
1697     xmlns:clm5ISO42173A="urn:un:unece:uncefact:odelist:standard:5:ISO42173A:2010-04-07"
1698     xmlns:gml="http://www.opengis.net/gml/3.2" targetNamespace="http://docs.oasis-
1699 open.org/ns/emix" elementFormDefault="qualified" attributeFormDefault="unqualified">
1700     <xs:include schemaLocation="emix.xsd"/>
1701     <xs:element name="constraints" type="emix:ConstraintsType"/>
1702     <xs:complexType name="ConstraintsType">
1703         <xs:annotation>
1704             <xs:documentation>Constraints are extrinsic to the product delivery
1705 but effect how a partner may request performance of a service. Performance constraints
1706 may be tied to the basic mechanical needs of the resource or to the business needs of
1707 the source. These constraints can affect the market value of the resource or the
1708 repeated invocation of a resource. It is possible for a given underlying resource to be
1709 offered to the market with different constraints and therefor different values. It is
1710 possible for a given underlying resource to be offered to the market with different
1711 constraints and therefor different values.</xs:documentation>
1712         </xs:annotation>

```

```

1713     <xs:sequence>
1714         <xs:element name="constraints" type="emix:ArrayOfConstraints"/>
1715         <xs:element name="requirements" type="emix:ArrayOfRequirements"/>
1716     </xs:sequence>
1717 </xs:complexType>
1718 <!-- 8.9.1 Core EMIX Constraints-->
1719 <xs:element name="baseConstraint" type="emix:BaseConstraintType" abstract="true">
1720     <xs:annotation>
1721         <xs:documentation>Abstract extension object for Emix
1722 Constraints</xs:documentation>
1723     </xs:annotation>
1724 </xs:element>
1725 <xs:complexType name="ArrayOfConstraints">
1726     <xs:annotation>
1727         <xs:documentation>Collection of Emix Constraints</xs:documentation>
1728     </xs:annotation>
1729     <xs:sequence>
1730         <xs:element ref="emix:baseConstraint" minOccurs="0"
1731 maxOccurs="unbounded"/>
1732     </xs:sequence>
1733 </xs:complexType>
1734 <xs:complexType name="BaseConstraintType" abstract="true">
1735     <xs:annotation>
1736         <xs:documentation>Type of Abstract extension object for Emix
1737 Constraints</xs:documentation>
1738     </xs:annotation>
1739 </xs:complexType>
1740 <xs:element name="minimumResponseDuration" type="emix:MinimumResponseDurationType"
1741 substitutionGroup="emix:baseConstraint">
1742     <xs:annotation>
1743         <xs:documentation>The shortest Duration for which the resource will
1744 accept a request to maintain a response before returning to pre-request
1745 levels.</xs:documentation>
1746     </xs:annotation>
1747 </xs:element>
1748 <xs:element name="maximumResponseDuration" type="emix:MaximumResponseDurationType"
1749 substitutionGroup="emix:baseConstraint">
1750     <xs:annotation>
1751         <xs:documentation>The longest Duration for which the resource will
1752 accept a request.</xs:documentation>
1753     </xs:annotation>
1754 </xs:element>
1755 <xs:element name="minimumRecoveryDuration" type="emix:MinimumRecoveryDurationType"
1756 substitutionGroup="emix:baseConstraint">
1757     <xs:annotation>
1758         <xs:documentation>The minimum Duration that the Resource requires
1759 after the end of a response the resource has is ready to respond to a new
1760 request.</xs:documentation>
1761     </xs:annotation>
1762 </xs:element>
1763 <xs:element name="minimumDurationBetweenInvocations"
1764 type="emix:MinimumDurationBetweenInvocationsType"
1765 substitutionGroup="emix:baseConstraint">
1766     <xs:annotation>
1767         <xs:documentation>The minimum Duration that the Resource requires
1768 after receiving a request before the resource has is ready to respond to a new
1769 request.</xs:documentation>
1770     </xs:annotation>
1771 </xs:element>
1772 <xs:element name="minimumNotificationDuration"
1773 type="emix:MinimumNotificationDurationType" substitutionGroup="emix:baseConstraint">
1774     <xs:annotation>
1775         <xs:documentation>The minimum Duration that the Resource requires for
1776 Notification before initiating a response to a request.</xs:documentation>
1777     </xs:annotation>
1778 </xs:element>
1779 <xs:element name="maximumNotificationDuration"
1780 type="emix:MaximumNotificationDurationType" substitutionGroup="emix:baseConstraint">
1781     <xs:annotation>
1782         <xs:documentation>The maximum Duration in advance of a requested
1783 response that the resource is willing to accept a request.</xs:documentation>

```

```

1784         </xs:annotation>
1785     </xs:element>
1786     <xs:element name="responseTime" type="emix:ResponseTimeType"
1787 substitutionGroup="emix:baseConstraint">
1788         <xs:annotation>
1789             <xs:documentation>Duration required from receipt of a request to
1790 initiation of a response by the resource</xs:documentation>
1791         </xs:annotation>
1792     </xs:element>
1793     <xs:element name="maximumInvocationsPerDuration"
1794 type="emix:MaximumInvocationsPerDurationType" substitutionGroup="emix:baseConstraint">
1795         <xs:annotation>
1796             <xs:documentation>Maximum number of invocations of service during a
1797 given duration</xs:documentation>
1798         </xs:annotation>
1799     </xs:element>
1800     <xs:element name="maximumConsecutiveDurations"
1801 type="emix:MaximumConsecutiveDurationsType" substitutionGroup="emix:baseConstraint">
1802         <xs:annotation>
1803             <xs:documentation>Maximim consecutive durations in which service can
1804 be invoked, e.g., it will not accept requests on more than 3 consecutive
1805 days.</xs:documentation>
1806         </xs:annotation>
1807     </xs:element>
1808     <xs:element name="minimumStartsPerDuration" type="emix:MinimumStartsPerDurationType"
1809 substitutionGroup="emix:baseConstraint">
1810         <xs:annotation>
1811             <xs:documentation>The fewest Requests that the resource will accept
1812 during any duration. This constraint is typically used in market rather than in resource
1813 descriptions.</xs:documentation>
1814         </xs:annotation>
1815     </xs:element>
1816     <xs:element name="maximumRunDuration" type="emix:MaximumRunDurationType"
1817 substitutionGroup="emix:baseConstraint">
1818         <xs:annotation>
1819             <xs:documentation>The Maximum duration for which a resource will
1820 accept a request</xs:documentation>
1821         </xs:annotation>
1822     </xs:element>
1823     <xs:element name="minimumRunDuration" type="emix:MinimumRunDurationType"
1824 substitutionGroup="emix:baseConstraint">
1825         <xs:annotation>
1826             <xs:documentation>The Minimum duration for which a resource will
1827 accept a request</xs:documentation>
1828         </xs:annotation>
1829     </xs:element>
1830     <xs:element name="availabilitySchedule" type="emix:AvailabilityScheduleType"
1831 substitutionGroup="emix:baseConstraint">
1832         <xs:annotation>
1833             <xs:documentation>A schedule of times for which which a resource will
1834 accept requests. The schedule may include multiple availability windows. The scheduled
1835 duration must be entirely within an availability window.</xs:documentation>
1836         </xs:annotation>
1837     </xs:element>
1838     <xs:element name="notificationSchedule" type="emix:NotificationScheduleType"
1839 substitutionGroup="emix:baseConstraint">
1840         <xs:annotation>
1841             <xs:documentation>A schedule of time during which a resource will
1842 accept requests. The schedule may include multiple availability windows. THE
1843 notification must occur within an availability window.</xs:documentation>
1844         </xs:annotation>
1845     </xs:element>
1846     <xs:element name="unavailabilitySchedule" type="emix:UnavailabilityScheduleType"
1847 substitutionGroup="emix:baseConstraint">
1848         <xs:annotation>
1849             <xs:documentation>A schedule of times for which which a resource will
1850 not accept requests. The schedule may include multiple unavailability windows. The
1851 scheduled duration must not occur within or overlap an unavailability
1852 window.</xs:documentation>
1853         </xs:annotation>
1854     </xs:element>

```

```

1855 <!-- 8.9.1.1 Minimum Response-->
1856 <xs:complexType name="MinimumResponseDurationType" mixed="false">
1857 <xs:annotation>
1858 <xs:documentation>Type of the shortest Duration for which the resource
1859 will accept a request to maintain a response before returning to pre-request
1860 levels.</xs:documentation>
1861 </xs:annotation>
1862 <xs:complexContent mixed="false">
1863 <xs:extension base="emix:BaseConstraintType">
1864 <xs:sequence>
1865 <xs:element ref="emix:duration" minOccurs="1"
1866 maxOccurs="1"/>
1867 </xs:sequence>
1868 </xs:extension>
1869 </xs:complexContent>
1870 </xs:complexType>
1871 <!-- 8.9.1.2 Maximum Response-->
1872 <xs:complexType name="MaximumResponseDurationType" mixed="false">
1873 <xs:annotation>
1874 <xs:documentation>Type of the longest Duration for which the resource
1875 will accept a request.</xs:documentation>
1876 </xs:annotation>
1877 <xs:complexContent mixed="false">
1878 <xs:extension base="emix:BaseConstraintType">
1879 <xs:sequence>
1880 <xs:element ref="emix:duration" minOccurs="1"
1881 maxOccurs="1"/>
1882 </xs:sequence>
1883 </xs:extension>
1884 </xs:complexContent>
1885 </xs:complexType>
1886 <xs:complexType name="MinimumRecoveryDurationType" mixed="false">
1887 <xs:annotation>
1888 <xs:documentation>Type of the minimum Duration that the Resource
1889 requires after the end of a response the resource has is ready to respond to a new
1890 request.</xs:documentation>
1891 </xs:annotation>
1892 <xs:complexContent mixed="false">
1893 <xs:extension base="emix:BaseConstraintType">
1894 <xs:sequence>
1895 <xs:element ref="emix:duration" minOccurs="1"
1896 maxOccurs="1"/>
1897 </xs:sequence>
1898 </xs:extension>
1899 </xs:complexContent>
1900 </xs:complexType>
1901 <xs:complexType name="MinimumDurationBetweenInvocationsType" mixed="false">
1902 <xs:annotation>
1903 <xs:documentation>Type of the minimum Duration that the Resource
1904 requires after receiving a request before the resource has is ready to respond to a new
1905 request.</xs:documentation>
1906 </xs:annotation>
1907 <xs:complexContent mixed="false">
1908 <xs:extension base="emix:BaseConstraintType">
1909 <xs:sequence>
1910 <xs:element ref="emix:duration" minOccurs="1"
1911 maxOccurs="1"/>
1912 </xs:sequence>
1913 </xs:extension>
1914 </xs:complexContent>
1915 </xs:complexType>
1916 <xs:complexType name="MinimumNotificationDurationType" mixed="false">
1917 <xs:annotation>
1918 <xs:documentation>Type of the minimum Duration that the Resource
1919 requires for Notification before initiating a response to a request.</xs:documentation>
1920 </xs:annotation>
1921 <xs:complexContent mixed="false">
1922 <xs:extension base="emix:BaseConstraintType">
1923 <xs:sequence>
1924 <xs:element ref="emix:duration" minOccurs="1"
1925 maxOccurs="1"/>

```

```

1926         </xs:sequence>
1927         </xs:extension>
1928     </xs:complexContent>
1929 </xs:complexType>
1930 <xs:complexType name="MaximumNotificationDurationType" mixed="false">
1931     <xs:annotation>
1932         <xs:documentation>Type of the maximum Duration in advance that a
1933 Resource is willing to accept a request for a response.</xs:documentation>
1934     </xs:annotation>
1935     <xs:complexContent mixed="false">
1936         <xs:extension base="emix:BaseConstraintType">
1937             <xs:sequence>
1938                 <xs:element ref="emix:duration" minOccurs="1"
1939 maxOccurs="1"/>
1940             </xs:sequence>
1941         </xs:extension>
1942     </xs:complexContent>
1943 </xs:complexType>
1944 <xs:complexType name="ResponseTimeType" mixed="false">
1945     <xs:annotation>
1946         <xs:documentation>Type of the Duration required from receipt of a
1947 request to initiation of a response by the resource</xs:documentation>
1948     </xs:annotation>
1949     <xs:complexContent mixed="false">
1950         <xs:extension base="emix:BaseConstraintType">
1951             <xs:sequence>
1952                 <xs:element ref="emix:duration" minOccurs="1"
1953 maxOccurs="1"/>
1954             </xs:sequence>
1955         </xs:extension>
1956     </xs:complexContent>
1957 </xs:complexType>
1958 <xs:complexType name="MaximumInvocationsPerDurationType" mixed="false">
1959     <xs:annotation>
1960         <xs:documentation>Type of the Maximum number of invocations of service
1961 during a given duration</xs:documentation>
1962     </xs:annotation>
1963     <xs:complexContent mixed="false">
1964         <xs:annotation>
1965             <xs:documentation>The resource will only accept a given number
1966 of requests for performance during a given interval.</xs:documentation>
1967         </xs:annotation>
1968         <xs:extension base="emix:BaseConstraintType">
1969             <xs:sequence>
1970                 <xs:element name="starts" type="xs:int" minOccurs="1"
1971 maxOccurs="1"/>
1972                 <xs:element ref="emix:duration" minOccurs="1"
1973 maxOccurs="1"/>
1974             </xs:sequence>
1975         </xs:extension>
1976     </xs:complexContent>
1977 </xs:complexType>
1978 <xs:complexType name="MaximumConsecutiveDurationsType" mixed="false">
1979     <xs:annotation>
1980         <xs:documentation>Type of Maximim consecutive durations in which
1981 service can be invoked, e.g., it will not accept requests on more than 3 consecutive
1982 days.</xs:documentation>
1983     </xs:annotation>
1984     <xs:complexContent mixed="false">
1985         <xs:extension base="emix:BaseConstraintType">
1986             <xs:sequence>
1987                 <xs:element name="durations" type="xs:int"/>
1988                 <xs:element ref="emix:duration" minOccurs="1"
1989 maxOccurs="1"/>
1990             </xs:sequence>
1991         </xs:extension>
1992     </xs:complexContent>
1993 </xs:complexType>
1994 <xs:complexType name="MinimumStartsPerDurationType" mixed="false">
1995     <xs:annotation>

```

```

1996         <xs:documentation>Type of the fewest Requests that the resource will
1997 accept during any duration. This constraint is typically used in market rather than in
1998 resource descriptions.</xs:documentation>
1999     </xs:annotation>
2000     <xs:complexContent mixed="false">
2001         <xs:extension base="emix:BaseConstraintType">
2002             <xs:sequence>
2003                 <xs:element name="starts" type="xs:int" minOccurs="1"
2004 maxOccurs="1"/>
2005                 <xs:element ref="emix:duration" minOccurs="1"
2006 maxOccurs="1"/>
2007             </xs:sequence>
2008         </xs:extension>
2009     </xs:complexContent>
2010 </xs:complexType>
2011 <xs:complexType name="MaximumRunDurationType" mixed="false">
2012     <xs:annotation>
2013         <xs:documentation>Type of the Maximum duration for which a resource
2014 will accept a request</xs:documentation>
2015     </xs:annotation>
2016     <xs:complexContent mixed="false">
2017         <xs:extension base="emix:BaseConstraintType">
2018             <xs:sequence>
2019                 <xs:element ref="emix:duration" minOccurs="1"
2020 maxOccurs="1"/>
2021             </xs:sequence>
2022         </xs:extension>
2023     </xs:complexContent>
2024 </xs:complexType>
2025 <xs:complexType name="MinimumRunDurationType" mixed="false">
2026     <xs:annotation>
2027         <xs:documentation>Type of the Minimum duration for which a resource
2028 will accept a request</xs:documentation>
2029     </xs:annotation>
2030     <xs:complexContent mixed="false">
2031         <xs:extension base="emix:BaseConstraintType">
2032             <xs:sequence>
2033                 <xs:element ref="emix:duration" minOccurs="1"
2034 maxOccurs="1"/>
2035             </xs:sequence>
2036         </xs:extension>
2037     </xs:complexContent>
2038 </xs:complexType>
2039 <!-- Business Schedules -->
2040 <xs:complexType name="AvailabilityScheduleType" mixed="false">
2041     <xs:annotation>
2042         <xs:documentation>Type of the schedule of time for which a resource
2043 will accept requests. The schedule may include multiple availability windows. The
2044 scheduled duration must be entirely within an availability window.</xs:documentation>
2045     </xs:annotation>
2046     <xs:complexContent mixed="false">
2047         <xs:extension base="emix:BaseConstraintType">
2048             <xs:sequence>
2049                 <xs:element ref="emix:businessSchedule"
2050 maxOccurs="unbounded"/>
2051             </xs:sequence>
2052         </xs:extension>
2053     </xs:complexContent>
2054 </xs:complexType>
2055 <xs:complexType name="NotificationScheduleType" mixed="false">
2056     <xs:annotation>
2057         <xs:documentation>Type of the schedule of time during which a resource
2058 will accept requests. The schedule may include multiple notofication windows. The
2059 request must occur within a notification window.</xs:documentation>
2060     </xs:annotation>
2061     <xs:complexContent mixed="false">
2062         <xs:extension base="emix:BaseConstraintType">
2063             <xs:sequence>
2064                 <xs:element ref="emix:businessSchedule"
2065 maxOccurs="unbounded"/>
2066             </xs:sequence>

```

```

2067         </xs:extension>
2068     </xs:complexContent>
2069 </xs:complexType>
2070 <xs:complexType name="UnavailabilityScheduleType" mixed="false">
2071     <xs:annotation>
2072         <xs:documentation>Type of the schedule of time for which a resource
2073 will not accept requests. The schedule may include multiple unavailability windows. The
2074 scheduled duration must not occur within or overlap an unavailability
2075 window.</xs:documentation>
2076     </xs:annotation>
2077     <xs:complexContent mixed="false">
2078         <xs:extension base="emix:BaseConstraintType">
2079             <xs:sequence>
2080                 <xs:element ref="emix:businessSchedule"
2081 maxOccurs="unbounded"/>
2082             </xs:sequence>
2083         </xs:extension>
2084     </xs:complexContent>
2085 </xs:complexType>
2086 <!-- 8.2 EMIX Requirements-->
2087 <xs:element name="marketRequirements" type="emix:MarketRequirementsType">
2088     <xs:annotation>
2089         <xs:documentation>Market Requirements are the market portion of
2090 Constraints, i.e., they are used to state the offeror's expectations about a tender.It
2091 is possible for a given underlying resource to be offered to the market with different
2092 Requirements and therefor different values.</xs:documentation>
2093     </xs:annotation>
2094 </xs:element>
2095 <xs:complexType name="MarketRequirementsType">
2096     <xs:annotation>
2097         <xs:documentation>Market Requirements are the market portion of
2098 Constraints, i.e., they are used to state the offeror's expectations about a tender.It
2099 is possible for a given underlying resource to be offered to the market with different
2100 Requirements and therefor different values.</xs:documentation>
2101     </xs:annotation>
2102     <xs:sequence>
2103         <xs:element name="requirements" type="emix:ArrayOfRequirements"/>
2104     </xs:sequence>
2105 </xs:complexType>
2106 <xs:complexType name="BaseRequirementType" abstract="true">
2107     <xs:annotation>
2108         <xs:documentation>Abstract base for all
2109 Requirements</xs:documentation>
2110     </xs:annotation>
2111 </xs:complexType>
2112 <xs:element name="baseRequirement" type="emix:BaseRequirementType">
2113     <xs:annotation>
2114         <xs:documentation>Abstract base for all
2115 Requirements</xs:documentation>
2116     </xs:annotation>
2117 </xs:element>
2118 <xs:complexType name="ArrayOfRequirements">
2119     <xs:annotation>
2120         <xs:documentation>Abstract base for a collection of
2121 requirements</xs:documentation>
2122     </xs:annotation>
2123     <xs:sequence>
2124         <xs:element ref="emix:baseRequirement" minOccurs="0"
2125 maxOccurs="unbounded"/>
2126     </xs:sequence>
2127 </xs:complexType>
2128 <xs:element name="minimumEconomicRequirement"
2129 type="emix:MinimumEconomicRequirementType" substitutionGroup="emix:baseRequirement">
2130     <xs:annotation>
2131         <xs:documentation> Minimum net remuneration this resource requires
2132 from a total response</xs:documentation>
2133     </xs:annotation>
2134 </xs:element>
2135 <xs:element name="requiredStartupCost" type="emix:RequiredStartupCostType"
2136 substitutionGroup="emix:baseRequirement">

```

```

2138     <xs:annotation>
2139         <xs:documentation>Minimum remuneration required from start-up of this
2140 service. </xs:documentation>
2141     </xs:annotation>
2142 </xs:element>
2143     <xs:element name="minimumResourceCost" type="emix:MinimumResourceCostType"
2144 substitutionGroup="emix:baseRequirement">
2145         <xs:annotation>
2146             <xs:documentation>Resource requires this amount per period, i.e., a
2147 minimum requirement for $100 / hour at whatever rate</xs:documentation>
2148         </xs:annotation>
2149     </xs:element>
2150     <xs:complexType name="MinimumEconomicRequirementType" mixed="false">
2151         <xs:annotation>
2152             <xs:documentation>Minimum net remuneration this resource requires from
2153 a total response</xs:documentation>
2154         </xs:annotation>
2155         <xs:complexContent mixed="false">
2156             <xs:extension base="emix:BaseRequirementType">
2157                 <xs:sequence>
2158                     <xs:element ref="emix:price"/>
2159                 </xs:sequence>
2160             </xs:extension>
2161         </xs:complexContent>
2162     </xs:complexType>
2163     <xs:complexType name="RequiredStartupCostType" mixed="false">
2164         <xs:annotation>
2165             <xs:documentation> Minimum remuneration required from start-up of this
2166 service. </xs:documentation>
2167         </xs:annotation>
2168         <xs:complexContent mixed="false">
2169             <xs:extension base="emix:BaseRequirementType">
2170                 <xs:sequence>
2171                     <xs:element ref="emix:price" minOccurs="1"
2172 maxOccurs="1"/>
2173                 </xs:sequence>
2174             </xs:extension>
2175         </xs:complexContent>
2176     </xs:complexType>
2177     <!-- 4.3.2 Minimum Resource Cost -->
2178     <xs:complexType name="MinimumResourceCostType" mixed="false">
2179         <xs:annotation>
2180             <xs:documentation>Resource requires this amount per period, i.e., a
2181 minimum requirement for $100 / hour at whatever rate</xs:documentation>
2182         </xs:annotation>
2183         <xs:complexContent mixed="false">
2184             <xs:extension base="emix:BaseRequirementType">
2185                 <xs:sequence>
2186                     <xs:element ref="emix:price"/>
2187                     <xs:element ref="emix:duration"/>
2188                 </xs:sequence>
2189             </xs:extension>
2190         </xs:complexContent>
2191     </xs:complexType>
2192 </xs:schema>

```

### 2193 F.1.3 EMIX Warrants

```

2194 <?xml version="1.0" encoding="UTF-8"?>
2195 <!-- emix.xsd
2196 Schema Set for OASIS EMIX 1.0 WD23 (20110411)
2197 Set includes:
2198     EMIX, EMIX-Requirements, EMIX-Warrants (emix)
2199     Power, Power-Contracts, Power-Quality (power)
2200     Resource (resource)
2201
2202 This set built on the WS-Calendar v1.0 PRD02 Schemas.
2203 -->

```

```

2204 <xs:schema xmlns:emix="http://docs.oasis-open.org/ns/emix"
2205 xmlns:ical="urn:ietf:params:xml:ns:icalendar-2.0"
2206 xmlns:clm5ISO42173A="urn:unec:unefact:codelist:standard:5:ISO42173A:2010-04-07"
2207 xmlns:gml="http://www.opengis.net/gml/3.2" xmlns:xs="http://www.w3.org/2001/XMLSchema"
2208 targetNamespace="http://docs.oasis-open.org/ns/emix" elementFormDefault="qualified"
2209 attributeFormDefault="unqualified">
2210   <xs:include schemaLocation="emix.xsd"/>
2211   <!-- 8.8 EMIX Warrants-->
2212   <xs:element name="warrants" type="emix:ArrayOfWarrants">
2213     <xs:annotation>
2214       <xs:documentation>Warrants are "a written assurances that some product
2215 or service will be provided or will meet certain specifications" . Sellers use EMIX
2216 Warrants to provide information about the source of the energy or about its
2217 environmental characteristics. Buyers can use warrants to indicate what they wish to
2218 purchase. EMIX does not define specific warrants, although it does define base types for
2219 extension by those who wish to develop the various types of warrants.</xs:documentation>
2220     </xs:annotation>
2221   </xs:element>
2222   <xs:element name="baseWarrant" type="emix:BaseWarrantType">
2223     <xs:annotation>
2224       <xs:documentation>Abstract extension object for Emix
2225 Warrants</xs:documentation>
2226     </xs:annotation>
2227   </xs:element>
2228   <xs:complexType name="ArrayOfWarrants">
2229     <xs:annotation>
2230       <xs:documentation>Collection of Emix Warrants</xs:documentation>
2231     </xs:annotation>
2232     <xs:sequence>
2233       <xs:element ref="emix:baseWarrant" minOccurs="0"
2234 maxOccurs="unbounded"/>
2235     </xs:sequence>
2236   </xs:complexType>
2237   <xs:complexType name="BaseWarrantType" abstract="true">
2238     <xs:annotation>
2239       <xs:documentation>Type of Abstract extension object for Emix
2240 Warrants</xs:documentation>
2241     </xs:annotation>
2242   </xs:complexType>
2243   <xs:element name="supportForPrice" type="emix:SupportForPriceType"
2244 substitutionGroup="emix:baseWarrant"/>
2245   <xs:element name="qualityWarrant" type="emix:QualityWarrantType"
2246 substitutionGroup="emix:baseWarrant"/>
2247   <xs:element name="environmentalWarrant" type="emix:EnvironmentalWarrantType"
2248 substitutionGroup="emix:baseWarrant"/>
2249   <xs:element name="sourceWarrant" type="emix:SourceWarrantType"
2250 substitutionGroup="emix:baseWarrant"/>
2251   <xs:element name="contentWarrant" type="emix:ContentWarrantType"
2252 substitutionGroup="emix:baseWarrant"/>
2253   <xs:element name="controllabilityWarrant" type="emix:ControllabilityWarrantType"
2254 substitutionGroup="emix:baseWarrant"/>
2255   <!-- 8.8.1 Core EMIX Warrants-->
2256   <xs:complexType name="SupportForPriceType" abstract="true" mixed="false">
2257     <xs:annotation>
2258       <xs:documentation>Price Support products may be needed to justify the
2259 price. An example would be a transport product that support the difference between a
2260 product price at a point of delivery and a product price at a point of
2261 receipt.</xs:documentation>
2262     </xs:annotation>
2263     <xs:complexContent mixed="false">
2264       <xs:extension base="emix:BaseWarrantType"/>
2265     </xs:complexContent>
2266   </xs:complexType>
2267   <xs:complexType name="QualityWarrantType" abstract="true" mixed="false">
2268     <xs:annotation>
2269       <xs:documentation>A Quality Warrant asserts or requires that the power
2270 be of a certain quality or better.</xs:documentation>
2271     </xs:annotation>
2272     <xs:complexContent mixed="false">
2273       <xs:extension base="emix:BaseWarrantType">
2274         <xs:sequence>

```

```

2275         <xs:element ref="emix:product" minOccurs="1"
2276 maxOccurs="unbounded"/>
2277     </xs:sequence>
2278 </xs:extension>
2279 </xs:complexContent>
2280 </xs:complexType>
2281 <xs:complexType name="EnvironmentalWarrantType" abstract="true" mixed="false">
2282 <xs:annotation>
2283 <xs:documentation>An Environmental Warrant asserts what environmental
2284 cost was created by the product.</xs:documentation>
2285 </xs:annotation>
2286 <xs:complexContent mixed="false">
2287 <xs:extension base="emix:BaseWarrantType">
2288 <xs:sequence>
2289 <xs:element ref="emix:product" minOccurs="1"
2290 maxOccurs="unbounded"/>
2291 </xs:sequence>
2292 </xs:extension>
2293 </xs:complexContent>
2294 </xs:complexType>
2295 <xs:complexType name="SourceWarrantType" abstract="true" mixed="false">
2296 <xs:annotation>
2297 <xs:documentation>A source warrant consists of assertions about
2298 through what proces energy originated. </xs:documentation>
2299 </xs:annotation>
2300 <xs:complexContent mixed="false">
2301 <xs:extension base="emix:BaseWarrantType">
2302 <xs:sequence>
2303 <xs:element ref="emix:product" minOccurs="1"
2304 maxOccurs="unbounded"/>
2305 </xs:sequence>
2306 </xs:extension>
2307 </xs:complexContent>
2308 </xs:complexType>
2309 <xs:complexType name="ContentWarrantType" abstract="true" mixed="false">
2310 <xs:annotation>
2311 <xs:documentation>A content warrant consists of assertions about where
2312 energy originated. </xs:documentation>
2313 </xs:annotation>
2314 <xs:complexContent mixed="false">
2315 <xs:extension base="emix:BaseWarrantType">
2316 <xs:sequence>
2317 <xs:element ref="emix:product" minOccurs="1"
2318 maxOccurs="unbounded"/>
2319 </xs:sequence>
2320 </xs:extension>
2321 </xs:complexContent>
2322 </xs:complexType>
2323 <xs:complexType name="ControllabilityWarrantType" abstract="true" mixed="false">
2324 <xs:annotation>
2325 <xs:documentation>A Controllability Warrant makes certifies that the
2326 resource is controlable byt the market buyer. </xs:documentation>
2327 </xs:annotation>
2328 <xs:complexContent mixed="false">
2329 <xs:extension base="emix:BaseWarrantType">
2330 <xs:sequence>
2331 <xs:element ref="emix:product" minOccurs="1"
2332 maxOccurs="unbounded"/>
2333 </xs:sequence>
2334 </xs:extension>
2335 </xs:complexContent>
2336 </xs:complexType>
2337 </xs:schema>

```

## 2338 F.2 Power Schemas

2339 The Power Schema is in 3 parts

## 2340 F.2.1 Power.xsd

```
2341 <?xml version="1.0" encoding="UTF-8"?>
2342 <!-- power-quality.xsd - Power Products for OASIS EMIX 1.0 WD23 (20110411)
2343
2344 Set includes:
2345     EMIX, EMIX-Requirements, EMIX-Warrants (emix)
2346     Power, Power-Contracts, Power-Quality (power)
2347     Resource (resource)
2348
2349 This set built on the WS-Calendar v1.0 PRD02 Schemas.
2350 -->
2351 <xs:schema xmlns:power="http://docs.oasis-open.org/ns/emix/power"
2352 xmlns:emix="http://docs.oasis-open.org/ns/emix"
2353 xmlns:xcal="urn:ietf:params:xml:ns:icalendar-2.0"
2354 xmlns:clm5ISO42173A="urn:un:unece:uncefact:codelist:standard:5:ISO42173A:2010-04-07"
2355 xmlns:gml="http://www.opengis.net/gml/3.2" xmlns:xs="http://www.w3.org/2001/XMLSchema"
2356 targetNamespace="http://docs.oasis-open.org/ns/emix/power"
2357 elementFormDefault="unqualified" attributeFormDefault="unqualified">
2358   <xs:include schemaLocation="power-products.xsd"/>
2359   <xs:include schemaLocation="power-quality.xsd"/>
2360   <xs:import namespace="http://docs.oasis-open.org/ns/emix" schemaLocation="emix.xsd"/>
2361   <!-- 1.0 Core EMIX Power objects-->
2362   <!-- 1.1 Power Product-->
2363   <!-- 1.2 Reserves and Power Options-->
2364   <!-- 2.0 Contract Power Products -->
2365   <!-- 4.0 Resource Semantics -->
2366   <!-- 6.0 Power Quality -->
2367   <!-- 9.1.2 Unit Energy Price -->
2368   <xs:element name="unitEnergyPrice" type="power:UnitEnergyPriceType"/>
2369   <xs:complexType name="UnitEnergyPriceType">
2370     <xs:annotation>
2371       <xs:documentation>Price per Unit of Energy, i.e., Power times
2372 Duration</xs:documentation>
2373     </xs:annotation>
2374     <xs:sequence>
2375       <xs:element ref="emix:priceBase"/>
2376       <xs:element ref="power:energyItem"/>
2377     </xs:sequence>
2378   </xs:complexType>
2379   <xs:element name="energyQuantity" type="power:EnergyQuantityType"/>
2380   <xs:complexType name="EnergyQuantityType">
2381     <xs:annotation>
2382       <xs:documentation>Level of Energy</xs:documentation>
2383     </xs:annotation>
2384     <xs:sequence>
2385       <xs:element ref="emix:quantity"/>
2386       <xs:element ref="power:energyItem"/>
2387     </xs:sequence>
2388   </xs:complexType>
2389   <!-- 9.1.3 Power Delivery Rate -->
2390   <xs:element name="powerQuantity" type="power:PowerQuantityType"/>
2391   <xs:complexType name="PowerQuantityType">
2392     <xs:annotation>
2393       <xs:documentation>Quantity of Power</xs:documentation>
2394     </xs:annotation>
2395     <xs:sequence>
2396       <xs:element ref="emix:quantity"/>
2397       <xs:element ref="power:powerItem"/>
2398     </xs:sequence>
2399   </xs:complexType>
2400   <!-- 9.1.5 Reactive Power -->
2401   <xs:element name="varQuantity" type="power:VarQuantityType"/>
2402   <xs:complexType name="VarQuantityType">
2403     <xs:sequence>
2404       <xs:element ref="emix:quantity"/>
2405       <xs:element ref="power:powerReactive"/>
2406     </xs:sequence>
2407   </xs:complexType>
2408   <!-- 9.8 Interface Types -->
2409   <!-- 9.8.1 EndDevices -->
```

```

2410     <!-- updated name of this section to reflect the more generic EndDevice rather than
2411 Meters specifically -->
2412     <xs:element name="endDeviceAsset" type="power:EndDeviceAssetType"
2413 substitutionGroup="emix:emixInterface">
2414         <xs:annotation>
2415             <xs:documentation>One type of EndDeviceAsset is a MeterAsset which can
2416 perform metering, load management, connect/disconnect, accounting functions, etc. Some
2417 EndDeviceAssets may be connected to a MeterAsset.</xs:documentation>
2418         </xs:annotation>
2419     </xs:element>
2420     <xs:complexType name="EndDeviceAssetType">
2421         <xs:annotation>
2422             <xs:documentation>The EndDeviceAssets are the physical device or
2423 devices which could be meters or other types of devices that may be of
2424 interest</xs:documentation>
2425         </xs:annotation>
2426         <xs:complexContent>
2427             <xs:extension base="emix:EmixInterfaceType">
2428                 <xs:sequence>
2429                     <xs:element ref="power:mRID"/>
2430                 </xs:sequence>
2431             </xs:extension>
2432         </xs:complexContent>
2433     </xs:complexType>
2434     <!-- 9.8.1.1 Meters -->
2435     <xs:element name="meterAsset" type="power:MeterAssetType"
2436 substitutionGroup="emix:emixInterface"/>
2437     <xs:complexType name="MeterAssetType">
2438         <xs:annotation>
2439             <xs:documentation>The MeterAsset is the physical device or devices
2440 that performs the role of the meter</xs:documentation>
2441         </xs:annotation>
2442         <xs:complexContent>
2443             <xs:extension base="emix:EmixInterfaceType">
2444                 <xs:sequence>
2445                     <xs:element ref="power:mRID"/>
2446                 </xs:sequence>
2447             </xs:extension>
2448         </xs:complexContent>
2449     </xs:complexType>
2450     <!-- 9.8.2 Nodes -->
2451     <xs:element name="pnode" type="power:PnodeType"
2452 substitutionGroup="emix:emixInterface"/>
2453     <xs:complexType name="PnodeType" mixed="false">
2454         <xs:annotation>
2455             <xs:documentation>A pricing node is directly associated with a
2456 connectivity node. It is a pricing location for which market participants submit their
2457 bids, offers, buy/sell CRRs, and settle.</xs:documentation>
2458         </xs:annotation>
2459         <xs:complexContent mixed="false">
2460             <xs:extension base="emix:EmixInterfaceType">
2461                 <xs:sequence>
2462                     <xs:element ref="power:node"/>
2463                 </xs:sequence>
2464             </xs:extension>
2465         </xs:complexContent>
2466     </xs:complexType>
2467     <xs:element name="aggregatedPnode" type="power:AggregatedPnodeType"
2468 substitutionGroup="emix:emixInterface"/>
2469     <xs:complexType name="AggregatedPnodeType" mixed="false">
2470         <xs:annotation>
2471             <xs:documentation>An aggregated pricing node is a specialized type of
2472 pricing node used to model items such as System Zone, Default Price Zone, Custom Price
2473 Zone, Control Area, Aggregated Generation, Aggregated Participating Load, Aggregated Non-
2474 Participating Load, Trading Hub, DCA Zone</xs:documentation>
2475         </xs:annotation>
2476         <xs:complexContent mixed="false">
2477             <xs:extension base="emix:EmixInterfaceType">
2478                 <xs:sequence>
2479                     <xs:element ref="power:node"/>
2480                 </xs:sequence>

```

```

2481         </xs:extension>
2482     </xs:complexContent>
2483 </xs:complexType>
2484 <xs:element name="serviceLocation" type="power:ServiceLocationType"
2485 substitutionGroup="emix:emixInterface"/>
2486 <xs:complexType name="ServiceLocationType" mixed="false">
2487     <xs:annotation>
2488         <xs:documentation>A customer ServiceLocation has one or more
2489 ServiceDeliveryPoint(s), which in turn relate to Meters. The location may be a point or
2490 a polygon, depending on the specific circumstances. For distribution, the
2491 ServiceLocation is typically the location of the utility customer's premise.
2492 </xs:documentation>
2493     </xs:annotation>
2494     <xs:complexContent mixed="false">
2495         <xs:extension base="emix:EmixInterfaceType">
2496             <xs:sequence>
2497                 <xs:element ref="emix:geographicArea"/>
2498             </xs:sequence>
2499         </xs:extension>
2500     </xs:complexContent>
2501 </xs:complexType>
2502 <xs:element name="serviceDeliveryPoint" type="power:ServiceDeliveryPointType"
2503 substitutionGroup="emix:emixInterface"/>
2504 <xs:complexType name="ServiceDeliveryPointType" mixed="false">
2505     <xs:annotation>
2506         <xs:documentation>Logical point on the network where the ownership of
2507 the service changes hands. It is one of potentially many service points within a
2508 ServiceLocation, delivering service in accordance with a CustomerAgreement. Used at the
2509 place where a meter may be installed.</xs:documentation>
2510     </xs:annotation>
2511     <xs:complexContent mixed="false">
2512         <xs:extension base="emix:EmixInterfaceType">
2513             <xs:sequence>
2514                 <xs:element ref="power:node" maxOccurs="1"/>
2515             </xs:sequence>
2516         </xs:extension>
2517     </xs:complexContent>
2518 </xs:complexType>
2519 <!-- 9.8.3 Transport Interface -->
2520 <xs:element name="transportInterface" type="power:TransportInterfaceType"
2521 substitutionGroup="emix:emixInterface"/>
2522 <xs:complexType name="TransportInterfaceType" mixed="false">
2523     <xs:annotation>
2524         <xs:documentation>The Transport Interface delineates the edges at
2525 either end of a transport segment.</xs:documentation>
2526     </xs:annotation>
2527     <xs:complexContent mixed="false">
2528         <xs:extension base="emix:EmixInterfaceType">
2529             <xs:sequence>
2530                 <xs:element name="pointOfReceipt"
2531 type="power:NodeType"/>
2532                 <xs:element name="pointOfDelivery"
2533 type="power:NodeType"/>
2534             </xs:sequence>
2535         </xs:extension>
2536     </xs:complexContent>
2537 </xs:complexType>
2538 <!-- 9.8.9 Base Elements for Interfaces -->
2539 <xs:element name="node" type="power:NodeType"/>
2540 <xs:simpleType name="NodeType">
2541     <xs:annotation>
2542         <xs:documentation>The Node is a place where something changes (often
2543 ownership) or connects on the grid. Many nodes are associated with meters, but not all
2544 are.</xs:documentation>
2545     </xs:annotation>
2546     <xs:restriction base="xs:string"/>
2547 </xs:simpleType>
2548 <!-- 9.8.9.1 Base Elements for Interfaces -->
2549 <!-- The identifier for a EndDevice (meter or other), is mRID from IEC61968-->
2550 <xs:element name="mRID" type="power:mRIDType"/>
2551 <xs:simpleType name="mRIDType">

```

```

2552         <xs:annotation>
2553             <xs:documentation>The mRID identifies the physical device that may be
2554 a CustomerMeter or other types of EndDevices.</xs:documentation>
2555         </xs:annotation>
2556         <xs:restriction base="xs:string"/>
2557     </xs:simpleType>
2558     <!-- 9.9 Enumerations -->
2559     <!-- 9.9.1 Voltage -->
2560     <xs:element name="voltage" type="power:VoltageType"
2561 substitutionGroup="emix:itemBase"/>
2562     <xs:complexType name="VoltageType" mixed="false">
2563         <xs:annotation>
2564             <xs:documentation>Voltage</xs:documentation>
2565         </xs:annotation>
2566         <xs:complexContent mixed="false">
2567             <xs:extension base="emix:ItemBaseType">
2568                 <xs:sequence>
2569                     <xs:element name="itemDescription" type="xs:string"
2570 fixed="Voltage"/>
2571                     <xs:element name="itemUnits" type="xs:string"
2572 fixed="V"/>
2573                     <xs:element ref="emix:scale"/>
2574                 </xs:sequence>
2575             </xs:extension>
2576         </xs:complexContent>
2577     </xs:complexType>
2578     <!-- 9.9.2 Energy Units -->
2579     <xs:element name="energyApparent" type="power:EnergyApparentType"
2580 substitutionGroup="power:energyItem"/>
2581     <xs:complexType name="EnergyApparentType" mixed="false">
2582         <xs:annotation>
2583             <xs:documentation>Apparent Energy, measured in volt-ampere hours
2584 (VAh)</xs:documentation>
2585         </xs:annotation>
2586         <xs:complexContent mixed="false">
2587             <xs:restriction base="power:EnergyItemType">
2588                 <xs:sequence>
2589                     <xs:element name="itemDescription" type="xs:string"
2590 fixed="ApparentEnergy"/>
2591                     <xs:element name="itemUnits" type="xs:string"
2592 fixed="VAh"/>
2593                     <xs:element name="scale" type="emix:SiScaleType"/>
2594                 </xs:sequence>
2595             </xs:restriction>
2596         </xs:complexContent>
2597     </xs:complexType>
2598     <xs:element name="energyReactive" type="power:EnergyReactiveType"
2599 substitutionGroup="power:energyItem"/>
2600     <xs:complexType name="EnergyReactiveType" mixed="false">
2601         <xs:annotation>
2602             <xs:documentation>Reactive Energy, volt-amperes reactive hours
2603 (VARh)</xs:documentation>
2604         </xs:annotation>
2605         <xs:complexContent mixed="false">
2606             <xs:restriction base="power:EnergyItemType">
2607                 <xs:sequence>
2608                     <xs:element name="itemDescription" type="xs:string"
2609 fixed="ReactiveEnergy"/>
2610                     <xs:element name="itemUnits" type="xs:string"
2611 fixed="VARh"/>
2612                     <xs:element name="scale" type="emix:SiScaleType"/>
2613                 </xs:sequence>
2614             </xs:restriction>
2615         </xs:complexContent>
2616     </xs:complexType>
2617     <xs:element name="energyReal" type="power:EnergyRealType"
2618 substitutionGroup="power:energyItem"/>
2619     <xs:complexType name="EnergyRealType" mixed="false">
2620         <xs:annotation>
2621             <xs:documentation>Real Energy, Watt Hours (Wh)</xs:documentation>
2622         </xs:annotation>

```

```

2623     <xs:complexContent mixed="false">
2624         <xs:restriction base="power:EnergyItemType">
2625             <xs:sequence>
2626                 <xs:element name="itemDescription" type="xs:string"
2627 fixed="RealEnergy"/>
2628                 <xs:element name="itemUnits" type="xs:string"
2629 fixed="Wh"/>
2630                 <xs:element name="scale" type="emix:SiScaleType"/>
2631             </xs:sequence>
2632         </xs:restriction>
2633     </xs:complexContent>
2634 </xs:complexType>
2635 <!-- ===== -->
2636 <!-- 9.9.5 Base Energy Item Type -->
2637 <!-- ===== -->
2638 <xs:element name="energyItem" type="power:EnergyItemType"
2639 substitutionGroup="emix:itemBase"/>
2640 <xs:complexType name="EnergyItemType" abstract="true" mixed="false">
2641     <xs:annotation>
2642         <xs:documentation>Base for the measurement of
2643 Energy</xs:documentation>
2644     </xs:annotation>
2645     <xs:complexContent mixed="false">
2646         <xs:extension base="emix:ItemBaseType">
2647             <xs:sequence>
2648                 <xs:element name="itemDescription" type="xs:string"/>
2649                 <xs:element name="itemUnits" type="xs:string"/>
2650                 <xs:element name="scale" type="emix:SiScaleType"/>
2651             </xs:sequence>
2652         </xs:extension>
2653     </xs:complexContent>
2654 </xs:complexType>
2655 <!-- ===== -->
2656 <!-- 9.9.4 Power Units -->
2657 <!-- ===== -->
2658 <!-- ===== -->
2659 <xs:element name="powerApparent" type="power:PowerApparentType"
2660 substitutionGroup="power:powerItem"/>
2661 <xs:complexType name="PowerApparentType" mixed="false">
2662     <xs:annotation>
2663         <xs:documentation>Apparent Power measured in volt-amperes
2664 (VA)</xs:documentation>
2665     </xs:annotation>
2666     <xs:complexContent mixed="false">
2667         <xs:restriction base="power:PowerItemType">
2668             <xs:sequence>
2669                 <xs:element name="itemDescription" type="xs:string"
2670 fixed="ApparentPower"/>
2671                 <xs:element name="itemUnits" type="xs:string"
2672 fixed="VA"/>
2673                 <xs:element name="scale" type="emix:SiScaleType"/>
2674                 <xs:element ref="power:powerAttributes"/>
2675             </xs:sequence>
2676         </xs:restriction>
2677     </xs:complexContent>
2678 </xs:complexType>
2679 <!-- ===== -->
2680 <xs:element name="powerReactive" type="power:PowerReactiveType"
2681 substitutionGroup="power:powerItem"/>
2682 <xs:complexType name="PowerReactiveType" mixed="false">
2683     <xs:annotation>
2684         <xs:documentation>Reactive power, measured in volt-amperes reactive
2685 (VAR)</xs:documentation>
2686     </xs:annotation>
2687     <xs:complexContent mixed="false">
2688         <xs:restriction base="power:PowerItemType">
2689             <xs:sequence>
2690                 <xs:element name="itemDescription" type="xs:string"
2691 fixed="ReactivePower"/>
2692                 <xs:element name="itemUnits" type="xs:string"
2693 fixed="VAR"/>

```

```

2694         <xs:element name="scale" type="emix:SiScaleType"/>
2695         <xs:element ref="power:powerAttributes"/>
2696     </xs:sequence>
2697 </xs:restriction>
2698 </xs:complexContent>
2699 </xs:complexType>
2700 <!-- ===== -->
2701 <xs:element name="powerReal" type="power:PowerRealType"
2702 substitutionGroup="power:powerItem"/>
2703 <xs:complexType name="PowerRealType" mixed="false">
2704     <xs:annotation>
2705         <xs:documentation>Real power measured in Watts (W) or Joules/second
2706 (J/s)</xs:documentation>
2707     </xs:annotation>
2708     <xs:complexContent mixed="false">
2709         <xs:restriction base="power:PowerItemType">
2710             <xs:sequence>
2711                 <xs:element name="itemDescription" type="xs:string"
2712 fixed="RealPower"/>
2713                 <xs:element name="itemUnits">
2714                     <xs:simpleType>
2715                         <xs:restriction base="xs:token">
2716                             <xs:enumeration value="W"/>
2717                             <xs:enumeration value="J/s"/>
2718                         </xs:restriction>
2719                     </xs:simpleType>
2720                 </xs:element>
2721                 <xs:element name="scale" type="emix:SiScaleType"/>
2722                 <xs:element ref="power:powerAttributes"/>
2723             </xs:sequence>
2724         </xs:restriction>
2725     </xs:complexContent>
2726 </xs:complexType>
2727 <!-- ===== -->
2728 <!-- 9.9.5 Base Power Item Type -->
2729 <!-- ===== -->
2730 <xs:element name="powerItem" type="power:PowerItemType"
2731 substitutionGroup="emix:itemBase"/>
2732 <xs:complexType name="PowerItemType" abstract="true" mixed="false">
2733     <xs:annotation>
2734         <xs:documentation>Base for the measurement of Power</xs:documentation>
2735     </xs:annotation>
2736     <xs:complexContent mixed="false">
2737         <xs:extension base="emix:ItemBaseType">
2738             <xs:sequence>
2739                 <xs:element name="itemDescription" type="xs:string"/>
2740                 <xs:element name="itemUnits" type="xs:string"/>
2741                 <xs:element name="scale" type="emix:SiScaleType"/>
2742                 <xs:element ref="power:powerAttributes"/>
2743             </xs:sequence>
2744         </xs:extension>
2745     </xs:complexContent>
2746 </xs:complexType>
2747 <!-- ===== -->
2748 <xs:element name="powerAttributes" type="power:PowerAttributesType"/>
2749 <xs:complexType name="PowerAttributesType">
2750     <xs:sequence>
2751         <xs:element name="hertz" type="xs:decimal"/>
2752         <xs:element name="voltage" type="xs:decimal"/>
2753         <xs:element name="ac" type="xs:boolean"/>
2754     </xs:sequence>
2755 </xs:complexType>
2756 <!-- 9.9.5 Enumeration for Reserves and other Power Options -->
2757 <xs:element name="powerOptionType" type="power:PowerOptionTypeType"/>
2758 <xs:simpleType name="PowerOptionTypeType">
2759     <xs:union memberTypes="power:PowerOptionTypeEnumeratedType
2760 emix:EmixExtensionType"/>
2761 </xs:simpleType>
2762 <xs:simpleType name="PowerOptionTypeEnumeratedType">
2763     <xs:annotation>
2764         <xs:documentation>Power Reserve Options</xs:documentation>

```

```

2765     </xs:annotation>
2766     <xs:restriction base="xs:string">
2767         <xs:enumeration value="SpinningReserve"/>
2768         <xs:enumeration value="NonSpinningReserve"/>
2769         <xs:enumeration value="OperatingReserve"/>
2770         <xs:enumeration value="DemandResponse"/>
2771     </xs:restriction>
2772 </xs:simpleType>
2773 </xs:schema>

```

## 2774 F.2.2 Power Quality

2775 Demonstrates extensibility of base Warrant classes, as well.

```

2776 <?xml version="1.0" encoding="UTF-8"?>
2777 <!-- power-quality.xsd - Power Products for OASIS EMIX 1.0 WD23 (20110411)
2778
2779 Set includes:
2780     EMIX, EMIX-Requirements, EMIX-Warrants (emix)
2781     Power, Power-Contracts, Power-Quality (power)
2782     Resource (resource)
2783
2784 This set built on the WS-Calendar v1.0 PRD02 Schemas.
2785 -->
2786 <xs:schema xmlns:power="http://docs.oasis-open.org/ns/emix/power"
2787 xmlns:emix="http://docs.oasis-open.org/ns/emix"
2788 xmlns:xcal="urn:ietf:params:xml:ns:icalendar-2.0"
2789 xmlns:clm5ISO42173A="urn:un:unece:uncefact:odelist:standard:5:ISO42173A:2010-04-07"
2790 xmlns:gml="http://www.opengis.net/gml/3.2" xmlns:xs="http://www.w3.org/2001/XMLSchema"
2791 targetNamespace="http://docs.oasis-open.org/ns/emix/power"
2792 elementFormDefault="qualified" attributeFormDefault="unqualified">
2793     <xs:include schemaLocation="power.xsd"/>
2794     <xs:import namespace="http://docs.oasis-open.org/ns/emix" schemaLocation="emix.xsd"/>
2795     <!-- 6.0 Quality Warrants -->
2796     <xs:element name="powerQualityWarrant" type="power:PowerQualityWarrantType"
2797 substitutionGroup="emix:baseWarrant"/>
2798     <xs:complexType name="PowerQualityWarrantType" mixed="false">
2799         <xs:annotation>
2800             <xs:documentation>A Power Quality Warrant asserts or requires that the
2801 power be of a certain quality or better.</xs:documentation>
2802         </xs:annotation>
2803         <xs:complexContent mixed="false">
2804             <xs:extension base="emix:BaseWarrantType">
2805                 <xs:sequence>
2806                     <xs:element name="measurementProtocol"
2807 type="power:MeasurementProtocolType"/>
2808                     <xs:element name="constraints"
2809 type="power:ArrayOfPowerQualities"/>
2810                 </xs:sequence>
2811             </xs:extension>
2812         </xs:complexContent>
2813     </xs:complexType>
2814     <!-- 6.1 Power Quality -->
2815     <xs:element name="powerQuality" type="power:PowerQualityType">
2816         <xs:annotation>
2817             <xs:documentation>Power Quality warrant</xs:documentation>
2818         </xs:annotation>
2819     </xs:element>
2820     <xs:complexType name="PowerQualityType">
2821         <xs:annotation>
2822             <xs:documentation>Power Quality consists of a number of measures,
2823 based on contract, negotiation, and local regulation. Extend Power Quality to incorporate
2824 new elements by creating additional elements based on
2825 PowerQualityBaseType</xs:documentation>
2826         </xs:annotation>
2827         <xs:sequence>
2828             <xs:element name="measurementProtocol"
2829 type="power:MeasurementProtocolType"/>
2830             <xs:element name="constraints" type="power:ArrayOfPowerQualities"/>
2831         </xs:sequence>
2832     </xs:complexType>

```

```

2833     <xs:element name="basePowerQualityMeasurement"
2834     type="power:BasePowerQualityMeasurementType" abstract="true">
2835         <xs:annotation>
2836             <xs:documentation>Abstract extension object for Power
2837     Qualities</xs:documentation>
2838         </xs:annotation>
2839     </xs:element>
2840     <xs:complexType name="ArrayOfPowerQualities">
2841         <xs:annotation>
2842             <xs:documentation>Collection of Power Qualities</xs:documentation>
2843         </xs:annotation>
2844         <xs:sequence>
2845             <xs:element ref="power:basePowerQualityMeasurement" minOccurs="0"
2846     maxOccurs="unbounded"/>
2847         </xs:sequence>
2848     </xs:complexType>
2849     <xs:complexType name="BasePowerQualityMeasurementType" abstract="true">
2850         <xs:annotation>
2851             <xs:documentation>An identification of the standard or other protocol
2852     used to measure power quality. Sets definition for all other power attributes. Type of
2853     Abstract extension object for Power Qualities</xs:documentation>
2854         </xs:annotation>
2855     </xs:complexType>
2856     <!-- 6.1 Defined Power Qualities -->
2857     <xs:element name="powerFrequency" type="power:PowerFrequencyType"
2858     substitutionGroup="power:basePowerQualityMeasurement"/>
2859     <xs:element name="supplyVoltageVariations" type="power:SupplyVoltageVariationsType"
2860     substitutionGroup="power:basePowerQualityMeasurement"/>
2861     <xs:element name="rapidVoltageChanges" type="power:RapidVoltageChangesType"
2862     substitutionGroup="power:basePowerQualityMeasurement"/>
2863     <xs:element name="flicker" type="power:FlickerType"
2864     substitutionGroup="power:basePowerQualityMeasurement"/>
2865     <xs:element name="supplyVoltageDips" type="power:SupplyVoltageDipsType"
2866     substitutionGroup="power:basePowerQualityMeasurement"/>
2867     <xs:element name="shortInterruptions" type="power:ShortInterruptionsType"
2868     substitutionGroup="power:basePowerQualityMeasurement"/>
2869     <xs:element name="longInterruptions" type="power:LongInterruptionsType"
2870     substitutionGroup="power:basePowerQualityMeasurement"/>
2871     <xs:element name="temporaryOvervoltage" type="power:TemporaryOvervoltageType"
2872     substitutionGroup="power:basePowerQualityMeasurement"/>
2873     <xs:element name="supplyVoltageImbalance" type="power:SupplyVoltageImbalanceType"
2874     substitutionGroup="power:basePowerQualityMeasurement"/>
2875     <xs:element name="harmonicVoltage" type="power:HarmonicVoltageType"
2876     substitutionGroup="power:basePowerQualityMeasurement"/>
2877     <xs:element name="mainsVoltage" type="power:MainsVoltageType"
2878     substitutionGroup="power:basePowerQualityMeasurement"/>
2879     <!-- 6.2 Defines Power Quality Measure -->
2880     <xs:complexType name="PowerFrequencyType" mixed="false">
2881         <xs:annotation>
2882             <xs:documentation>measured Power frequency, e.g. 50.4, 59.9, ,
2883     measured as per referenced measurement protocol. 0 for DC
2884         </xs:documentation>
2885         </xs:annotation>
2886         <xs:complexContent mixed="false">
2887             <xs:extension base="power:BasePowerQualityMeasurementType">
2888                 <xs:sequence>
2889                     <xs:element name="frequency" type="xs:float"/>
2890                 </xs:sequence>
2891             </xs:extension>
2892         </xs:complexContent>
2893     </xs:complexType>
2894     <xs:complexType name="SupplyVoltageVariationsType" mixed="false">
2895         <xs:annotation>
2896             <xs:documentation>count of Supply Voltage Variations during the
2897     period, measured as per referenced measurement protocol
2898         </xs:documentation>
2899         </xs:annotation>
2900         <xs:complexContent mixed="false">
2901             <xs:extension base="power:BasePowerQualityMeasurementType">
2902                 <xs:sequence>
2903                     <xs:element name="count" type="xs:int"/>

```

```

2904         </xs:sequence>
2905     </xs:extension>
2906 </xs:complexContent>
2907 </xs:complexType>
2908 <xs:complexType name="RapidVoltageChangesType" mixed="false">
2909     <xs:annotation>
2910         <xs:documentation>count of Rapid Voltage Changes during the period,
2911 measured as per referenced measurement protocol
2912     </xs:documentation>
2913 </xs:annotation>
2914 <xs:complexContent mixed="false">
2915     <xs:extension base="power:BasePowerQualityMeasurementType">
2916         <xs:sequence>
2917             <xs:element name="count" type="xs:int"/>
2918         </xs:sequence>
2919     </xs:extension>
2920 </xs:complexContent>
2921 </xs:complexType>
2922 <xs:complexType name="FlickerType" mixed="false">
2923     <xs:annotation>
2924         <xs:documentation>count of Flicker during the period, measured as per
2925 referenced measurement protocol
2926     </xs:documentation>
2927 </xs:annotation>
2928 <xs:complexContent mixed="false">
2929     <xs:extension base="power:BasePowerQualityMeasurementType">
2930         <xs:sequence>
2931             <xs:element name="count" type="xs:int"/>
2932         </xs:sequence>
2933     </xs:extension>
2934 </xs:complexContent>
2935 </xs:complexType>
2936 <xs:complexType name="SupplyVoltageDipsType" mixed="false">
2937     <xs:annotation>
2938         <xs:documentation>count of Supply Voltage Dips during the period,
2939 measured as per referenced measurement protocol
2940     </xs:documentation>
2941 </xs:annotation>
2942 <xs:complexContent mixed="false">
2943     <xs:extension base="power:BasePowerQualityMeasurementType">
2944         <xs:sequence>
2945             <xs:element name="count" type="xs:int"/>
2946         </xs:sequence>
2947     </xs:extension>
2948 </xs:complexContent>
2949 </xs:complexType>
2950 <xs:complexType name="ShortInterruptionsType" mixed="false">
2951     <xs:annotation>
2952         <xs:documentation>count of Short Interruptions during the period,
2953 measured as per referenced measurement protocol
2954     </xs:documentation>
2955 </xs:annotation>
2956 <xs:complexContent mixed="false">
2957     <xs:extension base="power:BasePowerQualityMeasurementType">
2958         <xs:sequence>
2959             <xs:element name="count" type="xs:int"/>
2960         </xs:sequence>
2961     </xs:extension>
2962 </xs:complexContent>
2963 </xs:complexType>
2964 <xs:complexType name="LongInterruptionsType" mixed="false">
2965     <xs:annotation>
2966         <xs:documentation>count of Long Interruptions during the period,
2967 measured as per referenced measurement protocol
2968     </xs:documentation>
2969 </xs:annotation>
2970 <xs:complexContent mixed="false">
2971     <xs:extension base="power:BasePowerQualityMeasurementType">
2972         <xs:sequence>
2973             <xs:element name="count" type="xs:int"/>
2974         </xs:sequence>

```

```

2975         </xs:extension>
2976     </xs:complexContent>
2977 </xs:complexType>
2978 <xs:complexType name="TemporaryOvervoltageType" mixed="false">
2979     <xs:annotation>
2980         <xs:documentation>count of Temporary Overvoltage Events during the
2981 period, measured as per referenced measurement protocol
2982     </xs:documentation>
2983     </xs:annotation>
2984     <xs:complexContent mixed="false">
2985         <xs:extension base="power:BasePowerQualityMeasurementType">
2986             <xs:sequence>
2987                 <xs:element name="count" type="xs:int"/>
2988             </xs:sequence>
2989         </xs:extension>
2990     </xs:complexContent>
2991 </xs:complexType>
2992 <xs:complexType name="SupplyVoltageImbalanceType" mixed="false">
2993     <xs:annotation>
2994         <xs:documentation>count of Supply Voltage Imbalance events during the
2995 period, measured as per referenced measurement protocol. Not meaningful for DC.
2996     </xs:documentation>
2997     </xs:annotation>
2998     <xs:complexContent mixed="false">
2999         <xs:extension base="power:BasePowerQualityMeasurementType">
3000             <xs:sequence>
3001                 <xs:element name="count" type="xs:int"/>
3002             </xs:sequence>
3003         </xs:extension>
3004     </xs:complexContent>
3005 </xs:complexType>
3006 <xs:complexType name="HarmonicVoltageType" mixed="false">
3007     <xs:annotation>
3008         <xs:documentation>Harmonic Voltage during the period, measured as per
3009 referenced measurement protocol. For DC, distortion is with respect to a signal of 0 Hz,
3010 The period is usually much shorter than other power quality measures.
3011     </xs:documentation>
3012     </xs:annotation>
3013     <xs:complexContent mixed="false">
3014         <xs:extension base="power:BasePowerQualityMeasurementType">
3015             <xs:sequence>
3016                 <xs:element name="voltage" type="xs:float"/>
3017             </xs:sequence>
3018         </xs:extension>
3019     </xs:complexContent>
3020 </xs:complexType>
3021 <xs:complexType name="MainsVoltageType" mixed="false">
3022     <xs:annotation>
3023         <xs:documentation>Mains [Signaling] Voltage. Nominal value, e.g, 110,
3024 130, 220, 208. See referenced measurement protocol for definition.
3025     </xs:documentation>
3026     </xs:annotation>
3027     <xs:complexContent mixed="false">
3028         <xs:extension base="power:BasePowerQualityMeasurementType">
3029             <xs:sequence>
3030                 <xs:element name="voltage" type="xs:float"/>
3031             </xs:sequence>
3032         </xs:extension>
3033     </xs:complexContent>
3034 </xs:complexType>
3035 <xs:simpleType name="MeasurementProtocolType">
3036     <xs:union memberTypes="power:MeasurementProtocolEnumeratedType
3037 emix:EmixExtensionType"/>
3038 </xs:simpleType>
3039 <xs:simpleType name="MeasurementProtocolEnumeratedType">
3040     <xs:annotation>
3041         <xs:documentation>An identification of the standard or other protocol
3042 used to measure power quality. Sets definition for all other power
3043 attributes</xs:documentation>
3044     </xs:annotation>
3045     <xs:restriction base="xs:string">

```

3046  
3047  
3048  
3049  
3050

```
        <xs:enumeration value="EN 50160"/>
        <xs:enumeration value="IEEE 1549-2009"/>
    </xs:restriction>
</xs:simpleType>
</xs:schema>
```

3051

## F.2.3 Power Products.xsd

3052  
3053  
3054  
3055  
3056  
3057  
3058  
3059  
3060  
3061  
3062  
3063  
3064  
3065  
3066  
3067  
3068  
3069  
3070  
3071  
3072  
3073  
3074  
3075  
3076  
3077  
3078  
3079  
3080  
3081  
3082  
3083  
3084  
3085  
3086  
3087  
3088  
3089  
3090  
3091  
3092  
3093  
3094  
3095  
3096  
3097  
3098  
3099  
3100  
3101  
3102  
3103  
3104  
3105  
3106  
3107  
3108  
3109  
3110  
3111  
3112  
3113

```
<?xml version="1.0" encoding="UTF-8"?>
<!-- power-quality.xsd - Power Products for OASIS EMIX 1.0 WD23 (20110411)

Set includes:
  EMIX, EMIX-Requirements, EMIX-Warrants (emix)
  Power, Power-Contracts, Power-Quality (power)
  Resource (resource)

This set built on the WS-Calendar v1.0 PRD02 Schemas.
-->
<xs:schema xmlns:power="http://docs.oasis-open.org/ns/emix/power"
  xmlns:emix="http://docs.oasis-open.org/ns/emix"
  xmlns:xcal="urn:ietf:params:xml:ns:icalendar-2.0"
  xmlns:clm5ISO42173A="urn:un:uncefact:odelist:standard:5:ISO42173A:2010-04-07"
  xmlns:gml="http://www.opengis.net/gml/3.2" xmlns:xs="http://www.w3.org/2001/XMLSchema"
  targetNamespace="http://docs.oasis-open.org/ns/emix/power"
  elementFormDefault="qualified" attributeFormDefault="unqualified">
  <xs:include schemaLocation="power.xsd"/>
  <xs:import namespace="http://docs.oasis-open.org/ns/emix" schemaLocation="emix.xsd"/>
  <!-- 2.0 Power Products -->
  <xs:element name="powerProductDescription" type="power:PowerProductDescriptionType"
    substitutionGroup="emix:productDescription"/>
  <xs:complexType name="PowerProductDescriptionType" abstract="true">
    <xs:annotation>
      <xs:documentation>Type of Product Description for simple transactions.
Also used as template for other Power Product Description Types. A product is advertised
(or bought) with a constant power, which dictates the rate of delivery. After a
specified duration, energy has been delivered, at a price per energy, price per unit
energy</xs:documentation>
    </xs:annotation>
    <xs:complexContent>
      <xs:extension base="emix:ProductDescriptionType">
        <xs:sequence>
          <xs:element ref="power:productType"/>
          <xs:element ref="emix:emixInterface"/>
          <xs:element ref="power:unitEnergyPrice"/>
          <xs:element ref="power:powerItem"/>
          <xs:element name="charges"
type="power:ArrayOfCharges"/>
        </xs:sequence>
      </xs:extension>
    </xs:complexContent>
  </xs:complexType>
  <!-- 2.1 Full Requirements Power -->
  <xs:element name="fullRequirementsPower" type="power:FullRequirementsPowerType"
    substitutionGroup="power:powerProductDescription"/>
  <xs:complexType name="FullRequirementsPowerType">
    <xs:annotation>
      <xs:documentation>Type of Product Description for Supplier to provide
for full requirements of buyer. Simple prices, will supply all used. Demand Charges
Optional. Often used in retail residential rates.</xs:documentation>
    </xs:annotation>
    <xs:complexContent>
      <xs:extension base="power:PowerProductDescriptionType">
        <xs:sequence>
          <xs:element ref="emix:priceBase"/>
          <xs:element name="maximumPower"
type="emix:QuantityType"/>
          <xs:element name="minimumPower"
type="emix:QuantityType"/>
        </xs:sequence>
      </xs:extension>
    </xs:complexContent>
  </xs:complexType>
```

```

3114     </xs:complexContent>
3115 </xs:complexType>
3116 <!-- 2.2 Block Power Full Requirements -->
3117 <xs:element name="blockPowerFullRequirements"
3118 type="power:BlockPowerFullRequirementsType"
3119 substitutionGroup="power:powerProductDescription"/>
3120 <xs:complexType name="BlockPowerFullRequirementsType">
3121 <xs:annotation>
3122 <xs:documentation>Type of Product Description for Supplier to provide
3123 for full requirements of buyer in "blocks". Price is constant within a block, but
3124 changes as each block is used during a period. Demand Charges MAY be included. Often
3125 used in retail residential rates.</xs:documentation>
3126 </xs:annotation>
3127 <xs:complexContent>
3128 <xs:extension base="power:PowerProductDescriptionType">
3129 <xs:sequence minOccurs="1" maxOccurs="unbounded">
3130 <xs:element name="powerPriceTiers"
3131 type="power:ArrayOfBlockPowerPrices" minOccurs="1" maxOccurs="1"/>
3132 <xs:element name="maximumPower"
3133 type="emix:QuantityType" minOccurs="0" maxOccurs="1"/>
3134 <xs:element name="minimumPower"
3135 type="emix:QuantityType" minOccurs="0" maxOccurs="1"/>
3136 </xs:sequence>
3137 </xs:extension>
3138 </xs:complexContent>
3139 </xs:complexType>
3140 <!-- 2.3 Transport Service -->
3141 <xs:element name="transportProduct" type="power:TransportProductType"
3142 substitutionGroup="power:powerProductDescription"/>
3143 <xs:complexType name="TransportProductType">
3144 <xs:annotation>
3145 <xs:documentation>Type of Product Description for charges and revenue
3146 related to Transport Services for a Power Product, i.e., the movement of Power through
3147 Transmission and Distribution. The Interface used matches a segment of the transport
3148 infrastructure, usually identified by an injection node and a delivery
3149 node.</xs:documentation>
3150 </xs:annotation>
3151 <xs:complexContent>
3152 <xs:extension base="power:PowerProductDescriptionType">
3153 <xs:sequence>
3154 <xs:element name="transportCharges"
3155 type="power:ArrayOfTransportCharges"/>
3156 </xs:sequence>
3157 </xs:extension>
3158 </xs:complexContent>
3159 </xs:complexType>
3160 <!-- 2.1 TEMIX Power -->
3161 <xs:element name="temixPower" type="power:TemixPowerType"
3162 substitutionGroup="emix:productDescription"/>
3163 <xs:complexType name="TemixPowerType">
3164 <xs:annotation>
3165 <xs:documentation>Type of contract Product Description for Supplier to
3166 a specific sized block of power to buyer. Simple prices, will supply fixed block.
3167 Derived directly from emix:ProductDescriptionType rather than
3168 power:PowerProductDescriptionType because optionality stripped out.</xs:documentation>
3169 </xs:annotation>
3170 <xs:complexContent>
3171 <xs:extension base="emix:ProductDescriptionType">
3172 <xs:sequence>
3173 <xs:element ref="emix:emixInterface"/>
3174 <xs:element ref="emix:price" minOccurs="1"
3175 maxOccurs="1"/>
3176 <xs:element ref="power:powerItem" minOccurs="1"
3177 maxOccurs="1"/>
3178 <xs:element ref="power:energyItem" minOccurs="1"
3179 maxOccurs="1"/>
3180 <xs:element ref="emix:quantity" minOccurs="1"
3181 maxOccurs="1"/>
3182 </xs:sequence>
3183 </xs:extension>
3184 </xs:complexContent>

```

```

3185     </xs:complexType>
3186     <!--
3187 =====
3188 ===== -->
3189     <!-- Charge Defintions -->
3190     <!--
3191 =====
3192 ===== -->
3193     <!-- 2.5 Charge Abstractions -->
3194     <xs:element name="baseCharge" type="power:BaseChargeType" abstract="true">
3195         <xs:annotation>
3196             <xs:documentation>Abstract extension object for Emix Power Product
3197 Charges</xs:documentation>
3198             </xs:annotation>
3199         </xs:element>
3200     <xs:complexType name="ArrayOfCharges">
3201         <xs:annotation>
3202             <xs:documentation>Collection of Emix Power Product
3203 Charges</xs:documentation>
3204             </xs:annotation>
3205             <xs:sequence>
3206                 <xs:element ref="power:baseCharge" minOccurs="0"
3207 maxOccurs="unbounded"/>
3208             </xs:sequence>
3209         </xs:complexType>
3210     <xs:complexType name="BaseChargeType" abstract="true">
3211         <xs:annotation>
3212             <xs:documentation>Type of Abstract extension object for Emix Power
3213 Product Charges</xs:documentation>
3214             </xs:annotation>
3215         </xs:complexType>
3216     <!--
3217 =====
3218 ===== -->
3219     <!-- 2.6 General Charges -->
3220     <!-- 2.6.1 Blocks for use in Block Power -->
3221     <xs:element name="blockPowerPrice" type="power:BlockPowerPriceType"
3222 substitutionGroup="power:baseCharge"/>
3223     <xs:complexType name="BlockPowerPriceType" mixed="false">
3224         <xs:complexContent mixed="false">
3225             <xs:extension base="power:BaseChargeType">
3226                 <xs:sequence>
3227                     <xs:element ref="emix:priceBase"/>
3228                     <xs:element name="maximumEnergyQuantity"
3229 type="emix:QuantityType"/>
3230                 </xs:sequence>
3231             </xs:extension>
3232         </xs:complexContent>
3233     </xs:complexType>
3234     <xs:complexType name="ArrayOfBlockPowerPrices">
3235         <xs:annotation>
3236             <xs:documentation>Collection of Emix Block Power
3237 Prices</xs:documentation>
3238             </xs:annotation>
3239             <xs:sequence>
3240                 <xs:element ref="power:blockPowerPrice" minOccurs="0"
3241 maxOccurs="unbounded"/>
3242             </xs:sequence>
3243         </xs:complexType>
3244     <!--
3245 =====
3246 ===== -->
3247     <!-- 2.6.2 Demand Charges -->
3248     <xs:element name="demandCharge" type="power:DemandChargeType"
3249 substitutionGroup="power:baseCharge"/>
3250     <xs:complexType name="DemandChargeType" mixed="false">
3251         <xs:complexContent mixed="false">
3252             <xs:extension base="power:BaseChargeType">
3253                 <xs:sequence>
3254                     <xs:element name="demandChargeUnits"
3255 type="power:PowerItemType"/>

```

```

3256                                     <xs:element name="demandChargeFloor"
3257 type="emix:QuantityType"/>
3258                                     <xs:element name="demandChargeRate"
3259 type="emix:PriceBaseType"/>
3260                                     <xs:element name="measurementInterval"
3261 type="emix:DurationType"/>
3262                                     <xs:element name="collectionInterval"
3263 type="emix:DurationType"/>
3264                                     <xs:element name="collectionPeriod"
3265 type="emix:DurationType"/>
3266                                     <xs:element name="chargeDuration"
3267 type="emix:DurationType"/>
3268                                     </xs:sequence>
3269                                 </xs:extension>
3270                            </xs:complexContent>
3271                    </xs:complexType>
3272                    <!--
3273                    =====
3274                    ===== -->
3275                    <!-- Transport Charges and Losses Types -->
3276                    <!--
3277                    =====
3278                    ===== -->
3279                    <!-- 2.7 Transport Abstract Types -->
3280                    <xs:element name="baseTransportCharge" type="power:BaseTransportChargeType"
3281 abstract="true" substitutionGroup="power:baseCharge">
3282                        <xs:annotation>
3283                            <xs:documentation>Abstract extension object for Emix Power Product
3284 Charges</xs:documentation>
3285                        </xs:annotation>
3286                    </xs:element>
3287                    <xs:complexType name="ArrayOfTransportCharges">
3288                        <xs:annotation>
3289                            <xs:documentation>Collection of Emix Power Transport Product
3290 Charges</xs:documentation>
3291                        </xs:annotation>
3292                        <xs:sequence>
3293                            <xs:element ref="power:baseTransportCharge" minOccurs="0"
3294 maxOccurs="unbounded"/>
3295                        </xs:sequence>
3296                    </xs:complexType>
3297                    <xs:complexType name="BaseTransportChargeType" abstract="true" mixed="false">
3298                        <xs:annotation>
3299                            <xs:documentation>Type of Abstract extension object for Emix
3300 Transport Charges</xs:documentation>
3301                        </xs:annotation>
3302                        <xs:complexContent mixed="false">
3303                            <xs:extension base="power:BaseChargeType"/>
3304                        </xs:complexContent>
3305                    </xs:complexType>
3306                    <!--
3307                    =====
3308                    ===== -->
3309                    <!-- 2.8 Congestion and Loss Charges -->
3310                    <!-- 2.8.1 Congestion Revenue Rights Charge-->
3311                    <xs:element name="congestionRevenueRights" type="power:CongestionRevenueRightsType"
3312 substitutionGroup="power:baseTransportCharge">
3313                        <xs:complexType name="CongestionRevenueRightsType" mixed="false">
3314                            <xs:annotation>
3315                                <xs:documentation>Financial Hedge for Congestion, a forward contract
3316 for congestion revenues to potentially offset congestion charges. Also known as
3317 Financial Transmission Rights or Congestion Revenue Rights</xs:documentation>
3318                            </xs:annotation>
3319                            <xs:complexContent mixed="false">
3320                                <xs:extension base="power:BaseTransportChargeType">
3321                                    <xs:sequence>
3322                                        <xs:element ref="power:transportInterface"/>
3323                                        <xs:element ref="power:transportCongestionFee"/>
3324                                    </xs:sequence>
3325                                </xs:extension>
3326                            </xs:complexContent>

```

```

3327     </xs:complexType>
3328     <!-- 2.8.2 Congestion Charge-->
3329     <xs:element name="congestionCharge" type="power:CongestionChargeType"
3330 substitutionGroup="power:baseTransportCharge"/>
3331     <xs:complexType name="CongestionChargeType" mixed="false">
3332         <xs:annotation>
3333             <xs:documentation>Congestion Charge is the cost of purchasing the
3334 right to transfer power over a given segment of the grid.</xs:documentation>
3335         </xs:annotation>
3336         <xs:complexContent mixed="false">
3337             <xs:extension base="power:BaseTransportChargeType">
3338                 <xs:sequence>
3339                     <xs:element ref="power:transportInterface"/>
3340                     <xs:element ref="power:transportCongestionFee"/>
3341                 </xs:sequence>
3342             </xs:extension>
3343         </xs:complexContent>
3344     </xs:complexType>
3345     <!-- 2.8.3 Marginal Loss Charge -->
3346     <xs:element name="marginalLossCharge" type="power:MarginalLossChargeType"
3347 substitutionGroup="power:baseTransportCharge"/>
3348     <xs:complexType name="MarginalLossChargeType" mixed="false">
3349         <xs:complexContent mixed="false">
3350             <xs:extension base="power:BaseTransportChargeType">
3351                 <xs:sequence>
3352                     <xs:element ref="power:marginalLossFee"/>
3353                 </xs:sequence>
3354             </xs:extension>
3355         </xs:complexContent>
3356     </xs:complexType>
3357     <!-- 2.8.4 Marginal Loss -->
3358     <xs:element name="marginalLoss" type="power:MarginalLossType"
3359 substitutionGroup="power:baseTransportCharge"/>
3360     <xs:complexType name="MarginalLossType" mixed="false">
3361         <xs:complexContent mixed="false">
3362             <xs:extension base="power:BaseTransportChargeType">
3363                 <xs:sequence>
3364                     <xs:element ref="power:lossFactor"/>
3365                 </xs:sequence>
3366             </xs:extension>
3367         </xs:complexContent>
3368     </xs:complexType>
3369     <!-- 2.8.5 Conversion Loss -->
3370     <xs:element name="conversionLoss" type="power:ConversionLossType"
3371 substitutionGroup="power:baseTransportCharge"/>
3372     <xs:complexType name="ConversionLossType" mixed="false">
3373         <xs:complexContent mixed="false">
3374             <xs:extension base="power:BaseTransportChargeType">
3375                 <xs:sequence>
3376                     <xs:element ref="power:pnode"/>
3377                     <xs:element ref="power:lossFactor"/>
3378                 </xs:sequence>
3379             </xs:extension>
3380         </xs:complexContent>
3381     </xs:complexType>
3382     <xs:element name="transportAccessFee" type="power:TransportAccessFeeType"
3383 substitutionGroup="power:baseTransportCharge"/>
3384     <xs:complexType name="TransportAccessFeeType" mixed="false">
3385         <xs:annotation>
3386             <xs:documentation>Transport Access Fee is a Fixed Charge (not
3387 dependent on congestion or quantity) to access a transport system.</xs:documentation>
3388         </xs:annotation>
3389         <xs:complexContent mixed="false">
3390             <xs:extension base="power:BaseTransportChargeType">
3391                 <xs:sequence>
3392                     <xs:element ref="power:transportInterface"/>
3393                     <xs:element ref="emix:price"/>
3394                 </xs:sequence>
3395             </xs:extension>
3396         </xs:complexContent>
3397     </xs:complexType>

```

```

3398 <!--
3399 ===== -->
3400 <!-- 2.9 Elemental Charge and Loss Types -->
3401 <!--
3402 ===== -->
3403 <!-- 2.9.3 Loss Fee -->
3404 <xs:element name="marginalLossFee" type="power:MarginalLossFeeType"/>
3405 <xs:simpleType name="MarginalLossFeeType">
3406 <xs:annotation>
3407 <xs:documentation>Marginal Loss Fee</xs:documentation>
3408 </xs:annotation>
3409 <xs:restriction base="xs:decimal"/>
3410 </xs:simpleType>
3411 <!-- 2.9.4 Transport Congestion Fee -->
3412 <xs:element name="transportCongestionFee" type="power:TransportCongestionFeeType"/>
3413 <xs:simpleType name="TransportCongestionFeeType">
3414 <xs:annotation>
3415 <xs:documentation>Financial Transmission Rights (FTR) regarding
3416 transmission capacity.</xs:documentation>
3417 </xs:annotation>
3418 <xs:restriction base="xs:decimal"/>
3419 </xs:simpleType>
3420 <!-- 2.9.5 Loss Factor -->
3421 <xs:element name="lossFactor" type="power:LossFactorType"/>
3422 <xs:simpleType name="LossFactorType">
3423 <xs:annotation>
3424 <xs:documentation>Reduction in amount delivered as product travels.
3425 (lossFactor * purchase amount) = delivered amount</xs:documentation>
3426 </xs:annotation>
3427 <xs:restriction base="xs:float">
3428 <xs:maxInclusive value="1"/>
3429 </xs:restriction>
3430 </xs:simpleType>
3431 <!-- 2.9.6 Enumeration & Simple Types for Products -->
3432 <xs:element name="productType" type="power:ProductTypeType"/>
3433 <xs:simpleType name="ProductTypeType">
3434 <xs:union memberTypes="power:ProductTypeEnumeratedType emix:EmixExtensionType
3435 power:PowerOptionTypeType"/>
3436 </xs:simpleType>
3437 <xs:simpleType name="ProductTypeEnumeratedType">
3438 <xs:restriction base="xs:string">
3439 <xs:enumeration value="Energy"/>
3440 <xs:enumeration value="Transport"/>
3441 <xs:enumeration value="EnergyOption"/>
3442 <xs:enumeration value="TransportOption"/>
3443 <xs:enumeration value="FullRequirementsPower"/>
3444 <xs:enumeration value="FullRequirementsPowerWithDemandCharge"/>
3445 <xs:enumeration value="FullRequirementsPowerWithMaximumAndMinimum"/>
3446 <xs:enumeration value="HourlyDayAhead"/>
3447 <xs:enumeration value="Ex-AnteRealTimePrice"/>
3448 <xs:enumeration value="TimeOfUsePricing"/>
3449 <xs:enumeration value="Transport"/>
3450 <xs:enumeration value="CongestionRevenueRights"/>
3451 </xs:restriction>
3452 </xs:simpleType>
3453 </xs:schema>
3454
3455

```

### 3456 F.3 Resource.xsd

```

3457 <?xml version="1.0" encoding="UTF-8"?>
3458 <!-- edited with XMLSpy v2011 rel. 2 (x64) (http://www.altova.com) by Toby Considine
3459 (TC9, Inc) -->
3460 <!-- resource.xsd - Resource Descriptions for OASIS EMIX 1.0 WD23 (20110411)
3461
3462 Set includes:
3463 EMIX, EMIX-Requirements, EMIX-Warrants (emix)
3464 Power, Power-Contracts, Power-Quality (power)
3465 Resource (resource)

```

3466  
3467  
3468  
3469  
3470  
3471  
3472  
3473  
3474  
3475  
3476  
3477  
3478  
3479  
3480  
3481  
3482  
3483  
3484  
3485  
3486  
3487  
3488  
3489  
3490  
3491  
3492  
3493  
3494  
3495  
3496  
3497  
3498  
3499  
3500  
3501  
3502  
3503  
3504  
3505  
3506  
3507  
3508  
3509  
3510  
3511  
3512  
3513  
3514  
3515  
3516  
3517  
3518  
3519  
3520  
3521  
3522  
3523  
3524  
3525  
3526  
3527  
3528  
3529  
3530  
3531  
3532  
3533  
3534  
3535  
3536

```
This set built on the WS-Calendar v1.0 PRD02 Schemas.
-->
<xs:schema xmlns:resource="http://docs.oasis-open.org/ns/emix/power/resource"
xmlns:power="http://docs.oasis-open.org/ns/emix/power" xmlns:emix="http://docs.oasis-
open.org/ns/emix" xmlns:ical="urn:ietf:params:xml:ns:icalendar-2.0"
xmlns:clm5ISO42173A="urn:un:unece:uncefact:odelist:standard:5:ISO42173A:2010-04-07"
xmlns:gml="http://www.opengis.net/gml/3.2" xmlns:xs="http://www.w3.org/2001/XMLSchema"
targetNamespace="http://docs.oasis-open.org/ns/emix/power/resource"
elementFormDefault="qualified" attributeFormDefault="unqualified">
  <xs:import namespace="http://docs.oasis-open.org/ns/emix" schemaLocation="emix.xsd"/>
  <xs:import namespace="http://docs.oasis-open.org/ns/emix/power"
schemaLocation="power.xsd"/>
  <!-- 3.0 Resource are described in terms of their capabilities Capabilities to aid in
the matching of need and supplier -->
  <xs:element name="loadReduction" type="resource:LoadReductionType"
substitutionGroup="emix:productDescription"/>
  <xs:element name="generation" type="resource:GenerationType"
substitutionGroup="emix:productDescription"/>
  <xs:element name="activeReserve" type="resource:ActiveReserveType"
substitutionGroup="emix:productDescription"/>
  <xs:element name="regulationService" type="resource:RegulationServiceType"
substitutionGroup="emix:productDescription"/>
  <xs:element name="productVoltageRegulation"
type="resource:ProductVoltageRegulationType"
substitutionGroup="emix:productDescription"/>
  <!-- 3.1 Load resource -->
  <xs:complexType name="LoadReductionType">
    <xs:annotation>
      <xs:documentation>A Load Reduction Resource ramps down, stays down,
and then ramps up. For stagingRamps, endRamp is less than beginRamp. For recoveryRamps,
endRamp is greater than beginRamp.</xs:documentation>
    </xs:annotation>
    <xs:complexContent>
      <xs:extension base="resource:PowerResponseType"/>
    </xs:complexContent>
  </xs:complexType>
  <!-- 3.2 Generation Resource -->
  <xs:complexType name="GenerationType">
    <xs:annotation>
      <xs:documentation>A Generation Resource ramps up, stays up, and then
ramps down. For stagingRamps, endRamp is greater than beginRamp. For recoveryRamps,
endRamp is less than beginRamp.</xs:documentation>
    </xs:annotation>
    <xs:complexContent>
      <xs:extension base="resource:PowerResponseType">
        <xs:sequence>
          <xs:element name="Type"
type="resource:ResourceTypeType" minOccurs="0" maxOccurs="1"/>
        </xs:sequence>
      </xs:extension>
    </xs:complexContent>
  </xs:complexType>
  <!-- 3.5 Active Reserve -->
  <xs:complexType name="ActiveReserveType">
    <xs:annotation>
      <xs:documentation>Active Reserve</xs:documentation>
    </xs:annotation>
    <xs:complexContent>
      <xs:extension base="resource:ResourceDescriptionType">
        <xs:sequence>
          <xs:element ref="power:powerOptionType"/>
          <xs:element ref="resource:targetRegulation"/>
          <xs:element ref="resource:dispatchTime"/>
          <xs:element ref="emix:autonomous" minOccurs="0">
            <xs:annotation>
              <xs:documentation>Resource provides
autonomous management of its local circuits. If true, service notes local conditions and
dispatches itself. If false, it waits for dispatch request from VTN.</xs:documentation>
            </xs:annotation>
          </xs:element>
        </xs:sequence>
      </xs:extension>
    </xs:complexContent>
  </xs:complexType>
  </xs:element>
```

```

3537         <xs:element ref="resource:maximumDeliveryRate"/>
3538         <xs:element ref="resource:minimumDeliveryRate"/>
3539     </xs:sequence>
3540 </xs:extension>
3541 </xs:complexContent>
3542 </xs:complexType>
3543 <!-- 3.6 Regulation Service Product -->
3544 <xs:complexType name="RegulationServiceType">
3545     <xs:annotation>
3546         <xs:documentation>Regulation Service</xs:documentation>
3547     </xs:annotation>
3548     <xs:complexContent>
3549         <xs:extension base="resource:ResourceDescriptionType">
3550             <xs:sequence>
3551                 <xs:element ref="resource:productTypeRegulation"/>
3552                 <xs:element ref="resource:targetRegulation"/>
3553                 <xs:element ref="resource:dispatchUp"/>
3554                 <xs:element ref="resource:dispatchDown"/>
3555                 <xs:element ref="emix:autonomous"/>
3556                 <!-- frequency response faster than freq regulation -->
3557             </xs:sequence>
3558         </xs:extension>
3559     </xs:complexContent>
3560 </xs:complexType>
3561 <!-- 3.6 Voltage Regulation -->
3562 <xs:complexType name="ProductVoltageRegulationType">
3563     <xs:annotation>
3564         <xs:documentation>Voltage Regulation</xs:documentation>
3565         <xs:appinfo>At the end of the scheduled interval, VAR resources should
3566 return to their original state</xs:appinfo>
3567     </xs:annotation>
3568     <xs:complexContent>
3569         <xs:extension base="resource:ResourceDescriptionType">
3570             <xs:sequence>
3571                 <!-- *** <xs:element name="voltVar"
3572 type="resource:VoltVarType" maxOccurs="unbounded"/> -->
3573                 <xs:element ref="resource:rampTime">
3574                     <xs:annotation>
3575                         <xs:documentation>Requested ramp time to
3576 move from the current setpoint to the new setpoint</xs:documentation>
3577                     </xs:annotation>
3578                 </xs:element>
3579                 <xs:element ref="resource>window">
3580                     <xs:annotation>
3581                         <xs:documentation>Time window within
3582 which to randomly execute the command. If the time window is zero, the command will be
3583 executed immediately, (if not included, then default time window for this function will
3584 be used)</xs:documentation>
3585                     </xs:annotation>
3586                 </xs:element>
3587             </xs:sequence>
3588         </xs:extension>
3589     </xs:complexContent>
3590 </xs:complexType>
3591 <!-- 3.9 Resource Description -->
3592 <xs:complexType name="ResourceDescriptionType">
3593     <xs:annotation>
3594         <xs:documentation>Resource Description based on the EMIX Product
3595 Description.</xs:documentation>
3596     </xs:annotation>
3597     <xs:complexContent>
3598         <xs:extension base="emix:ProductDescriptionType">
3599             <xs:sequence>
3600                 <xs:element ref="resource:mrid"/>
3601                 <xs:element ref="emix:emixInterface"/>
3602                 <xs:element ref="emix:constraints" minOccurs="0"
3603 maxOccurs="1"/>
3604             </xs:sequence>
3605         </xs:extension>
3606     </xs:complexContent>
3607 </xs:complexType>

```

```

3608 <!-- 3.9.1 Resource Types -->
3609 <xs:element name="resourceType" type="resource:ResourceTypeType"/>
3610 <xs:simpleType name="ResourceTypeType">
3611   <xs:union memberTypes="resource:ResourceTypeEnumeratedType
3612 emix:EmixExtensionType"/>
3613 </xs:simpleType>
3614 <xs:simpleType name="ResourceTypeEnumeratedType">
3615   <xs:annotation>
3616     <xs:documentation>Resource types share common responsiveness and
3617 predictability characteristics, sometimes covarying across resources in the same class.
3618 (Example: Solar in the same region failing at the same time)</xs:documentation>
3619   </xs:annotation>
3620   <xs:restriction base="xs:token">
3621     <xs:enumeration value="DispatchableHydro"/>
3622     <xs:enumeration value="NonDispatchableHydro"/>
3623     <xs:enumeration value="WindGeneration"/>
3624     <xs:enumeration value="SolarGeneration"/>
3625     <xs:enumeration value="TollingContract"/>
3626     <xs:enumeration value="AggregateResource"/>
3627     <xs:enumeration value="DispatchableStorage"/>
3628   </xs:restriction>
3629 </xs:simpleType>
3630 <!-- 3.9.2 Regulation Products -->
3631 <xs:element name="productTypeRegulation" type="resource:ProductTypeRegulationType"/>
3632 <xs:simpleType name="ProductTypeRegulationType">
3633   <xs:annotation>
3634     <xs:documentation>enumerates the Voltage Regulation
3635 Products</xs:documentation>
3636   </xs:annotation>
3637   <xs:restriction base="xs:string">
3638     <xs:enumeration value="RegulationUp"/>
3639     <xs:enumeration value="RegulationDn"/>
3640     <xs:enumeration value="RegulationUp-Dn"/>
3641   </xs:restriction>
3642 </xs:simpleType>
3643 <!-- 4.0 Resource Semantics -->
3644 <!-- 4.1 Resource Capability -->
3645 <xs:element name="powerResponse" type="resource:PowerResponseType"/>
3646 <xs:complexType name="PowerResponseType" abstract="true">
3647   <xs:annotation>
3648     <xs:documentation>Generic model describing the power response
3649 capabilities of a resource</xs:documentation>
3650   </xs:annotation>
3651   <xs:complexContent>
3652     <xs:extension base="resource:ResourceDescriptionType">
3653       <xs:sequence>
3654         <xs:element ref="resource:stagingRamp" minOccurs="0"
3655 maxOccurs="1"/>
3656         <xs:element ref="resource:maximumResponse"
3657 minOccurs="0" maxOccurs="1"/>
3658         <xs:element ref="resource:minimumResponse"
3659 maxOccurs="1"/>
3660         <xs:element ref="resource:recoveryRamp" minOccurs="0"
3661 maxOccurs="1"/>
3662         <xs:element ref="resource:offerCurve" minOccurs="0"
3663 maxOccurs="1"/>
3664       </xs:sequence>
3665     </xs:extension>
3666   </xs:complexContent>
3667 </xs:complexType>
3668 <!-- 4.1 Ramp Rates -->
3669 <!-- 4.1.3 Power Ramp Rate -->
3670 <xs:element name="stagingRamp" type="resource:ArrayOfRampSegments"/>
3671 <xs:element name="recoveryRamp" type="resource:ArrayOfRampSegments"/>
3672 <xs:element name="powerRamp" type="resource:ArrayOfRampSegments"/>
3673 <xs:complexType name="PowerRampType">
3674   <xs:annotation>
3675     <xs:documentation>A Power Ramp is an Array of of Ramp Segments that
3676 describing a Resource's ability to change level. A Power Ramp is either monotonically
3677 increasing or monotonically decreasing.</xs:documentation>
3678   </xs:annotation>

```

```

3679     <xs:sequence>
3680         <xs:element ref="resource:rampSegments"/>
3681     </xs:sequence>
3682 </xs:complexType>
3683 <xs:element name="rampSegments" type="resource:ArrayOfRampSegments"/>
3684 <xs:complexType name="ArrayOfRampSegments">
3685     <xs:annotation>
3686         <xs:documentation>Collection of Power Ramp Segments</xs:documentation>
3687     </xs:annotation>
3688     <xs:sequence>
3689         <xs:element ref="resource:powerRampSegment" minOccurs="0"
3690 maxOccurs="unbounded"/>
3691     </xs:sequence>
3692 </xs:complexType>
3693 <xs:element name="powerRampSegment" type="resource:PowerRampSegmentType"/>
3694 <xs:complexType name="PowerRampSegmentType">
3695     <xs:annotation>
3696         <xs:documentation>A Power Ramp Segment describes a change up or down
3697 in units/duration. A ramp rate holds for the duration between beginRamp to
3698 endRamp</xs:documentation>
3699     </xs:annotation>
3700     <xs:sequence>
3701         <xs:element name="rate" type="power:PowerQuantityType"/>
3702         <xs:element ref="emix:duration"/>
3703         <xs:element ref="resource:beginRamp"/>
3704         <xs:element ref="resource:endRamp"/>
3705         <xs:element ref="emix:integralOnly"/>
3706     </xs:sequence>
3707 </xs:complexType>
3708 <xs:element name="beginRamp" type="xs:int"/>
3709 <xs:element name="endRamp" type="xs:int"/>
3710 <!-- 4.1.4 Power Ramp Rate -->
3711 <xs:element name="percentRampRate" type="resource:PercentRampRateType"/>
3712 <xs:complexType name="PercentRampRateType">
3713     <xs:annotation>
3714         <xs:documentation>Change up or down in percent of total
3715 response.</xs:documentation>
3716     </xs:annotation>
3717     <xs:sequence>
3718         <xs:element ref="resource:rate"/>
3719         <xs:element ref="emix:duration"/>
3720     </xs:sequence>
3721 </xs:complexType>
3722 <!-- 4.2 Constraints and Requirements unique to Power Resources-->
3723 <xs:element name="minimumLoad" type="resource:MinimumLoadType"
3724 substitutionGroup="emix:baseConstraint">
3725     <xs:annotation>
3726         <xs:documentation>Constraint on Minimum Load that a Resource can
3727 maintain</xs:documentation>
3728     </xs:annotation>
3729 </xs:element>
3730 <xs:element name="maximumPower" type="resource:MaximumPowerType"
3731 substitutionGroup="emix:baseConstraint">
3732     <xs:annotation>
3733         <xs:documentation>Constraint on Maximum Power available from a
3734 resource</xs:documentation>
3735     </xs:annotation>
3736 </xs:element>
3737 <xs:element name="maximumEnergy" type="resource:MaximumEnergyType"
3738 substitutionGroup="emix:baseConstraint">
3739     <xs:annotation>
3740         <xs:documentation>Constraint on Maximum Energy available from a
3741 resource</xs:documentation>
3742     </xs:annotation>
3743 </xs:element>
3744 <xs:element name="minimumLoadReduction" type="resource:MinimumLoadReductionType"
3745 substitutionGroup="emix:baseConstraint">
3746     <xs:annotation>
3747         <xs:documentation>Constraint on Minimum Load Reduction resource can
3748 make</xs:documentation>
3749     </xs:annotation>

```

```

3750     </xs:element>
3751     <xs:complexType name="MinimumLoadType" mixed="false">
3752       <xs:annotation>
3753         <xs:documentation>type of Constraint on Minimum Load that a Resource
3754 can maintain</xs:documentation>
3755       </xs:annotation>
3756       <xs:complexContent mixed="false">
3757         <xs:extension base="emix:BaseConstraintType">
3758           <xs:sequence>
3759             <xs:element ref="power:powerQuantity"/>
3760           </xs:sequence>
3761         </xs:extension>
3762       </xs:complexContent>
3763     </xs:complexType>
3764     <xs:complexType name="MaximumPowerType" mixed="false">
3765       <xs:annotation>
3766         <xs:documentation>Type of Constraint on Maximum Power available from a
3767 resource</xs:documentation>
3768       </xs:annotation>
3769       <xs:complexContent mixed="false">
3770         <xs:extension base="emix:BaseConstraintType">
3771           <xs:sequence>
3772             <xs:element ref="power:powerQuantity" minOccurs="1"
3773 maxOccurs="1"/>
3774           </xs:sequence>
3775         </xs:extension>
3776       </xs:complexContent>
3777     </xs:complexType>
3778     <xs:complexType name="MaximumEnergyType" mixed="false">
3779       <xs:annotation>
3780         <xs:documentation> Type of Constraint on Maximum Energy available from
3781 a resource</xs:documentation>
3782       </xs:annotation>
3783       <xs:complexContent mixed="false">
3784         <xs:extension base="emix:BaseConstraintType">
3785           <xs:sequence>
3786             <xs:element ref="power:energyQuantity"/>
3787           </xs:sequence>
3788         </xs:extension>
3789       </xs:complexContent>
3790     </xs:complexType>
3791     <!-- 4.2.5 Minimum Load Reduction -->
3792     <xs:complexType name="MinimumLoadReductionType" mixed="false">
3793       <xs:annotation>
3794         <xs:documentation>Minimum units for a load reduction (e.g., MW rating
3795 of a discrete pump)</xs:documentation>
3796       </xs:annotation>
3797       <xs:complexContent mixed="false">
3798         <xs:extension base="emix:BaseConstraintType">
3799           <xs:sequence>
3800             <xs:element ref="power:powerQuantity" minOccurs="1"
3801 maxOccurs="1"/>
3802           </xs:sequence>
3803         </xs:extension>
3804       </xs:complexContent>
3805     </xs:complexType>
3806     <!-- 4.3.1 Offer Segment elements -->
3807     <xs:element name="offerCurve" type="resource:OfferCurveType"
3808 substitutionGroup="emix:baseRequirement"/>
3809     <xs:complexType name="OfferCurveType" mixed="false">
3810       <xs:annotation>
3811         <xs:documentation>Type of a collection of Offer Segments used to
3812 compute cost requirements across a range of power.</xs:documentation>
3813       </xs:annotation>
3814       <xs:complexContent mixed="false">
3815         <xs:extension base="emix:BaseRequirementType">
3816           <xs:sequence>
3817             <xs:element name="offerSegment"
3818 type="resource:OfferSegmentType" maxOccurs="unbounded"/>
3819           </xs:sequence>
3820         </xs:extension>

```

```

3821     </xs:complexContent>
3822 </xs:complexType>
3823 <xs:element name="offerSegment" type="resource:OfferSegmentType"/>
3824 <xs:complexType name="OfferSegmentType">
3825     <xs:annotation>
3826         <xs:documentation> Type of Marginal offer for Power within a range.
3827 Marginal costs must be computed within the context of a range of segments as conformed
3828 by the Offer Type</xs:documentation>
3829     </xs:annotation>
3830     <xs:sequence>
3831         <xs:element ref="emix:price"/>
3832         <xs:element ref="emix:quantity"/>
3833         <xs:element ref="power:powerItem"/>
3834         <xs:element ref="emix:integralOnly"/>
3835     </xs:sequence>
3836 </xs:complexType>
3837 <!-- 4.3.9 Resource ID -->
3838 <xs:element name="mrid" type="resource:MridType"/>
3839 <xs:simpleType name="MridType">
3840     <xs:annotation>
3841         <xs:documentation>multi-part resource id from the ISO TC57
3842 CIM.</xs:documentation>
3843     </xs:annotation>
3844     <xs:restriction base="xs:string"/>
3845 </xs:simpleType>
3846 <!-- 4.4 Volt-Var Elements -->
3847 <!-- 4.4.1 VMin -->
3848 <!-- These are the 4 parts of an inverter.. -->
3849 <xs:element name="vMin" type="resource:VMinType"/>
3850 <xs:complexType name="VMinType">
3851     <xs:annotation>
3852         <xs:documentation>The minimum voltage level of the Voltage Regulation
3853 Service. In IEEE 1547, this represents a voltage level of 88% of nominal voltage for a
3854 photovoltaic (PV) inverter.</xs:documentation>
3855     </xs:annotation>
3856     <xs:sequence>
3857         <xs:element ref="power:voltage"/>
3858     </xs:sequence>
3859 </xs:complexType>
3860 <!-- 4.4.2 VMax -->
3861 <xs:element name="vMax" type="resource:VMaxType"/>
3862 <xs:complexType name="VMaxType">
3863     <xs:annotation>
3864         <xs:documentation>VMax is the IEEE 1547 maximum voltage level of 110%
3865 of nominal voltage where the PV inverter must disconnect.</xs:documentation>
3866     </xs:annotation>
3867     <xs:sequence>
3868         <xs:element ref="power:voltage"/>
3869     </xs:sequence>
3870 </xs:complexType>
3871 <!-- 4.4.3 QMax -->
3872 <xs:element name="qMax" type="resource:QMaxType"/>
3873 <xs:complexType name="QMaxType">
3874     <xs:annotation>
3875         <xs:documentation>Qmax is the inverter's var capability and may be
3876 positive (capacitive) or negative (inductive).</xs:documentation>
3877     </xs:annotation>
3878     <xs:sequence>
3879         <xs:element ref="power:varQuantity"/>
3880     </xs:sequence>
3881 </xs:complexType>
3882 <!-- 4.4.4 volt-var -->
3883 <xs:element name="pMax" type="resource:PMaxType"/>
3884 <xs:complexType name="PMaxType">
3885     <xs:annotation>
3886         <xs:documentation>PMax is the inverter's watt capability and may be
3887 positive or negative. </xs:documentation>
3888     </xs:annotation>
3889     <xs:sequence>
3890         <xs:element ref="power:powerQuantity"/>
3891     </xs:sequence>

```

```

3892 </xs:complexType>
3893 <!-- 4.9 Miscelenous Semantic elementsvolt-var -->
3894 <xs:element name="dispatchTime" type="emix:DurationType"/>
3895 <xs:element name="maximumDeliveryRate" type="emix:QuantityType"/>
3896 <xs:element name="minimumDeliveryRate" type="emix:QuantityType"/>
3897 <xs:element name="maximumResponse" type="emix:QuantityType"/>
3898 <xs:element name="minimumResponse" type="emix:QuantityType"/>
3899 <xs:element name="rate" type="emix:QuantityType"/>
3900 <xs:element name="targetRegulation" type="power:PowerAttributesType"/>
3901 <xs:element name="dispatchUp" type="emix:DurationType">
3902   <xs:annotation>
3903     <xs:documentation>Time in which resource can respond to a request to
3904 increase energy provided. If zero, no dispatchUp available. Can also be startup delay
3905 for non-spinning reserve.</xs:documentation>
3906   </xs:annotation>
3907 </xs:element>
3908 <xs:element name="dispatchDown" type="emix:DurationType">
3909   <xs:annotation>
3910     <xs:documentation>Time in which resource can respond to a request to
3911 decrease energy provided. If zero, no dispatch Down available.</xs:documentation>
3912   </xs:annotation>
3913 </xs:element>
3914 <xs:element name="rampTime" type="emix:DurationType">
3915   <xs:annotation>
3916     <xs:documentation>Requested ramp time to move from the current
3917 setpoint to the new setpoint</xs:documentation>
3918   </xs:annotation>
3919 </xs:element>
3920 <xs:element name="window" type="emix:DurationType">
3921   <xs:annotation>
3922     <xs:documentation>Time window within which to randomly execute the
3923 command. If the time window is zero, the command will be executed immediately, (If not
3924 included, then default time window for this function will be used)</xs:documentation>
3925   </xs:annotation>
3926 </xs:element>
3927 </xs:schema>

```

3928

## G. An Example

3929

24 Hours of pricing on a full requirements contract.

3930

3931

3932

3933

3934

3935

3936

3937

3938

3939

3940

3941

3942

3943

3944

3945

3946

3947

3948

3949

3950

3951

3952

3953

3954

3955

3956

3957

3958

3959

3960

3961

3962

3963

3964

3965

3966

3967

3968

3969

3970

3971

3972

3973

3974

3975

3976

3977

3978

3979

3980

3981

3982

3983

3984

3985

```
<?xml version="1.0" encoding="utf-16"?>
<!--
Jira 274 Price Publication
  emix = EMIXType
  createdDateTime = 2-12-2011 14:00
  transactive State = Tender
  currency = USD

  terms:
  PriceType = absolutePrice

  Gluon: StartTime = 2-13-2001 00:00, Duration = 3600 seconds
  Intervals (0.71,0.21,-0.13, 0.15,0.70,0.86,0.90,1.01,1.12,1.14,1.15,2.74,
            1.25,1.20,1.29,1.31,1.00,0.99,0.89,0.86,0.79,0.88,0.87,0.76)
-->
<emix:product xmlns:power="http://docs.oasis-open.org/ns/emix/power"
  xmlns:emix="http://docs.oasis-open.org/ns/emix" xmlns:xcal="http://docs.oasis-
  open.org/ns/ws-calendar/201103" xmlns:xs="http://www.w3.org/2001/XMLSchema-
  instance">
  <xcal:properties>
    <xcal:created>
      <xcal:utc-date-time>20110328</xcal:utc-date-time>
    </xcal:created>
  </xcal:properties>
  <xcal:components>
    <xcal:gluon>
      <xcal:properties>
        <xcal:uid>
          <xcal:text>b375a906-64bc-4573-9971-
045b52e30a56@examples.oasis-open.org</xcal:text>
        </xcal:uid>
        <xcal:related-to>
          <xcal:parameters>
            <xcal:reltype>
              <xcal:text>CHILD</xcal:text>
            </xcal:reltype>
          </xcal:parameters>
          <xcal:uid>cd6de037-1c39-481d-87cf-
8c587df56dfb@examples.oasis-open.org</xcal:uid>
        </xcal:related-to>
        <xcal:dtstart>
          <xcal:parameters>
            <xcal:tzid>
              <xcal:text>America/New_York</xcal:text>
            </xcal:tzid>
          </xcal:parameters>
          <xcal:date-time>20110330T00000000</xcal:date-time>
        </xcal:dtstart>
        <xcal:duration>
          </xcal:duration>
        <xcal:x-wsCalendar-attach>
          <emix:productDescription
xs:type="power:PowerProductDescription">
          <power:unitEnergyPrice>
```

```

3986         <emix:priceAbsolute>
3987
3988     <emix:priceEnumeration>0.111</emix:priceEnumeration>
3989         </emix:priceAbsolute>
3990     <power:wattHours>
3991         <emix:scale>#k</emix:scale>
3992     </power:wattHours>
3993 </power:unitEnergyPrice>
3994 <power:Watts>
3995     <emix:scale>#M</emix:scale>
3996     <power:powerAttributes>
3997         <power:hertz>60</power:hertz>
3998         <power:voltage>220</power:voltage>
3999         <power:ac>true</power:ac>
4000     </power:powerAttributes>
4001 </power:Watts>
4002 <power:serviceLocation>
4003     <power:node>xxNode.IDxx</power:node>
4004 </power:serviceLocation>
4005 </emix:productDescription>
4006 </xcal:x-wsCalendar-attach>
4007 </xcal:properties>
4008 </xcal:gluon>
4009 <xcal:interval>
4010     <xcal:properties>
4011         <xcal:uid>
4012             <xcal:text>cd6de037-1c39-481d-87cf-
4013 8c587df56dfb@examples.oasis-open.org</xcal:text>
4014         </xcal:uid>
4015         <xcal:x-wsCalendar-attach>
4016             <emix:productDescription
4017 xs:type="power:PowerProductDescription">
4018                 <power:unitEnergyPrice>
4019                     <emix:priceAbsolute>
4020
4021 <emix:priceEnumeration>0.71</emix:priceEnumeration>
4022                 </emix:priceAbsolute>
4023                 </power:unitEnergyPrice>
4024             </emix:productDescription>
4025         </xcal:x-wsCalendar-attach>
4026     </xcal:properties>
4027 </xcal:interval>
4028 <xcal:interval>
4029     <xcal:properties>
4030         <xcal:uid>
4031             <xcal:text>78839070-98bc-42c4-b216-
4032 3665efdeaef4@examples.oasis-open.org</xcal:text>
4033         </xcal:uid>
4034         <xcal:related-to>
4035             <xcal:parameters>
4036                 <xcal:reltype>
4037                     </xcal:reltype>
4038             </xcal:parameters>
4039             <xcal:uid>cd6de037-1c39-481d-87cf-
4040 8c587df56dfb@examples.oasis-open.org</xcal:uid>
4041         </xcal:related-to>
4042         <xcal:x-wsCalendar-attach>
4043             <emix:productDescription
4044 xs:type="power:PowerProductDescription">
4045                 <power:unitEnergyPrice>
4046                     <emix:priceAbsolute>
4047
4048 <emix:priceEnumeration>0.21</emix:priceEnumeration>

```

```

4049         </emix:priceAbsolute>
4050     </power:unitEnergyPrice>
4051     </emix:productDescription>
4052     </xcal:x-wsCalendar-attach>
4053 </xcal:properties>
4054 </xcal:interval>
4055 <xcal:interval>
4056     <xcal:properties>
4057         <xcal:uid>
4058             <xcal:text>3fbb3ccb-a38e-43b2-968b-
4059 0117c57a1d24@examples.oasis-open.org</xcal:text>
4060         </xcal:uid>
4061         <xcal:related-to>
4062             <xcal:parameters>
4063                 <xcal:reltype>
4064                     </xcal:reltype>
4065             </xcal:parameters>
4066             <xcal:uid>78839070-98bc-42c4-b216-
4067 3665efdeaef4@examples.oasis-open.org</xcal:uid>
4068         </xcal:related-to>
4069         <xcal:x-wsCalendar-attach>
4070             <emix:productDescription
4071 xs:type="power:PowerProductDescription">
4072                 <power:unitEnergyPrice>
4073                     <emix:priceAbsolute>
4074                         <emix:priceEnumeration>-
4075 0.13</emix:priceEnumeration>
4076                     </emix:priceAbsolute>
4077                 </power:unitEnergyPrice>
4078             </emix:productDescription>
4079         </xcal:x-wsCalendar-attach>
4080     </xcal:properties>
4081 </xcal:interval>
4082 <xcal:interval>
4083     <xcal:properties>
4084         <xcal:uid>
4085             <xcal:text>6a5d23b2-0aa9-4309-b2d3-
4086 b04f630add99@examples.oasis-open.org</xcal:text>
4087         </xcal:uid>
4088         <xcal:related-to>
4089             <xcal:parameters>
4090                 <xcal:reltype>
4091                     </xcal:reltype>
4092             </xcal:parameters>
4093             <xcal:uid>3fbb3ccb-a38e-43b2-968b-
4094 0117c57a1d24@examples.oasis-open.org</xcal:uid>
4095         </xcal:related-to>
4096         <xcal:x-wsCalendar-attach>
4097             <emix:productDescription
4098 xs:type="power:PowerProductDescription">
4099                 <power:unitEnergyPrice>
4100                     <emix:priceAbsolute>
4101 <emix:priceEnumeration>0.15</emix:priceEnumeration>
4102                     </emix:priceAbsolute>
4103                 </power:unitEnergyPrice>
4104             </emix:productDescription>
4105         </xcal:x-wsCalendar-attach>
4106     </xcal:properties>
4107 </xcal:interval>
4108 <xcal:interval>
4109     <xcal:properties>
4110         <xcal:uid>

```

```

4112         <xcal:text>5b0b2104-f2bd-4b7b-819c-
4113 ab970b29f668@examples.oasis-open.org</xcal:text>
4114     </xcal:uid>
4115     <xcal:related-to>
4116         <xcal:parameters>
4117             <xcal:reltype>
4118                 </xcal:reltype>
4119             </xcal:parameters>
4120             <xcal:uid>6a5d23b2-0aa9-4309-b2d3-
4121 b04f630add99@examples.oasis-open.org</xcal:uid>
4122         </xcal:related-to>
4123         <xcal:x-wsCalendar-attach>
4124             <emix:productDescription
4125 xs:type="power:PowerProductDescription">
4126                 <power:unitEnergyPrice>
4127                     <emix:priceAbsolute>
4128
4129 <emix:priceEnumeration>0.70</emix:priceEnumeration>
4130                     </emix:priceAbsolute>
4131                 </power:unitEnergyPrice>
4132             </emix:productDescription>
4133         </xcal:x-wsCalendar-attach>
4134     </xcal:properties>
4135 </xcal:interval>
4136 <xcal:interval>
4137     <xcal:properties>
4138         <xcal:uid>
4139             <xcal:text>0270f6af-56bc-4d9c-a7c2-
4140 bebcfe3bc0ea@examples.oasis-open.org</xcal:text>
4141         </xcal:uid>
4142         <xcal:related-to>
4143             <xcal:parameters>
4144                 <xcal:reltype>
4145                     </xcal:reltype>
4146                 </xcal:parameters>
4147                 <xcal:uid>5b0b2104-f2bd-4b7b-819c-
4148 ab970b29f668@examples.oasis-open.org</xcal:uid>
4149             </xcal:related-to>
4150             <xcal:x-wsCalendar-attach>
4151                 <emix:productDescription
4152 xs:type="power:PowerProductDescription">
4153                     <power:unitEnergyPrice>
4154                         <emix:priceAbsolute>
4155
4156 <emix:priceEnumeration>0.86</emix:priceEnumeration>
4157                         </emix:priceAbsolute>
4158                     </power:unitEnergyPrice>
4159                 </emix:productDescription>
4160             </xcal:x-wsCalendar-attach>
4161         </xcal:properties>
4162     </xcal:interval>
4163 <xcal:interval>
4164     <xcal:properties>
4165         <xcal:uid>
4166             <xcal:text>3c36a01d-1229-4f7f-86dc-
4167 31728bfaba6d@examples.oasis-open.org</xcal:text>
4168         </xcal:uid>
4169         <xcal:related-to>
4170             <xcal:parameters>
4171                 <xcal:reltype>
4172                     </xcal:reltype>
4173             </xcal:parameters>

```

```

4174         <xcal:uid>0270f6af-56bc-4d9c-a7c2-
4175 bebcfe3bc0ea@examples.oasis-open.org</xcal:uid>
4176         </xcal:related-to>
4177         <xcal:x-wsCalendar-attach>
4178         <emix:productDescription
4179 xs:type="power:PowerProductDescription">
4180         <power:unitEnergyPrice>
4181         <emix:priceAbsolute>
4182
4183 <emix:priceEnumeration>0.90</emix:priceEnumeration>
4184         </emix:priceAbsolute>
4185         </power:unitEnergyPrice>
4186         </emix:productDescription>
4187         </xcal:x-wsCalendar-attach>
4188     </xcal:properties>
4189 </xcal:interval>
4190 <xcal:interval>
4191     <xcal:properties>
4192     <xcal:uid>
4193     <xcal:text>0d96802b-bf0f-41e6-8d55-
4194 804598879be0@examples.oasis-open.org</xcal:text>
4195     </xcal:uid>
4196     <xcal:related-to>
4197     <xcal:parameters>
4198     <xcal:reltype>
4199     </xcal:reltype>
4200     </xcal:parameters>
4201     <xcal:uid>3c36a01d-1229-4f7f-86dc-
4202 31728bfaba6d@examples.oasis-open.org</xcal:uid>
4203     </xcal:related-to>
4204     <xcal:x-wsCalendar-attach>
4205     <emix:productDescription
4206 xs:type="power:PowerProductDescription">
4207     <power:unitEnergyPrice>
4208     <emix:priceAbsolute>
4209
4210 <emix:priceEnumeration>1.01</emix:priceEnumeration>
4211         </emix:priceAbsolute>
4212         </power:unitEnergyPrice>
4213         </emix:productDescription>
4214     </xcal:x-wsCalendar-attach>
4215 </xcal:properties>
4216 </xcal:interval>
4217 <xcal:interval>
4218     <xcal:properties>
4219     <xcal:uid>
4220     <xcal:text>a843d8d0-28f8-4a31-a7ee-
4221 25b14c701036@examples.oasis-open.org</xcal:text>
4222     </xcal:uid>
4223     <xcal:related-to>
4224     <xcal:parameters>
4225     <xcal:reltype>
4226     </xcal:reltype>
4227     </xcal:parameters>
4228     <xcal:uid>0d96802b-bf0f-41e6-8d55-
4229 804598879be0@examples.oasis-open.org</xcal:uid>
4230     </xcal:related-to>
4231     <xcal:x-wsCalendar-attach>
4232     <emix:productDescription
4233 xs:type="power:PowerProductDescription">
4234     <power:unitEnergyPrice>
4235     <emix:priceAbsolute>

```

```

4236 <emix:priceEnumeration>1.12</emix:priceEnumeration>
4237     </emix:priceAbsolute>
4238     </power:unitEnergyPrice>
4239     </emix:productDescription>
4240     </xcal:x-wsCalendar-attach>
4241     </xcal:properties>
4242 </xcal:interval>
4243 <xcal:interval>
4244     <xcal:properties>
4245     <xcal:uid>
4246         <xcal:text>2097d7d8-f554-469c-8c92-
4247 9eb8551c086d@examples.oasis-open.org</xcal:text>
4248     </xcal:uid>
4249     <xcal:related-to>
4250     <xcal:parameters>
4251     <xcal:reltype>
4252     </xcal:reltype>
4253     </xcal:parameters>
4254     <xcal:uid>a843d8d0-28f8-4a31-a7ee-
4255 25b14c701036@examples.oasis-open.org</xcal:uid>
4256     </xcal:related-to>
4257     <xcal:x-wsCalendar-attach>
4258     <emix:productDescription
4259 xs:type="power:PowerProductDescription">
4260     <power:unitEnergyPrice>
4261     <emix:priceAbsolute>
4262
4263 <emix:priceEnumeration>1.14</emix:priceEnumeration>
4264     </emix:priceAbsolute>
4265     </power:unitEnergyPrice>
4266     </emix:productDescription>
4267     </xcal:x-wsCalendar-attach>
4268     </xcal:properties>
4269 </xcal:interval>
4270 <xcal:interval>
4271     <xcal:properties>
4272     <xcal:uid>
4273         <xcal:text>f2f630f6-f673-47ae-8a89-
4274 3d2b23f379c6@examples.oasis-open.org</xcal:text>
4275     </xcal:uid>
4276     <xcal:related-to>
4277     <xcal:parameters>
4278     <xcal:reltype>
4279     </xcal:reltype>
4280     </xcal:parameters>
4281     <xcal:uid>2097d7d8-f554-469c-8c92-
4282 9eb8551c086d@examples.oasis-open.org</xcal:uid>
4283     </xcal:related-to>
4284     <xcal:x-wsCalendar-attach>
4285     <emix:productDescription
4286 xs:type="power:PowerProductDescription">
4287     <power:unitEnergyPrice>
4288     <emix:priceAbsolute>
4289
4290 <emix:priceEnumeration>1.15</emix:priceEnumeration>
4291     </emix:priceAbsolute>
4292     </power:unitEnergyPrice>
4293     </emix:productDescription>
4294     </xcal:x-wsCalendar-attach>
4295     </xcal:properties>
4296 </xcal:interval>
4297 <xcal:interval>
4298

```

```

4299         <xcal:properties>
4300             <xcal:uid>
4301                 <xcal:text>1d9ad168-433e-4504-97f5-
4302 05a8df1d1f20@examples.oasis-open.org</xcal:text>
4303             </xcal:uid>
4304             <xcal:related-to>
4305                 <xcal:parameters>
4306                     <xcal:reltype>
4307                         </xcal:reltype>
4308                 </xcal:parameters>
4309                 <xcal:uid>f2f630f6-f673-47ae-8a89-
4310 3d2b23f379c6@examples.oasis-open.org</xcal:uid>
4311             </xcal:related-to>
4312             <xcal:x-wsCalendar-attach>
4313                 <emix:productDescription
4314 xs:type="power:PowerProductDescription">
4315                     <power:unitEnergyPrice>
4316                         <emix:priceAbsolute>
4317
4318 <emix:priceEnumeration>2.74</emix:priceEnumeration>
4319                         </emix:priceAbsolute>
4320                     </power:unitEnergyPrice>
4321                 </emix:productDescription>
4322             </xcal:x-wsCalendar-attach>
4323         </xcal:properties>
4324     </xcal:interval>
4325     <xcal:interval>
4326         <xcal:properties>
4327             <xcal:uid>
4328                 <xcal:text>f65aa213-3176-47e3-88c3-
4329 0f7dbe0ec99e@examples.oasis-open.org</xcal:text>
4330             </xcal:uid>
4331             <xcal:related-to>
4332                 <xcal:parameters>
4333                     <xcal:reltype>
4334                         </xcal:reltype>
4335                 </xcal:parameters>
4336                 <xcal:uid>1d9ad168-433e-4504-97f5-
4337 05a8df1d1f20@examples.oasis-open.org</xcal:uid>
4338             </xcal:related-to>
4339             <xcal:x-wsCalendar-attach>
4340                 <emix:productDescription
4341 xs:type="power:PowerProductDescription">
4342                     <power:unitEnergyPrice>
4343                         <emix:priceAbsolute>
4344
4345 <emix:priceEnumeration>1.25</emix:priceEnumeration>
4346                         </emix:priceAbsolute>
4347                     </power:unitEnergyPrice>
4348                 </emix:productDescription>
4349             </xcal:x-wsCalendar-attach>
4350         </xcal:properties>
4351     </xcal:interval>
4352     <xcal:interval>
4353         <xcal:properties>
4354             <xcal:uid>
4355                 <xcal:text>920c3e26-cea2-4456-84a7-
4356 9f5f369cf491@examples.oasis-open.org</xcal:text>
4357             </xcal:uid>
4358             <xcal:related-to>
4359                 <xcal:parameters>
4360                     <xcal:reltype>
4361                         </xcal:reltype>

```

```

4362         </xcal:parameters>
4363         <xcal:uid>f65aa213-3176-47e3-88c3-
4364 0f7dbe0ec99e@examples.oasis-open.org</xcal:uid>
4365         </xcal:related-to>
4366         <xcal:x-wsCalendar-attach>
4367         <emix:productDescription
4368 xs:type="power:PowerProductDescription">
4369             <power:unitEnergyPrice>
4370                 <emix:priceAbsolute>
4371
4372 <emix:priceEnumeration>1.20</emix:priceEnumeration>
4373                 </emix:priceAbsolute>
4374             </power:unitEnergyPrice>
4375         </emix:productDescription>
4376     </xcal:x-wsCalendar-attach>
4377 </xcal:properties>
4378 </xcal:interval>
4379 <xcal:interval>
4380     <xcal:properties>
4381     <xcal:uid>
4382         <xcal:text>bd51713d-c84c-4a18-b641-
4383 65c37ec2728d@examples.oasis-open.org</xcal:text>
4384     </xcal:uid>
4385     <xcal:related-to>
4386         <xcal:parameters>
4387             <xcal:reltype>
4388                 </xcal:reltype>
4389         </xcal:parameters>
4390         <xcal:uid>920c3e26-cea2-4456-84a7-
4391 9f5f369cf491@examples.oasis-open.org</xcal:uid>
4392     </xcal:related-to>
4393     <xcal:x-wsCalendar-attach>
4394     <emix:productDescription
4395 xs:type="power:PowerProductDescription">
4396         <power:unitEnergyPrice>
4397             <emix:priceAbsolute>
4398
4399 <emix:priceEnumeration>1.29</emix:priceEnumeration>
4400             </emix:priceAbsolute>
4401         </power:unitEnergyPrice>
4402     </emix:productDescription>
4403 </xcal:x-wsCalendar-attach>
4404 </xcal:properties>
4405 </xcal:interval>
4406 <xcal:interval>
4407     <xcal:properties>
4408     <xcal:uid>
4409         <xcal:text>2482a65c-bd0c-4a33-b777-
4410 cf89d637d1b8@examples.oasis-open.org</xcal:text>
4411     </xcal:uid>
4412     <xcal:related-to>
4413         <xcal:parameters>
4414             <xcal:reltype>
4415                 </xcal:reltype>
4416         </xcal:parameters>
4417         <xcal:uid>bd51713d-c84c-4a18-b641-
4418 65c37ec2728d@examples.oasis-open.org</xcal:uid>
4419     </xcal:related-to>
4420     <xcal:x-wsCalendar-attach>
4421     <emix:productDescription
4422 xs:type="power:PowerProductDescription">
4423         <power:unitEnergyPrice>
4424             <emix:priceAbsolute>

```

```

4425
4426 <emix:priceEnumeration>1.31</emix:priceEnumeration>
4427     </emix:priceAbsolute>
4428     </power:unitEnergyPrice>
4429     </emix:productDescription>
4430     </xcal:x-wsCalendar-attach>
4431   </xcal:properties>
4432 </xcal:interval>
4433 <xcal:interval>
4434   <xcal:properties>
4435     <xcal:uid>
4436       <xcal:text>01063041-4d93-46a6-9fd6-
4437 7b4f92a938e0@examples.oasis-open.org</xcal:text>
4438     </xcal:uid>
4439     <xcal:related-to>
4440       <xcal:parameters>
4441         <xcal:reltype>
4442         </xcal:reltype>
4443       </xcal:parameters>
4444       <xcal:uid>2482a65c-bd0c-4a33-b777-
4445 cf89d637d1b8@examples.oasis-open.org</xcal:uid>
4446     </xcal:related-to>
4447     <xcal:x-wsCalendar-attach>
4448       <emix:productDescription
4449 xs:type="power:PowerProductDescription">
4450         <power:unitEnergyPrice>
4451         <emix:priceAbsolute>
4452
4453 <emix:priceEnumeration>1.00</emix:priceEnumeration>
4454     </emix:priceAbsolute>
4455     </power:unitEnergyPrice>
4456     </emix:productDescription>
4457     </xcal:x-wsCalendar-attach>
4458   </xcal:properties>
4459 </xcal:interval>
4460 <xcal:interval>
4461   <xcal:properties>
4462     <xcal:uid>
4463       <xcal:text>2bb61d4e-a3ea-423a-98ef-
4464 395e25b35674@examples.oasis-open.org</xcal:text>
4465     </xcal:uid>
4466     <xcal:related-to>
4467       <xcal:parameters>
4468         <xcal:reltype>
4469         </xcal:reltype>
4470       </xcal:parameters>
4471       <xcal:uid>01063041-4d93-46a6-9fd6-
4472 7b4f92a938e0@examples.oasis-open.org</xcal:uid>
4473     </xcal:related-to>
4474     <xcal:x-wsCalendar-attach>
4475       <emix:productDescription
4476 xs:type="power:PowerProductDescription">
4477         <power:unitEnergyPrice>
4478         <emix:priceAbsolute>
4479
4480 <emix:priceEnumeration>0.99</emix:priceEnumeration>
4481     </emix:priceAbsolute>
4482     </power:unitEnergyPrice>
4483     </emix:productDescription>
4484     </xcal:x-wsCalendar-attach>
4485   </xcal:properties>
4486 </xcal:interval>
4487 <xcal:interval>

```

```

4488         <xcal:properties>
4489             <xcal:uid>
4490                 <xcal:text>b50081d2-d7f8-4ab3-9881-
4491 f730ccfa76b4@examples.oasis-open.org</xcal:text>
4492             </xcal:uid>
4493             <xcal:related-to>
4494                 <xcal:parameters>
4495                     <xcal:reltype>
4496                     </xcal:reltype>
4497                 </xcal:parameters>
4498                 <xcal:uid>2bb61d4e-a3ea-423a-98ef-
4499 395e25b35674@examples.oasis-open.org</xcal:uid>
4500             </xcal:related-to>
4501             <xcal:x-wsCalendar-attach>
4502                 <emix:productDescription
4503 xs:type="power:PowerProductDescription">
4504                     <power:unitEnergyPrice>
4505                         <emix:priceAbsolute>
4506
4507 <emix:priceEnumeration>0.89</emix:priceEnumeration>
4508                         </emix:priceAbsolute>
4509                     </power:unitEnergyPrice>
4510                 </emix:productDescription>
4511             </xcal:x-wsCalendar-attach>
4512         </xcal:properties>
4513     </xcal:interval>
4514     <xcal:interval>
4515         <xcal:properties>
4516             <xcal:uid>
4517                 <xcal:text>49c38d29-e377-4c21-8089-
4518 6fb8919fef2@examples.oasis-open.org</xcal:text>
4519             </xcal:uid>
4520             <xcal:related-to>
4521                 <xcal:parameters>
4522                     <xcal:reltype>
4523                     </xcal:reltype>
4524                 </xcal:parameters>
4525                 <xcal:uid>b50081d2-d7f8-4ab3-9881-
4526 f730ccfa76b4@examples.oasis-open.org</xcal:uid>
4527             </xcal:related-to>
4528             <xcal:x-wsCalendar-attach>
4529                 <emix:productDescription
4530 xs:type="power:PowerProductDescription">
4531                     <power:unitEnergyPrice>
4532                         <emix:priceAbsolute>
4533
4534 <emix:priceEnumeration>0.86</emix:priceEnumeration>
4535                         </emix:priceAbsolute>
4536                     </power:unitEnergyPrice>
4537                 </emix:productDescription>
4538             </xcal:x-wsCalendar-attach>
4539         </xcal:properties>
4540     </xcal:interval>
4541     <xcal:interval>
4542         <xcal:properties>
4543             <xcal:uid>
4544                 <xcal:text>22ed71e5-7ab2-4fae-ac7a-
4545 f02f7496b391@examples.oasis-open.org</xcal:text>
4546             </xcal:uid>
4547             <xcal:related-to>
4548                 <xcal:parameters>
4549                     <xcal:reltype>
4550                     </xcal:reltype>

```

```

4551         </xcal:parameters>
4552         <xcal:uid>49c38d29-e377-4c21-8089-
4553 6fb8919fefd2@examples.oasis-open.org</xcal:uid>
4554         </xcal:related-to>
4555         <xcal:x-wsCalendar-attach>
4556         <emix:productDescription
4557 xs:type="power:PowerProductDescription">
4558             <power:unitEnergyPrice>
4559                 <emix:priceAbsolute>
4560
4561 <emix:priceEnumeration>0.79</emix:priceEnumeration>
4562             </emix:priceAbsolute>
4563             </power:unitEnergyPrice>
4564         </emix:productDescription>
4565         </xcal:x-wsCalendar-attach>
4566     </xcal:properties>
4567 </xcal:interval>
4568 <xcal:interval>
4569     <xcal:properties>
4570         <xcal:uid>
4571             <xcal:text>60cc5194-9c26-4ee8-a75f-
4572 02d476e1361d@examples.oasis-open.org</xcal:text>
4573         </xcal:uid>
4574         <xcal:related-to>
4575             <xcal:parameters>
4576                 <xcal:reltype>
4577                 </xcal:reltype>
4578             </xcal:parameters>
4579             <xcal:uid>22ed71e5-7ab2-4fae-ac7a-
4580 f02f7496b391@examples.oasis-open.org</xcal:uid>
4581         </xcal:related-to>
4582         <xcal:x-wsCalendar-attach>
4583         <emix:productDescription
4584 xs:type="power:PowerProductDescription">
4585             <power:unitEnergyPrice>
4586                 <emix:priceAbsolute>
4587
4588 <emix:priceEnumeration>0.88</emix:priceEnumeration>
4589             </emix:priceAbsolute>
4590             </power:unitEnergyPrice>
4591         </emix:productDescription>
4592         </xcal:x-wsCalendar-attach>
4593     </xcal:properties>
4594 </xcal:interval>
4595 <xcal:interval>
4596     <xcal:properties>
4597         <xcal:uid>
4598             <xcal:text>3d0b45e4-382b-4964-8779-
4599 1b7b8c3d7133@examples.oasis-open.org</xcal:text>
4600         </xcal:uid>
4601         <xcal:related-to>
4602             <xcal:parameters>
4603                 <xcal:reltype>
4604                 </xcal:reltype>
4605             </xcal:parameters>
4606             <xcal:uid>60cc5194-9c26-4ee8-a75f-
4607 02d476e1361d@examples.oasis-open.org</xcal:uid>
4608         </xcal:related-to>
4609         <xcal:x-wsCalendar-attach>
4610         <emix:productDescription
4611 xs:type="power:PowerProductDescription">
4612             <power:unitEnergyPrice>
4613                 <emix:priceAbsolute>

```

```

4614 <emix:priceEnumeration>0.87</emix:priceEnumeration>
4615     </emix:priceAbsolute>
4616     </power:unitEnergyPrice>
4617     </emix:productDescription>
4618     </xcal:x-wsCalendar-attach>
4619     </xcal:properties>
4620   </xcal:interval>
4621   <xcal:interval>
4622     <xcal:properties>
4623       <xcal:uid>
4624         <xcal:text>9e89696d-6511-427b-9086-
4625 b595ef25f23c@examples.oasis-open.org</xcal:text>
4626       </xcal:uid>
4627       <xcal:related-to>
4628         <xcal:parameters>
4629           <xcal:reltype>
4630             </xcal:reltype>
4631           </xcal:parameters>
4632           <xcal:uid>3d0b45e4-382b-4964-8779-
4633 1b7b8c3d7133@examples.oasis-open.org</xcal:uid>
4634         </xcal:related-to>
4635         <xcal:x-wsCalendar-attach>
4636           <emix:productDescription
4637 xs:type="power:PowerProductDescription">
4638             <power:unitEnergyPrice>
4639               <emix:priceAbsolute>
4640                 <emix:priceEnumeration>0.76</emix:priceEnumeration>
4641                 </emix:priceAbsolute>
4642                 </power:unitEnergyPrice>
4643                 </emix:productDescription>
4644                 </xcal:x-wsCalendar-attach>
4645               </xcal:properties>
4646             </xcal:interval>
4647           </xcal:components>
4648           <emix:currency>USD</emix:currency>
4649           <emix:marketContext>market.context@examples.com</emix:marketContext>
4650           <emix:transactiveState>Tender</emix:transactiveState>
4651         </emix:product>
4652       </emix:product>
4653     </emix:product>

```

4654

## H. Revision History

4655

Revision	Date	Editor	Changes Made
WD01	2009-12-08	Toby Considine	Initial Draft from templates and outline
WD02	2010-01-12	William Cox	Inserted information model details from TC discussions
WD03	2010-03-10	William Cox	Change to envelope and certificate metaphor. Changes in mandatory and optional definitions.
WD04	2010-03-24	William Cox	Updates based on TC comments and corrections. Additional open issues in TC agenda.
WD05	2010-05-18	Toby Considine	Aligned elements with current draft if WS-Calendar, cleaned up some language to align with the last two months of conversation. Extended envelop and intrinsic/extrinsic language
WD06	2010-05-21	Toby Considine	Began incorporating TeMIX language. Changed Certificates to Warrants. Fleshed out Energy Artifacts
WD07	2010-07-07	Toby Considine	Incorporated Aaron Snyder's extensive re-write into Power & Energy section
WD08	2010-08-10	Toby Considine	Extensive re-write for narrative quality, responded to first 52 comments, Updated to include WS-Calendar WD08 language, added tables of table, examples
WD09	2010-08-18	Toby Considine	Incorporated recent WS-Calendar changes to update Products. Added explanation of WS-Calendar. Cleaned up double entry of Partitions.
WD10	2010-08-30	Toby Considine	Reduced argumentation in intro, excluded WS-Calendar re-writes, pointed to WS-Calendar appendices. Merged AC and DC
WD11	2010-09-05	Toby Considine	Distinguished between Intrinsic elements and Generic Product, incorporated inheritance language into GP, Re-created T&D as a much smaller Transport Artifact, changed envelope language to face and contents.
WD12	2010-10-26	Toby Considine	Responded to many Jira comments. Re-created T&D as a much smaller Transport Artifact, changed envelope language to face and contents. Responded to many Jira comments. Descriptions now based on WD12

Revision	Date	Editor	Changes Made
			Schema.
WD13	2010-11-01	Toby Considine Ed Cazalet Dave Holmberg	Removed repetitive discussion of WS-Calendar objects. Reflect new use of WS-Calendar Sequence in Schema. Recast Options to describe reserves.
WD14	2010-11-09	Toby Considine Ed Cazalet	Changes to resources, block power, misc. tightening of document
WD15	2010-11-14	Toby Considine Ed Cazalet Sean Crimmins	EMIX Sequence changed to EMIX Base. General tightening. Addition of Load and Power Offers, including 3-part bids for each.
CSD01	2010-11-15	Toby Considine	Minor changes as per comments
WD16	2011-01-15	Toby Considine	46 Minor issues from PR01 Adopted new WD format Moved namespaces into section 1 Adjusted duplicate table names Fixed section numbering anomalies
WD17	2011-02-08	Toby Considine	Issue Resolution. See Release Notes from Jira
WD18	2011-03-07	Toby Considine	Numerous Jira Issues, (see release notes), Significant Schema work: Resources as discussed, General EMIX constraints and requirements now in Core EMIX namespace, but isolated in requirements.xsd. Added schedule constraints as optional constraint
WD19	2011-03-17	Toby Considine	Tightened language, some egregious errors and references not found removed
WD20	2011-03022	Toby Considine	Simplified Tables, Added NAESB appendix, updated schemas in appendix
WD21	2011-0323	Toby Considine	Quick Pass for show-stoppers, Purged last 16 uses of EMIXTerms for EMIX Base,
WD22	2011-0329	Toby Considine	Minor edits and comments from Jira. Made explicit relations between Base, Product Description, Items, Interfaces, and all derived extensions
WD23	2011-0411	Toby Considine	Extensive review and re-write to consolidate changes as logged in Jira

4656